40 BEST MACHINE CODE ROUTINES FOR THE COMMODORE 64

Mark Greenshields

40 Best Machine Code Routines for the 64

Mark Greenshields

Duckworth

First published in 1984 by
Gerald Duckworth & Co. Ltd.
The Old Piano Factory
43 Gloucester Crescent, London NW1

ISBN 0 7156 1899 7

British Library Cataloguing in Publication Data
Greenshields, Mark
Forty best machine codes for the 64
1. Commodore 64 (Computer) 2.Machine codes (Electronic codes)
I. Title
001.64'25 QA76.8.C64

ISBN 0-7156-1899-7

Typeset by The Electronic Village, Richmond
from text stored on a Commodore 64
Printed in Great Britain by
Redwood Burn Ltd., Trowbridge
and bound by Pegasus Bookbinding, Melksham

Contents

Preface

This book is not intended to teach you machine code on the CBM 64. It contains 40 machine code routines that can be used in your Basic or machine code programs to do things that are not implemented in the standard BASIC or operating system in your Commodore 64.

The book includes a listing of Supermon which is a public domain assembler/disassembler written by Jim Butterfield (thanks Jim). It can be used to enter the programs in this book if you do not possess an assembler. The listings are all given twice: once in an assembled listing from the PAL assembler from Proline Software (this, along with POWER, is the best machine code development package that I have seen), and once in a disassembled version suitable for entering with Supermon or similar.

I hope that you find the book useful and that the routines help to improve your programs.

Acknowledgments

I would like to thank my parents Jack and Sheila Greenshields, my sister Louise, Graeme Douglas, William Drummond, Mark Kelly and all my relations for their encouragement.

M.G.

I would like to dedicate this book to my grandparents, Roy and Gracie Reid.

Supermon

There follows a listing of Supermon which is a public domain assembler/disassembler/monitor. Thanks to Jim Butterfield for this program. The Basic program which follows is used to enter this assembler. You will need this assembler or a similar one to enter all the programs in this book.

Supermon is listed as a hex dump, which is a listing of hexadecimal numbers. This makes it easy to enter into a Basic loader program.

To enter Supermon, type in the following commands in direct mode (where <return> means press the return key), and then type in the Basic loader and save it.

```
POKE 43,1 <return>
POKE 44,32 <return>
POKE8192,0 <return>
NEW <return>
```

Now run the loader and you will see the prompt:

```
.0800 ?
```

You will see that the first number corresponds with the first number in the Supermon listing. This is where you type the data. The first three lines that you would type are as follows. Type the program in without spaces.

```
.0800 ? 001A086400992293
.0808 ? 121D1D1D1D535550
.0810 ? 45522036342D4D4F
```

Don't worry if you don't understand what you are typing in. Just type exactly what is printed and it will work. It is worth it as writing machine code using an assembler is far easier than doing

it by hand. Once you have finished typing in the program you will be prompted with:

SAVE TO TAPE OR DISK ?

Press T if you are using cassette and have a blank cassette in the recorder. Press D if you are using disk and make sure that a formatted disk with at least 11 blocks free is in the drive.

If you pressed T you will be prompted with PRESS PLAY ON TAPE and if you pressed D the drive will start whirring. The program is now being saved to tape or disk. If an error occurs then typing RUN100 will allow you to save the program again. It can be loaded in the normal way.

LOAD"SUPERMON",1 OR LOAD"SUPERMON",8

Then run the program. Some writing will appear on the screen and a '.' prompt will appear.

To make spare copies of Supermon just load the program and save it as if it was Basic.

Supermon is given here as a relocatable loader: it can be located anywhere in RAM. To adjust where it is to be located in memory, find the starting address and add 2065 to it. Use the following formula to calculate the two numbers necessary:

LO = INT(number/256)
HI = ((number/256)-LO)*256

Now POKE 55 with the value of LO and POKE 56 with the value of HI and run Supermon.

To restart Supermon, type SYS starting address + 1. The normal value to start Supermon is SYS 38893.

Instructions for using Supermon

Supermon commands are all one-letter commands usually

followed by parameters.

The first command that we will look at is 'A'. This stands for ASSEMBLE and is the most frequently used command in any assembler. It will be used for entering almost all the programs in this book. The syntax for 'A' is as follows:

A (start address in hex) (mnemonic) (operand).

e.g. A 1000 LDA #$10

The address is the starting address in hex. The mnemonic is the assembly language command and the operand is the number associated with the command if there is one.

After you press return from the first line, if it is incorrect syntax, the computer will prompt you with an 'A' and the next address. Therefore you need only enter the starting address, the assembler does the rest. To leave the assembly press the return key.

Here is a simple example program which shows you how the assembler works.

```
.A 1000 LDA #$00
.A 1002 STA $D020
.A 1005 STA $D021
.A 1008 RTS
```

This program makes the screen and the border black. Type it in to see how to use the assembler. If you make an error the computer will print a question mark. If this happens use the normal screen editor and change the mistake and delete the question mark. Press return and if the next address is prompted then the line is now correct.

Now that you have typed this in, you may want to save the program. The command to do this is 'S'. The syntax is as follows:

S"name",device,start,end + 1

The total length of the name must not exceed 16 or a question

mark will be printed. The device is the device that the computer is to save to: 01 is tape and 08 is disk. The 0's before the number are essential for correct syntax. The start is the starting address in hex of the save. The end + 1 is the end address plus 1 that the computer is to save to. The reason that you must save up to the end + 1 is that the ROM routine used to save to memory saves up to but not including the end address specified. All the parameters must be separated by a comma.

The next command is the command to execute a program in machine code from the assembler. It is 'G' and has the syntax:

G address to start at.

If you want to return control to the monitor when the program has been run then make the last command of the program a BRK command instead of an RTS.

The next command allows you to see a program in memory. It is 'D' and has the syntax:

D start

e.g. D 1000

This command clears the screen and prints a page of commands. To see more press D and return.

The next command is the same as 'D' except that it prints a continuous listing without clearing the screen. The command is 'P' and it has the syntax:

P start end

It is mainly used when you want a printer listing. To print a disassembly to the printer type the following in Basic:

OPEN4,4 : CMD4 : SYS38893

(The SYS assumes that the monitor is at its default position in memory. If it isn't, use your address.)

The printer will print something and then you can type what you want. You can use 'P' or 'M' (coming up next). To disable the printer when it has finished type 'X' <return> (explained later) and type CLOSE4. <return>.

Often you will want a listing of memory in hex (which Supermon was listed in). This is done with the 'M' command which has the syntax:

M start end

where start and end are in hex. This command may also be used to the printer. You may also change memory by using this command and then typing over values and pressing return at the end of each line.

The monitor has a command to fill areas of memory with a number. It is 'F' and it has the syntax:

F start end byte

where start and end are addresses in hex and byte is a byte in hex.

Supermon can move parts of memory to another part. The command is 'T' which stands for transfer memory. It has the syntax:

T oldstart oldend newstart

where oldstart, oldend and newstart are addresses in hex.

If you want to find the contents of the registers at any time, type the command 'R' on its own.

If you are working in the assembler and you want to load a program into memory where it came from, there are two ways to do this:

1. return to Basic and type LOAD"name",device,1

e.g. To load the file hello from tape type LOAD"HELLO",1,1

2. use the command 'L' in the monitor. It has the syntax:

L"name",device

where device is 01 for tape and 08 for disk.

To exit the assembler and return to Basic type X <return> or press run/stop and restore.

Summary of SUPERMON commands.

Command Syntax	Meaning
A Assemble Mnemonics into memory	A 1000 LDA #$10
D Disassemble memory	D 1000
M Display hex from memory	M 1000 2000
S Save memory to device	S"name",08,1000,2000
L Load memory from device	L"name",01
P Print disassembly of memory	P 1000 2000
F Fill memory	F 3000 4000 FF
T Transfer memory to memory	T 1000 2000 C000
X Exit to Basic	X
R Register display	R
G Goto address	G FFD2

```
1 HE$="0123456789ABCDEF"
10 PRINT"{CLR}"
20 FORA=2049TO4587STEP8
30 GOSUB1000:REM CONVERT ADDRESS TO HEX
IN H$
40 PRINT".";H$;:INPUT A$:REM 8 HEX NUMBE
RS
50 FORX=1TO16STEP2
```

```
60 B$=MID$(A$,X,2)
70 GOSUB2000:REM CONVERT HEX NO. TO DECI
MAL
80 POKEA+X/2,HEX
90 NEXT:NEXT
100 INPUT"SAVE TO TAPE OR DISK";TD$
110 IFTD$="D"ORTD$="T"THEN120
115 GOTO100
120 IFTD$="D"THENDEV=8
130 IFTD$="T"THENDEV=1
140 FORA=0TO34:READB:POKEA+49152,B:NEXT:
POKE49153,DEV:INPUT"ARE YOU SURE";S$
150 IFS$="N"THEN100
160 SYS49152: REM SAVE ASSEMBLER
170 PRINT"MACHINE CODE SAVED"
180 PRINT"IT MAY BE LOADED FROM TAPE OR
DISK IN THE NORMAL WAY LIKE A BASIC"
190 PRINT"PROGRAM AND THEN RUN"
200 END
1000 N1=INT(A/4096):N6=(A/4096-N1)*16:N2
=INT(N6):N3=INT((N6-N2)*16)
1010 N4=(((N6-N2)*16)-N3)*16
1030 H$=MID$(HE$,N1+1,1)+MID$(HE$,N2+1,1
)+MID$(HE$,N3+1,1)+MID$(HE$,N4+1,1)
1040 RETURN
2000 FORV=1TO16:B=V-1:IFLEFT$(B$,1)=MID$
(HE$,V,1)THEN2020
2010 NEXT
2020 HEX=B*16
2030 FORV=1TO16:B=V-1:IFRIGHT$(B$,1)=MID
$(HE$,V,1)THEN2050
2040 NEXT
2050 HEX=HEX+B
2060 PRINT HEX
2070 RETURN
10000 DATA 162,1,160,1,32,186,255,162,26
,160,192,169,8,32,189,255,162,236,160
10010 DATA 17,169,251,32,216,255,96,83,8
5,80,69,82,77,79,78,0
20000 OPEN15,8,15:INPUT#15,A$,B$,C$,D$:P
RINTA$,B$,C$,D$:CLOSE15
```

```
B*
   PC   SR AC XR YR SP
.;97FE 33 00 28 00 F6
.
.:0800 00 1A 08 64 00 99 22 93
.:0808 12 1D 1D 1D 1D 53 55 50
.:0810 45 52 20 36 34 2D 4D 4F
.:0818 4E 00 31 08 6E 00 99 22
.:0820 11 20 20 20 20 20 20 20
.:0828 20 20 20 20 20 20 20 20
.:0830 00 4B 08 78 00 99 22 11
.:0838 20 2E 2E 4A 49 4D 20 42
.:0840 55 54 54 45 52 46 49 45
.:0848 4C 44 00 66 08 82 00 9E
.:0850 28 C2 28 34 33 29 AA 32
.:0858 35 36 AC C2 28 34 34 29
.:0860 AA 31 32 37 29 00 00 00
.:0868 AA AA AA AA AA AA AA AA
.:0870 AA AA AA AA AA AA AA AA
.:0878 AA AA AA AA AA AA AA AA
.:0880 A5 2D 85 22 A5 2E 85 23
.:0888 A5 37 85 24 A5 38 85 25
.:0890 A0 00 A5 22 D0 02 C6 23
.:0898 C6 22 B1 22 D0 3C A5 22
.:08A0 D0 02 C6 23 C6 22 B1 22
.:08A8 F0 21 85 26 A5 22 D0 02
.:08B0 C6 23 C6 22 B1 22 18 65
.:08B8 24 AA A5 26 65 25 48 A5
.:08C0 37 D0 02 C6 38 C6 37 68
.:08C8 91 37 8A 48 A5 37 D0 02
.:08D0 C6 38 C6 37 68 91 37 18
.:08D8 90 B6 C9 4F D0 ED A5 37
.:08E0 85 33 A5 38 85 34 6C 37
.:08E8 00 4F 4F 4F 4F AD E6 FF
.:08F0 00 8D 16 03 AD E7 FF 00
.:08F8 8D 17 03 A9 80 20 90 FF
.:0900 00 00 D8 68 8D 3E 02 68
.:0908 8D 3D 02 68 8D 3C 02 68
.:0910 8D 3B 02 68 AA 68 A8 38
.:0918 8A E9 02 8D 3A 02 98 E9
.:0920 00 00 8D 39 02 BA 8E 3F
```

```
.:0928 Ø2 2Ø 57 FD ØØ A2 42 A9
.:0930 2A 2Ø 57 FA ØØ A9 52 DØ
.:0938 34 E6 C1 DØ Ø6 E6 C2 DØ
.:0940 Ø2 E6 26 6Ø 2Ø CF FF C9
.:0948 ØD DØ F8 68 68 EA EA EA
.:0950 EA EA A9 ØØ ØØ 85 26 A2
.:0958 ØD A9 2E 2Ø 57 FA ØØ EA
.:0960 EA EA EA EA 2Ø 3E F8 ØØ
.:0968 C9 2E FØ F9 C9 2Ø FØ F5
.:0970 A2 ØE DD B7 FF ØØ DØ ØC
.:0978 8A ØA AA BD C7 FF ØØ 48
.:0980 BD C6 FF ØØ 48 6Ø CA 1Ø
.:0988 EC 4C ED FA ØØ A5 C1 8D
.:0990 3A Ø2 A5 C2 8D 39 Ø2 6Ø
.:0998 A9 Ø8 85 1D AØ ØØ ØØ 2Ø
.:09A0 54 FD ØØ B1 C1 2Ø 48 FA
.:09A8 ØØ 2Ø 33 F8 ØØ C6 1D DØ
.:09B0 F1 6Ø 2Ø 88 FA ØØ 9Ø ØB
.:09B8 A2 ØØ ØØ 81 C1 C1 C1 FØ
.:09C0 Ø3 4C ED FA ØØ 2Ø 33 F8
.:09C8 ØØ C6 1D 6Ø A9 3B 85 C1
.:09D0 A9 Ø2 85 C2 A9 Ø5 6Ø 98
.:09D8 48 2Ø 57 FD ØØ 68 A2 2E
.:09E0 4C 57 FA ØØ EA EA EA EA
.:09E8 EA A2 ØØ ØØ BD EA FF ØØ
.:09F0 2Ø D2 FF E8 EØ 16 DØ F5
.:09F8 AØ 3B 2Ø C2 F8 ØØ AD 39
.:0A00 Ø2 2Ø 48 FA ØØ AD 3A Ø2
.:0A08 2Ø 48 FA ØØ 2Ø B7 F8 ØØ
.:0A10 2Ø 8D F8 ØØ FØ 5C 2Ø 3E
.:0A18 F8 ØØ 2Ø 79 FA ØØ 9Ø 33
.:0A20 2Ø 69 FA ØØ 2Ø 3E F8 ØØ
.:0A28 2Ø 79 FA ØØ 9Ø 28 2Ø 69
.:0A30 FA ØØ EA EA EA EA EA 2Ø
.:0A38 E1 FF FØ 3C A6 26 DØ 38
.:0A40 A5 C3 C5 C1 A5 C4 E5 C2
.:0A48 9Ø 2E AØ 3A 2Ø C2 F8 ØØ
.:0A50 2Ø 41 FA ØØ 2Ø 8B F8 ØØ
.:0A58 FØ EØ 4C ED FA ØØ 2Ø 79
.:0A60 FA ØØ 9Ø Ø3 2Ø 8Ø F8 ØØ
.:0A68 2Ø B7 F8 ØØ DØ Ø7 2Ø 79
```

```
.:0A70 FA 00 90 EB A9 08 85 1D
.:0A78 20 3E F8 00 20 A1 F8 00
.:0A80 D0 F8 4C 47 F8 00 20 CF
.:0A88 FF C9 0D F0 0C C9 20 D0
.:0A90 D1 20 79 FA 00 90 03 20
.:0A98 80 F8 00 EA EA EA EA EA
.:0AA0 AE 3F 02 9A 78 AD 39 02
.:0AA8 48 AD 3A 02 48 AD 3B 02
.:0AB0 48 AD 3C 02 AE 3D 02 AC
.:0AB8 3E 02 40 EA EA EA EA EA
.:0AC0 AE 3F 02 9A 6C 02 A0 A0
.:0AC8 01 84 BA 84 B9 88 84 B7
.:0AD0 84 90 84 93 A9 40 85 BB
.:0AD8 A9 02 85 BC 20 CF FF C9
.:0AE0 20 F0 F9 C9 0D F0 38 C9
.:0AE8 22 D0 14 20 CF FF C9 22
.:0AF0 F0 10 C9 0D F0 29 91 BB
.:0AF8 E6 B7 C8 C0 10 D0 EC 4C
.:0B00 ED FA 00 20 CF FF C9 0D
.:0B08 F0 16 C9 2C D0 DC 20 88
.:0B10 FA 00 29 0F F0 E9 C9 03
.:0B18 F0 E5 85 BA 20 CF FF C9
.:0B20 0D 60 6C 30 03 6C 32 03
.:0B28 20 96 F9 00 D0 D4 EA EA
.:0B30 EA EA EA A9 00 00 20 EF
.:0B38 F9 00 A5 90 29 10 D0 C4
.:0B40 4C 47 F8 00 20 96 F9 00
.:0B48 C9 2C D0 BA 20 79 FA 00
.:0B50 20 69 FA 00 20 CF FF C9
.:0B58 2C D0 AD 20 79 FA 00 A5
.:0B60 C1 85 AE A5 C2 85 AF 20
.:0B68 69 FA 00 20 CF FF C9 0D
.:0B70 D0 98 EA EA EA EA EA 20
.:0B78 F2 F9 00 4C 47 F8 00 A5
.:0B80 C2 20 48 FA 00 A5 C1 48
.:0B88 4A 4A 4A 4A 20 60 FA 00
.:0B90 AA 68 29 0F 20 60 FA 00
.:0B98 48 8A 20 D2 FF 68 4C D2
.:0BA0 FF 09 30 C9 3A 90 02 69
.:0BA8 06 60 A2 02 B5 C0 48 B5
.:0BB0 C2 95 C0 68 95 C2 CA D0
```

```
.:ØBB8 F3 6Ø 2Ø 88 FA ØØ 9Ø Ø2
.:ØBCØ 85 C2 2Ø 88 FA ØØ 9Ø Ø2
.:ØBC8 85 C1 6Ø A9 ØØ ØØ 85 2A
.:ØBDØ 2Ø 3E F8 ØØ C9 2Ø DØ Ø9
.:ØBD8 2Ø 3E F8 ØØ C9 2Ø DØ ØE
.:ØBEØ 18 6Ø 2Ø AF FA ØØ ØA ØA
.:ØBE8 ØA ØA 85 2A 2Ø 3E F8 ØØ
.:ØBFØ 2Ø AF FA ØØ Ø5 2A 38 6Ø
.:ØBF8 C9 3A 9Ø Ø2 69 Ø8 29 ØF
.:ØCØØ 6Ø A2 Ø2 2C A2 ØØ ØØ B4
.:ØCØ8 C1 DØ Ø8 B4 C2 DØ Ø2 E6
.:ØC1Ø 26 D6 C2 D6 C1 6Ø 2Ø 3E
.:ØC18 F8 ØØ C9 2Ø FØ F9 6Ø A9
.:ØC2Ø ØØ ØØ 8D ØØ ØØ Ø1 2Ø CC
.:ØC28 FA ØØ 2Ø 8F FA ØØ 2Ø 7C
.:ØC3Ø FA ØØ 9Ø Ø9 6Ø 2Ø 3E F8
.:ØC38 ØØ 2Ø 79 FA ØØ BØ DE AE
.:ØC4Ø 3F Ø2 9A EA EA EA EA EA
.:ØC48 A9 3F 2Ø D2 FF 4C 47 F8
.:ØC5Ø ØØ 2Ø 54 FD ØØ CA DØ FA
.:ØC58 6Ø E6 C3 DØ Ø2 E6 C4 6Ø
.:ØC6Ø A2 Ø2 B5 CØ 48 B5 27 95
.:ØC68 CØ 68 95 27 CA DØ F3 6Ø
.:ØC7Ø A5 C3 A4 C4 38 E9 Ø2 BØ
.:ØC78 ØE 88 9Ø ØB A5 28 A4 29
.:ØC8Ø 4C 33 FB ØØ A5 C3 A4 C4
.:ØC88 38 E5 C1 85 1E 98 E5 C2
.:ØC9Ø A8 Ø5 1E 6Ø 2Ø D4 FA ØØ
.:ØC98 2Ø 69 FA ØØ 2Ø E5 FA ØØ
.:ØCAØ 2Ø ØC FB ØØ 2Ø E5 FA ØØ
.:ØCA8 2Ø 2F FB ØØ 2Ø 69 FA ØØ
.:ØCBØ 9Ø 15 A6 26 DØ 64 2Ø 28
.:ØCB8 FB ØØ 9Ø 5F A1 C1 81 C3
.:ØCCØ 2Ø Ø5 FB ØØ 2Ø 33 F8 ØØ
.:ØCC8 DØ EB 2Ø 28 FB ØØ 18 A5
.:ØCDØ 1E 65 C3 85 C3 98 65 C4
.:ØCD8 85 C4 2Ø ØC FB ØØ A6 26
.:ØCEØ DØ 3D A1 C1 81 C3 2Ø 28
.:ØCE8 FB ØØ BØ 34 2Ø B8 FA ØØ
.:ØCFØ 2Ø BB FA ØØ 4C 7D FB ØØ
.:ØCF8 2Ø D4 FA ØØ 2Ø 69 FA ØØ
```

```
.:ØDØØ 2Ø E5 FA ØØ 2Ø 69 FA ØØ
.:ØD08 2Ø 3E F8 ØØ 2Ø 88 FA ØØ
.:ØD1Ø 9Ø 14 85 1D A6 26 DØ 11
.:ØD18 2Ø 2F FB ØØ 9Ø ØC A5 1D
.:ØD2Ø 81 C1 2Ø 33 F8 ØØ DØ EE
.:ØD28 4C ED FA ØØ 4C 47 F8 ØØ
.:ØD3Ø 2Ø D4 FA ØØ 2Ø 69 FA ØØ
.:ØD38 2Ø E5 FA ØØ 2Ø 69 FA ØØ
.:ØD4Ø 2Ø 3E F8 ØØ A2 ØØ ØØ 2Ø
.:ØD48 3E F8 ØØ C9 27 DØ 14 2Ø
.:ØD5Ø 3E F8 ØØ 9D 1Ø Ø2 E8 2Ø
.:ØD58 CF FF C9 ØD FØ 22 EØ 2Ø
.:ØD6Ø DØ F1 FØ 1C 8E ØØ ØØ Ø1
.:ØD68 2Ø 8F FA ØØ 9Ø C6 9D 1Ø
.:ØD7Ø Ø2 E8 2Ø CF FF C9 ØD FØ
.:ØD78 Ø9 2Ø 88 FA ØØ 9Ø B6 EØ
.:ØD8Ø 2Ø DØ EC 86 1C EA EA EA
.:ØD88 EA EA 2Ø 57 FD ØØ A2 ØØ
.:ØD9Ø ØØ AØ ØØ ØØ B1 C1 DD 1Ø
.:ØD98 Ø2 DØ ØC C8 E8 E4 1C DØ
.:ØDAØ F3 2Ø 41 FA ØØ 2Ø 54 FD
.:ØDA8 ØØ 2Ø 33 F8 ØØ A6 26 DØ
.:ØDBØ 8D 2Ø 2F FB ØØ BØ DD 4C
.:ØDB8 47 F8 ØØ 2Ø D4 FA ØØ 85
.:ØDCØ 2Ø A5 C2 85 21 A2 ØØ ØØ
.:ØDC8 86 28 A9 93 2Ø D2 FF EA
.:ØDDØ EA EA EA EA A9 16 85 1D
.:ØDD8 2Ø 6A FC ØØ 2Ø CA FC ØØ
.:ØDEØ 85 C1 84 C2 C6 1D DØ F2
.:ØDE8 A9 91 2Ø D2 FF 4C 47 F8
.:ØDFØ ØØ AØ 2C 2Ø C2 F8 ØØ 2Ø
.:ØDF8 54 FD ØØ 2Ø 41 FA ØØ 2Ø
.:ØEØØ 54 FD ØØ A2 ØØ ØØ A1 C1
.:ØE08 2Ø D9 FC ØØ 48 2Ø 1F FD
.:ØE1Ø ØØ 68 2Ø 35 FD ØØ A2 Ø6
.:ØE18 EØ Ø3 DØ 12 A4 1F FØ ØE
.:ØE2Ø A5 2A C9 E8 B1 C1 BØ 1C
.:ØE28 2Ø C2 FC ØØ 88 DØ F2 Ø6
.:ØE3Ø 2A 9Ø ØE BD 2A FF ØØ 2Ø
.:ØE38 A5 FD ØØ BD 3Ø FF ØØ FØ
.:ØE4Ø Ø3 2Ø A5 FD ØØ CA DØ D5
```

```
.:ØE48 6Ø 2Ø CD FC ØØ AA E8 DØ
.:ØE5Ø Ø1 C8 98 2Ø C2 FC ØØ 8A
.:ØE58 86 1C 2Ø 48 FA ØØ A6 1C
.:ØE6Ø 6Ø A5 1F 38 A4 C2 AA 1Ø
.:ØE68 Ø1 88 65 C1 9Ø Ø1 C8 6Ø
.:ØE7Ø A8 4A 9Ø ØB 4A BØ 17 C9
.:ØE78 22 FØ 13 29 Ø7 Ø9 8Ø 4A
.:ØE8Ø AA BD D9 FE ØØ BØ Ø4 4A
.:ØE88 4A 4A 4A 29 ØF DØ Ø4 AØ
.:ØE9Ø 8Ø A9 ØØ ØØ AA BD 1D FF
.:ØE98 ØØ 85 2A 29 Ø3 85 1F 98
.:ØEAØ 29 8F AA 98 AØ Ø3 EØ 8A
.:ØEA8 FØ ØB 4A 9Ø Ø8 4A 4A Ø9
.:ØEBØ 2Ø 88 DØ FA C8 88 DØ F2
.:ØEB8 6Ø B1 C1 2Ø C2 FC ØØ A2
.:ØECØ Ø1 2Ø FE FA ØØ C4 1F C8
.:ØEC8 9Ø F1 A2 Ø3 CØ Ø4 9Ø F2
.:ØEDØ 6Ø A8 B9 37 FF ØØ 85 28
.:ØED8 B9 77 FF ØØ 85 29 A9 ØØ
.:ØEEØ ØØ AØ Ø5 Ø6 29 26 28 2A
.:ØEE8 88 DØ F8 69 3F 2Ø D2 FF
.:ØEFØ CA DØ EC A9 2Ø 2C A9 ØD
.:ØEF8 4C D2 FF 2Ø D4 FA ØØ 2Ø
.:ØF ØØ 69 FA ØØ 2Ø E5 FA ØØ 2Ø
.:ØF Ø8 69 FA ØØ A2 ØØ ØØ 86 28
.:ØF1Ø EA EA EA EA EA 2Ø 57 FD
.:ØF18 ØØ 2Ø 72 FC ØØ 2Ø CA FC
.:ØF2Ø ØØ 85 C1 84 C2 2Ø E1 FF
.:ØF28 FØ Ø5 2Ø 2F FB ØØ BØ E9
.:ØF3Ø 4C 47 F8 ØØ 2Ø D4 FA ØØ
.:ØF38 A9 Ø3 85 1D 2Ø 3E F8 ØØ
.:ØF4Ø 2Ø A1 F8 ØØ DØ F8 A5 2Ø
.:ØF48 85 C1 A5 21 85 C2 4C 46
.:ØF5Ø FC ØØ C5 28 FØ Ø3 2Ø D2
.:ØF58 FF 6Ø 2Ø D4 FA ØØ 2Ø 69
.:ØF6Ø FA ØØ 8E 11 Ø2 A2 Ø3 2Ø
.:ØF68 CC FA ØØ 48 CA DØ F9 A2
.:ØF7Ø Ø3 68 38 E9 3F AØ Ø5 4A
.:ØF78 6E 11 Ø2 6E 1Ø Ø2 88 DØ
.:ØF8Ø F6 CA DØ ED A2 Ø2 2Ø CF
.:ØF88 FF C9 ØD FØ 1E C9 2Ø FØ
```

```
.:ØF9Ø F5 2Ø DØ FE ØØ BØ ØF 2Ø
.:ØF98 9C FA ØØ A4 C1 84 C2 85
.:ØFAØ C1 A9 3Ø 9D 1Ø Ø2 E8 9D
.:ØFA8 1Ø Ø2 E8 DØ DB 86 28 A2
.:ØFBØ ØØ ØØ 86 26 FØ Ø4 E6 26
.:ØFB8 FØ 75 A2 ØØ ØØ 86 1D A5
.:ØFCØ 26 2Ø D9 FC ØØ A6 2A 86
.:ØFC8 29 AA BC 37 FF ØØ BD 77
.:ØFDØ FF ØØ 2Ø B9 FE ØØ DØ E3
.:ØFD8 A2 Ø6 EØ Ø3 DØ 19 A4 1F
.:ØFEØ FØ 15 A5 2A C9 E8 A9 3Ø
.:ØFE8 BØ 21 2Ø BF FE ØØ DØ CC
.:ØFFØ 2Ø C1 FE ØØ DØ C7 88 DØ
.:ØFF8 EB Ø6 2A 9Ø ØB BC 3Ø FF
.:1ØØØ ØØ BD 2A FF ØØ 2Ø B9 FE
.:1ØØ8 ØØ DØ B5 CA DØ D1 FØ ØA
.:1Ø1Ø 2Ø B8 FE ØØ DØ AB 2Ø B8
.:1Ø18 FE ØØ DØ A6 A5 28 C5 1D
.:1Ø2Ø DØ AØ 2Ø 69 FA ØØ A4 1F
.:1Ø28 FØ 28 A5 29 C9 9D DØ 1A
.:1Ø3Ø 2Ø 1C FB ØØ 9Ø ØA 98 DØ
.:1Ø38 Ø4 A5 1E 1Ø ØA 4C ED FA
.:1Ø4Ø ØØ C8 DØ FA A5 1E 1Ø F6
.:1Ø48 A4 1F DØ Ø3 B9 C2 ØØ ØØ
.:1Ø5Ø 91 C1 88 DØ F8 A5 26 91
.:1Ø58 C1 2Ø CA FC ØØ 85 C1 84
.:1Ø6Ø C2 EA EA EA EA EA AØ 41
.:1Ø68 2Ø C2 F8 ØØ 2Ø 54 FD ØØ
.:1Ø7Ø 2Ø 41 FA ØØ 2Ø 54 FD ØØ
.:1Ø78 EA EA EA EA EA 4C BØ FD
.:1Ø8Ø ØØ A8 2Ø BF FE ØØ DØ 11
.:1Ø88 98 FØ ØE 86 1C A6 1D DD
.:1Ø9Ø 1Ø Ø2 Ø8 E8 86 1D A6 1C
.:1Ø98 28 6Ø C9 3Ø 9Ø Ø3 C9 47
.:1ØAØ 6Ø 38 6Ø 4Ø Ø2 45 Ø3 DØ
.:1ØA8 Ø8 4Ø Ø9 3Ø 22 45 33 DØ
.:1ØBØ Ø8 4Ø Ø9 4Ø Ø2 45 33 DØ
.:1ØB8 Ø8 4Ø Ø9 4Ø Ø2 45 B3 DØ
.:1ØCØ Ø8 4Ø Ø9 ØØ ØØ 22 44 33
.:1ØC8 DØ 8C 44 ØØ ØØ 11 22 44
.:1ØDØ 33 DØ 8C 44 9A 1Ø 22 44
```

```
.:10D8 33 D0 08 40 09 10 22 44
.:10E0 33 D0 08 40 09 62 13 78
.:10E8 A9 00 00 21 81 82 00 00
.:10F0 00 00 59 4D 91 92 86 4A
.:10F8 85 9D 2C 29 2C 23 28 24
.:1100 59 00 00 58 24 24 00 00
.:1108 1C 8A 1C 23 5D 8B 1B A1
.:1110 9D 8A 1D 23 9D 8B 1D A1
.:1118 00 00 29 19 AE 69 A8 19
.:1120 23 24 53 1B 23 24 53 19
.:1128 A1 00 00 1A 5B 5B A5 69
.:1130 24 24 AE AE A8 AD 29 00
.:1138 00 7C 00 00 15 9C 6D 9C
.:1140 A5 69 29 53 84 13 34 11
.:1148 A5 69 23 A0 D8 62 5A 48
.:1150 26 62 94 88 54 44 C8 54
.:1158 68 44 E8 94 00 00 B4 08
.:1160 84 74 B4 28 6E 74 F4 CC
.:1168 4A 72 F2 A4 8A 00 00 AA
.:1170 A2 A2 74 74 74 72 44 68
.:1178 B2 32 B2 00 00 22 00 00
.:1180 1A 1A 26 26 72 72 88 C8
.:1188 C4 CA 26 48 44 44 A2 C8
.:1190 3A 3B 52 4D 47 58 4C 53
.:1198 54 46 48 44 50 2C 41 42
.:11A0 F9 00 35 F9 00 CC F8 00
.:11A8 F7 F8 00 56 F9 00 89 F9
.:11B0 00 F4 F9 00 0C FA 00 3E
.:11B8 FB 00 92 FB 00 C0 FB 00
.:11C0 38 FC 00 5B FD 00 8A FD
.:11C8 00 AC FD 00 46 F8 00 FF
.:11D0 F7 00 ED F7 00 0D 20 20
.:11D8 20 50 43 20 20 53 52 20
.:11E0 41 43 20 58 52 20 59 52
.:11E8 20 53 50 45 52 22 20 20
.
```

ROM Routines

The routines in this book use various ROM routines to function. They are as follows:

$AEFD: Check if the next character is a comma and skip it. Otherwise print SYNTAX ERROR and return to Basic.

$AD8A: Read next expression (variable, number, etc.) into the FAC.

$B7F7: Change the value in the FAC into a 16 bit integer (0-65535). If the number is too big then print illegal quantity error and return to Basic. Otherwise put the low byte of the number into $14 and the high byte into $15.

$B79E: Read the next expression in the BASIC text and put it as a 8 bit integer in the X register. If the number is greater than 255 then print Illegal quantity error and return to Basic.

$B7EB: This routine reads two expressions or numbers separated by a comma from the Basic text. The first is a 16 bit number and the second is an 8 bit number. The 16 bit number is stored in $14 and $15 and the 8 bit number is stored in the X register. If either or both of the numbers are out of their ranges then the program will stop and print an illegal quantity error. If the comma is missing a syntax error with be displayed. Both these errors return control to Basic.

$E1D4: This routine gets the file name, the device number and the secondary address from the Basic text. It gives an error if any of the above are wrong. It is used in preparation for loading, saving or verifying a program, as in MSAVE/MLOAD/MVERIFY.

1. Fill

The following routine allows you to fill an area of memory with a byte. It is called by the following command:

SYS 28672,start address, end address, byte

e.g. to fill the text screen with 'A' characters and the colour screen with 1 (white), type the following:

SYS 28672,1024,2023,1
SYS 28672,55296,56295,1

An error will be given if any of the numbers are too big or negative.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     7000                    .OPT P,00
30:     7000                    *=   $7000
                          ;FILL ROUTINE
                          ;
                          ;USES $FB AND $FC
                          ;STORE TOP ADDRESS IN
                          ;828 AND 829
90:     7000 20 FD AE           JSR  $AEFD
                          ;SCAN PAST COMMA
110:    7003 20 8A AD           JSR  $AD8A
                          ;READ NUMBER AND PUT
                          ;INTO FAC
140:    7006 20 F7 B7           JSR  $B7F7
                          ;GET NUMBER FROM FAC
                          ; AND PUT IN $14 AND $15
170:    7009 A5 14              LDA  $14
170:    700B 85 FB              STA  $FB
```

```
180:   700D A5 15          LDA  $15
180:   700F 85 FC          STA  $FC
                           ;
200:   7011 20 FD AE       JSR  $AEFD
                           ;SCAN PAST COMMA
220:   7014 20 8A AD       JSR  $AD8A
230:   7017 20 F7 B7       JSR  $B7F7
240:   701A A5 14          LDA  $14
240:   701C 8D 3C 03       STA  828
250:   701F A5 15          LDA  $15
250:   7021 8D 3D 03       STA  829
                           ;
270:   7024 20 FD AE       JSR  $AEFD
280:   7027 20 8A AD       JSR  $AD8A
290:   702A 20 F7 B7       JSR  $B7F7
300:   702D A5 15          LDA  $15
300:   702F F0 03          BEQ  MORE
300:   7031 4C 48 B2       JMP  $B248
                           ;$B248 IS IQANT ERROR
320:   7034 A5 14    MORE  LDA  $14
320:   7036 8D 3E 03       STA  830
330:   7039 A0 00    LOOP  LDY  #0
340:   703B AD 3E 03       LDA  830
350:   703E 91 FB          STA  ($FB),Y
360:   7040 20 57 70       JSR  ADD
370:   7043 A5 FB          LDA  $FB
370:   7045 CD 3C 03       CMP  828
370:   7048 F0 03          BEQ  CHECK
380:   704A 4C 39 70       JMP  LOOP
390:   704D A5 FC    CHECK LDA  $FC
390:   704F CD 3D 03       CMP  829
390:   7052 F0 0B          BEQ  FINISH
400:   7054 4C 39 70       JMP  LOOP
410:   7057 E6 FB    ADD   INC  $FB
410:   7059 F0 01          BEQ  FCPLUS1
420:   705B 60             RTS
430:   705C E6 FC    FCPLUS1 INC $FC
430:   705E 60             RTS
440:   705F 60       FINISH RTS
]7000-7060
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 ØØ ØØ Ø1 F6
.
7ØØØ 2Ø FD AE     JSR $AEFD
7ØØ3 2Ø 8A AD     JSR $AD8A
7ØØ6 2Ø F7 B7     JSR $B7F7
7ØØ9 A5 14        LDA $14
7ØØB 85 FB        STA $FB
7ØØD A5 15        LDA $15
7ØØF 85 FC        STA $FC
7Ø11 2Ø FD AE     JSR $AEFD
7Ø14 2Ø 8A AD     JSR $AD8A
7Ø17 2Ø F7 B7     JSR $B7F7
7Ø1A A5 14        LDA $14
7Ø1C 8D 3C Ø3     STA $Ø33C
7Ø1F A5 15        LDA $15
7Ø21 8D 3D Ø3     STA $Ø33D
7Ø24 2Ø FD AE     JSR $AEFD
7Ø27 2Ø 8A AD     JSR $AD8A
7Ø2A 2Ø F7 B7     JSR $B7F7
7Ø2D A5 15        LDA $15
7Ø2F FØ Ø3        BEQ $7Ø34
7Ø31 4C 48 B2     JMP $B248
7Ø34 A5 14        LDA $14
7Ø36 8D 3E Ø3     STA $Ø33E
7Ø39 AØ ØØ        LDY #$ØØ
7Ø3B AD 3E Ø3     LDA $Ø33E
7Ø3E 91 FB        STA ($FB),Y
7Ø4Ø 2Ø 57 7Ø     JSR $7Ø57
7Ø43 A5 FB        LDA $FB
7Ø45 CD 3C Ø3     CMP $Ø33C
7Ø48 FØ Ø3        BEQ $7Ø4D
7Ø4A 4C 39 7Ø     JMP $7Ø39
7Ø4D A5 FC        LDA $FC
7Ø4F CD 3D Ø3     CMP $Ø33D
7Ø52 FØ ØB        BEQ $7Ø5F
7Ø54 4C 39 7Ø     JMP $7Ø39
7Ø57 E6 FB        INC $FB
7Ø59 FØ Ø1        BEQ $7Ø5C
.
```

2. Move

The following routine allows you to move an area of memory to another location. It has the syntax:

SYS 24576,start,finish,destination address.

e.g. to move the contents of the screen to 16384 type the following:

SYS 24576,1024,2023,16384

The three numbers or variables must be no bigger than 65535. If they are bigger then an error will be printed and control will return to Basic.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     6000                    .OPT P,OO
30:     6000                    *=   $6000
                            ;
                            ;ROUTINE TO MOVE ONE
                            ; AREA OF
                            ;MEMORY TO ANOTHER
                            ;
                            ;SCAN COMMA
90:     6000 20 FD AE           JSR  $AEFD
100:    6003 20 8A AD           JSR  $AD8A
110:    6006 20 F7 B7           JSR  $B7F7
120:    6009 A5 14              LDA  $14
130:    600B 8D 78 60           STA  TEMP
140:    600E A5 15              LDA  $15
150:    6010 8D 79 60           STA  TEMP+1
                            ;
165:    6013 20 FD AE           JSR  $AEFD
```

```
170:   6016 20 8A AD          JSR  $AD8A
180:   6019 20 F7 B7          JSR  $B7F7
190:   601C A5 14             LDA  $14
200:   601E 8D 7A 60          STA  TEMP+2
210:   6021 A5 15             LDA  $15
220:   6023 8D 7B 60          STA  TEMP+3
225:   6026 20 FD AE          JSR  $AEFD
230:   6029 20 8A AD          JSR  $AD8A
240:   602C 20 F7 B7          JSR  $B7F7
250:   602F A5 14             LDA  $14
260:   6031 8D 7C 60          STA  TEMP+4
270:   6034 A5 15             LDA  $15
280:   6036 8D 7D 60          STA  TEMP+5
                              ;
291:   6039 AD 78 60          LDA  TEMP
291:   603C 85 FB             STA  $FB
292:   603E AD 79 60          LDA  TEMP+1
292:   6041 85 FC             STA  $FC
293:   6043 AD 7C 60          LDA  TEMP+4
293:   6046 85 FD             STA  $FD
294:   6048 AD 7D 60          LDA  TEMP+5
294:   604B 85 FE             STA  $FE
300:   604D A0 00             LDY  #0
310:   604F B1 FB       LOOP  LDA  ($FB),Y
320:   6051 91 FD             STA  ($FD),Y
330:   6053 20 60 60          JSR  ADDONE
340:   6056 A5 FB             LDA  $FB
350:   6058 CD 7A 60          CMP  TEMP+2
360:   605B F0 10             BEQ  CHECK
370:   605D 4C 4F 60          JMP  LOOP
                              ;
                              ;
400:   6060 E6 FB       ADDONE INC  $FB
410:   6062 D0 02              BNE  MORE
420:   6064 E6 FC              INC  $FC
430:   6066 E6 FD       MORE   INC  $FD
440:   6068 D0 02              BNE  RETURN
450:   606A E6 FE              INC  $FE
460:   606C 60          RETURN RTS
                               ;
                               ;
```

```
490:    606D A5 FC     CHECK     LDA   #FC
500:    606F CD 7B 60            CMP   TEMP+3
510:    6072 F0 03               BEQ   FIN
520:    6074 4C 4F 60            JMP   LOOP
                         ;
                         ;
550:    6077             FIN     =     *
555:    6077 60                  RTS
560:    6078             TEMP    =     *
]6000-6078

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
6000 20 FD AE     JSR #AEFD
6003 20 8A AD     JSR #AD8A
6006 20 F7 B7     JSR #B7F7
6009 A5 14        LDA #14
600B 8D 78 60     STA #6078
600E A5 15        LDA #15
6010 8D 79 60     STA #6079
6013 20 FD AE     JSR #AEFD
6016 20 8A AD     JSR #AD8A
6019 20 F7 B7     JSR #B7F7
601C A5 14        LDA #14
601E 8D 7A 60     STA #607A
6021 A5 15        LDA #15
6023 8D 7B 60     STA #607B
6026 20 FD AE     JSR #AEFD
6029 20 8A AD     JSR #AD8A
602C 20 F7 B7     JSR #B7F7
602F A5 14        LDA #14
6031 8D 7C 60     STA #607C
6034 A5 15        LDA #15
6036 8D 7D 60     STA #607D
```

```
6039 AD 78 60     LDA $6078
603C 85 FB        STA $FB
603E AD 79 60     LDA $6079
6041 85 FC        STA $FC
6043 AD 7C 60     LDA $607C
6046 85 FD        STA $FD
6048 AD 7D 60     LDA $607D
604B 85 FE        STA $FE
604D A0 00        LDY #$00
604F B1 FB        LDA ($FB),Y
6051 91 FD        STA ($FD),Y
6053 20 60 60     JSR $6060
6056 A5 FB        LDA $FB
6058 CD 7A 60     CMP $607A
605B F0 10        BEQ $606D
605D 4C 4F 60     JMP $604F
6060 E6 FB        INC $FB
6062 D0 02        BNE $6066
6064 E6 FC        INC $FC
6066 E6 FD        INC $FD
6068 D0 02        BNE $606C
606A E6 FE        INC $FE
606C 60           RTS
606D A5 FC        LDA $FC
606F CD 7B 60     CMP $607B
6072 F0 03        BEQ $6077
6074 4C 4F 60     JMP $604F
6077 60           RTS
.
```

3. Pause

The following routine allows a listing to be stopped at any time. It will in fact stop any output to the screen that is printed. It works by interrupting the character out routine and check to see if the shift key has been pressed. If it has then it loops until the key has been released.

The syntax is SYS 960. To disable it press run/stop and restore simultaneously.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     03C0                        .OPT P,00
30:     03C0                        *=   960
                                ;
50:     03C0 A9 CB                  LDA  #<MAIN
60:     03C2 8D 26 03               STA  806
70:     03C5 A9 03                  LDA  #>MAIN
80:     03C7 8D 27 03               STA  807
90:     03CA 60                     RTS
                                ;
110:    03CB 48          MAIN       PHA
110:    03CC 8A                     TXA
110:    03CD 48                     PHA
110:    03CE 98                     TYA
110:    03CF 48                     PHA
120:    03D0 AD 8D 02 LOOP          LDA  653
130:    03D3 C9 01                  CMP  #1
140:    03D5 F0 F9                  BEQ  LOOP
160:    03D7 68                     PLA
160:    03D8 A8                     TAY
160:    03D9 68                     PLA
160:    03DA AA                     TAX
```

```
160:   03DB 68                  PLA
170:   03DC 4C CA F1            JMP  $F1CA
]03C0-03DF

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
03C0 A9 CB       LDA #$CB
03C2 8D 26 03    STA $0326
03C5 A9 03       LDA #$03
03C7 8D 27 03    STA $0327
03CA 60          RTS
03CB 48          PHA
03CC 8A          TXA
03CD 48          PHA
03CE 98          TYA
03CF 48          PHA
03D0 AD 8D 02    LDA $028D
03D3 C9 01       CMP #$01
03D5 F0 F9       BEQ $03D0
03D7 68          PLA
03D8 A8          TAY
03D9 68          PLA
03DA AA          TAX
03DB 68          PLA
03DC 4C CA F1    JMP $F1CA
.
```

4. Function keys

The following program allows you to put commands onto the function keys. It uses the IRQ interrupt to scan the keyboard. There are listings in PAL and Supermon format to see how the program works, but it is best to enter the program as the Basic loader which follows. Any of the three ways works equally well but it is easier to change the text to go on the function keys from the Basic listing.

To turn the keys on type SYS 49152 (for the Basic listing , SYS 24576 for the other two). To turn them off press run/stop and restore.

```
.

PAL (C)1979 BRAD TEMPLETON
2
20:     6000                    .OPT P,00
30:     6000                    *=   $6000
                          ;
                          ;ROUTINE TO SETUP
                          ;FUNCTION KEYS
                          ;
80:     6000 78                 SEI
90:     6001 A9 0D              LDA  #<MAIN
100:    6003 8D 14 03           STA  788
110:    6006 A9 60              LDA  #>MAIN
120:    6008 8D 15 03           STA  789
130:    600B 58                 CLI
140:    600C 60                 RTS
                          ;
                          ;
170:    600D 48           MAIN  PHA
180:    600E 8A                 TXA
190:    600F 48                 PHA
```

```
200:   6010 98                    TYA
210:   6011 48                    PHA
220:   6012 A5 C5                 LDA  $C5
230:   6014 C5 FB                 CMP  $FB
240:   6016 F0 52                 BEQ  LOOP
250:   6018 85 FB                 STA  $FB
260:   601A C9 03                 CMP  #3
270:   601C D0 08                 BNE  LOOP1
                                  ;
290:   601E A9 30                 LDA  #$30
300:   6020 8D 72 60              STA  C100
310:   6023 4C 47 60              JMP  PRINT
                                  ;
330:   6026 C9 04      LOOP1      CMP  #4
340:   6028 D0 08                 BNE  LOOP2
350:   602A A9 00                 LDA  #0
360:   602C 8D 72 60              STA  C100
370:   602F 4C 47 60              JMP  PRINT
                                  ;
390:   6032 C9 05      LOOP2      CMP  #5
400:   6034 D0 08                 BNE  LOOP3
                                  ;
420:   6036 A9 10                 LDA  #$10
430:   6038 8D 72 60              STA  C100
440:   603B 4C 47 60              JMP  PRINT
                                  ;
460:   603E C9 06      LOOP3      CMP  #6
470:   6040 D0 28                 BNE  LOOP
480:   6042 A9 20                 LDA  #$20
490:   6044 8D 72 60              STA  C100
                                  ;
510:   6047 AD 8D 02   PRINT      LDA  $028D
520:   604A C9 01                 CMP  #1
530:   604C D0 09                 BNE  PUTON
                                  ;
550:   604E AD 72 60              LDA  C100
560:   6051 18                    CLC
560:   6052 69 08                 ADC  #8
570:   6054 8D 72 60              STA  C100
                                  ;
590:   6057 A2 00      PUTON      LDX  #0
```

```
600:    6059 AC 72 60          LDY  C100
610:    605C B9 73 60 LOP      LDA  C101,Y
620:    605F 9D 77 02          STA  $0277,X
630:    6062 E8                INX
640:    6063 C8                INY
650:    6064 E0 08             CPX  #$08
660:    6066 D0 F4             BNE  LOP
670:    6068 86 C6             STX  $C6
680:    606A 68          LOOP  PLA
690:    606B A8                TAY
700:    606C 68                PLA
710:    606D AA                TAX
720:    606E 68                PLA
730:    606F 4C 31 EA          JMP  $EA31

                               ;
750:    6072 00          C100  .BYT 0
760:    6073 4C 49 53 C101     .ASC "LIST"
760:    6077 0D 04 04          .BYT 13,4,4,4
770:    607B 52 55 4E          .ASC "RUN"
770:    607E 0D 04 04          .BYT 13,4,4,4,4
780:    6083 50 52 49          .ASC "PRINT"
780:    6088 04 04 04          .BYT 4,4,4
790:    608B 54 48 45          .ASC "THEN"
790:    608F 04 04 04          .BYT 4,4,4,4
800:    6093 4C 4F 41          .ASC "LOAD"
800:    6097 04 04 04          .BYT 4,4,4,4
810:    609B 53 41 56          .ASC "SAVE"
810:    609F 04 04 04          .BYT 4,4,4,4
820:    60A3 56 45 52          .ASC "VERIFY"
820:    60A9 04 04             .BYT 4,4
830:    60AB 47 4F 54          .ASC "GOTO"
830:    60AF 04 04 04          .BYT 4,4,4,4
]6000-60B3

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
6000 78          SEI
6001 A9 0D       LDA #$0D
6003 8D 14 03    STA $0314
6006 A9 60       LDA #$60
6008 8D 15 03    STA $0315
600B 58          CLI
600C 60          RTS
600D 48          PHA
600E 8A          TXA
600F 48          PHA
6010 98          TYA
6011 48          PHA
6012 A5 C5       LDA $C5
6014 C5 FB       CMP $FB
6016 F0 52       BEQ $606A
6018 85 FB       STA $FB
601A C9 03       CMP #$03
601C D0 08       BNE $6026
601E A9 30       LDA #$30
6020 8D 72 60    STA $6072
6023 4C 47 60    JMP $6047
6026 C9 04       CMP #$04
6028 D0 08       BNE $6032
602A A9 00       LDA #$00
602C 8D 72 60    STA $6072
602F 4C 47 60    JMP $6047
6032 C9 05       CMP #$05
6034 D0 08       BNE $603E
6036 A9 10       LDA #$10
6038 8D 72 60    STA $6072
603B 4C 47 60    JMP $6047
603E C9 06       CMP #$06
6040 D0 28       BNE $606A
6042 A9 20       LDA #$20
6044 8D 72 60    STA $6072
6047 AD 8D 02    LDA $028D
604A C9 01       CMP #$01
```

```
604C D0 09       BNE $6057
604E AD 72 60    LDA $6072
6051 18          CLC
6052 69 08       ADC #$08
6054 8D 72 60    STA $6072
6057 A2 00       LDX #$00
6059 AC 72 60    LDY $6072
605C B9 73 60    LDA $6073,Y
605F 9D 77 02    STA $0277,X
6062 E8          INX
6063 C8          INY
6064 E0 08       CPX #$08
6066 D0 F4       BNE $605C
6068 86 C6       STX $C6
606A 68          PLA
606B A8          TAY
606C 68          PLA
606D AA          TAX
606E 68          PLA
606F 4C 31 EA    JMP $EA31
.
.
.
.
.:6072 00 4C 49 53 54 0D 04 04
.:607A 04 52 55 4E 0D 04 04 04
.:6082 04 50 52 49 4E 54 04 04
.:608A 04 54 48 45 4E 04 04 04
.:6092 04 4C 4F 41 44 04 04 04
.:609A 04 53 41 56 45 04 04 04
.:60A2 04 56 45 52 49 46 59 04
.:60AA 04 47 4F 54 4F 04 04 04
.:60B2 04 00 00 00 00 00 FF 00
.
```

```
10 DATA 120,169,16,141,20,3,169,192,141,
21,3,88,96,234,234,234,72,138,72,152,72
15 DATA 165,197,197,251,240,81,133,251,2
01,3,208,8,169,48,141,0,193,76,74,192
20 DATA201,4,208,8,169,0,141,0,193,76,74
,192,201,5,208,8,169,16,141,0,193,76,74
25 DATA 192,201,6,208,39,169,32,141,0,19
3,173,141,2,201,1,208,8,173,0,193,105,8
30 DATA141,0,193,162,0,172,0,193,185,1,1
93,157,119,2,232,200,224,8,208,244,134
35 DATA198,104,168,104,170,104,76,49,234

40 FORA=49152TO49267:READB:POKEA,B:NEXT
50 FORA=0TO7:READK$:FORB=1TO8:L=ASC((MID
$(K$,B,1))):IFL=95THENL=13
55 IFL=47THENL=4
60 POKE49409+(A*8)+B,L:NEXT:NEXT:POKE494
09,4:SYS49152
70 DATA"LIST←///"
80 DATA"PRINT///"
90 DATA"RUN←////"
100 DATA"THEN////"
110 DATA"LOAD////"
120 DATA"SAVE////"
130 DATA"VERIFY//"
140 DATA"GOTO////"

READY.
```

5. IRQ clock

The clock routine is updated by the IRQ interrupt which is called by the computer every 50th of a second. The routine used to print line numbers for BASIC is used to print the time (lo byte in X and high byte in A). It is not very good for using when typing in a program as the cursor is always at the top of the screen but it works fine in a program. The syntax to set the clock is as follows:

SYS 28672,hours,minutes.

The clock is in 24 hour format, so remember to enter the time in 24 hour format.

```
.
PAL (C)1979 BRAD TEMPLETON
2
20:     7000                    .OPT P,OO
30:     7000                    *=   $7000
                          ;
                          ;DISPLAYS A CLOCK AT
                          ;TOP LEFT
                          ;OF SCREEN
                          ;
                          ;TO SET TYPE
                          ;
                          ;SYS 24576,HOURS,MINS
                          ;
                          ;SECONDS ASSUMED ZERO
                          ;
150:    7000 20 FD AE           JSR  $AEFD
160:    7003 20 9E B7           JSR  $B79E
170:    7006 8A                 TXA
180:    7007 C9 18              CMP  #24
190:    7009 B0 14              BCS  IQERR
```

```
200:   700B 8D B7 70          STA  HOUR
                              ;
220:   700E 20 FD AE          JSR  $AEFD
230:   7011 20 9E B7          JSR  $B79E
240:   7014 8A                TXA
250:   7015 C9 3C             CMP  #60
260:   7017 B0 06             BCS  IQERR
270:   7019 8D B8 70          STA  MINUTE
                              ;
290:   701C 4C 22 70          JMP  SETUP
                              ;
310:   701F 4C 48 B2 IQERR    JMP  $B248
                              ;
330:   7022 78       SETUP    SEI
340:   7023 A9 3F             LDA  #<MAIN
350:   7025 8D 14 03          STA  788
360:   7028 A9 70             LDA  #>MAIN
370:   702A 8D 15 03          STA  789
380:   702D AD B7 70          LDA  HOUR
400:   7030 AD B8 70          LDA  MINUTE
420:   7033 A9 00             LDA  #0
430:   7035 8D B9 70          STA  SECOND
450:   7038 A9 00             LDA  #0
450:   703A 8D BA 70          STA  COUNTER
460:   703D 58                CLI
470:   703E 60                RTS
                              ;
                              ;
500:   703F EE BA 70 MAIN     INC  COUNTER
510:   7042 AD BA 70          LDA  COUNTER
520:   7045 C9 3C             CMP  #60
530:   7047 B0 03             BCS  CHANGE
                              ;
550:   7049 4C 31 EA          JMP  $EA31
                              ;
570:   704C A9 00    CHANGE   LDA  #0
580:   704E 8D BA 70          STA  COUNTER
                              ;
600:   7051 EE B9 70          INC  SECOND
610:   7054 AD B9 70          LDA  SECOND
620:   7057 C9 3C             CMP  #60
```

```
630:   7059 B0 03              BCS  MINUTECHANGE
                               ;
650:   705B 4C 8D 70           JMP  PRINT
                               ;
670:   705E A9 00     MINUTECHALDA  #0
680:   7060 8D B9 70           STA  SECOND
690:   7063 EE B8 70           INC  MINUTE
700:   7066 AD B8 70           LDA  MINUTE
710:   7069 C9 3C              CMP  #60
720:   706B B0 03              BCS  HOURCHANGE
                               ;
740:   706D 4C 8D 70           JMP  PRINT
                               ;
760:   7070 A9 00     HOURCHANGLDA  #0
770:   7072 8D B8 70           STA  MINUTE
780:   7075 EE B7 70           INC  HOUR
790:   7078 AD B7 70           LDA  HOUR
800:   707B C9 18              CMP  #24
810:   707D 90 0E              BCC  PRINT
                               ;
830:   707F A9 00              LDA  #0
840:   7081 8D B9 70           STA  SECOND
850:   7084 8D B8 70           STA  MINUTE
860:   7087 8D B7 70           STA  HOUR
870:   708A 4C 31 EA           JMP  $EA31
                               ;
890:   708D A9 13     PRINT    LDA  #"|
900:   708F 20 D2 FF           JSR  $FFD2
                               ;
920:   7092 A9 00              LDA  #0
930:   7094 AE B7 70           LDX  HOUR
940:   7097 20 CD BD           JSR  $BDCD
                               ;
960:   709A A9 3A              LDA  #":
970:   709C 20 D2 FF           JSR  $FFD2
                               ;
990:   709F A9 00              LDA  #0
1000:  70A1 AE B8 70           LDX  MINUTE
1010:  70A4 20 CD BD           JSR  $BDCD
                               ;
1030:  70A7 A9 3A              LDA  #":
```

```
1040:   70A9 20 D2 FF          JSR   $FFD2
                          ;
1060:   70AC A9 00             LDA   #0
1070:   70AE AE B9 70          LDX   SECOND
1080:   70B1 20 CD BD          JSR   $BDCD
1090:   70B4 4C 31 EA          JMP   $EA31
                          ;
1110:   70B7 00        HOUR    .BYT 0
1120:   70B8 00        MINUTE  .BYT 0
1130:   70B9 00        SECOND  .BYT 0
1140:   70BA 00        COUNTER .BYT 0
]7000-70BB

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
7000 20 FD AE    JSR $AEFD
7003 20 9E B7    JSR $B79E
7006 8A          TXA
7007 C9 18       CMP #$18
7009 B0 14       BCS $701F
700B 8D B7 70    STA $70B7
700E 20 FD AE    JSR $AEFD
7011 20 9E B7    JSR $B79E
7014 8A          TXA
7015 C9 3C       CMP #$3C
7017 B0 06       BCS $701F
7019 8D B8 70    STA $70B8
701C 4C 22 70    JMP $7022
701F 4C 48 B2    JMP $B248
7022 78          SEI
7023 A9 3F       LDA #$3F
7025 8D 14 03    STA $0314
```

```
7028 A9 70      LDA #$70
702A 8D 15 03   STA $0315
702D AD B7 70   LDA $70B7
7030 AD B8 70   LDA $70B8
7033 A9 00      LDA #$00
7035 8D B9 70   STA $70B9
7038 A9 00      LDA #$00
703A 8D BA 70   STA $70BA
703D 58         CLI
703E 60         RTS
703F EE BA 70   INC $70BA
7042 AD BA 70   LDA $70BA
7045 C9 3C      CMP #$3C
7047 B0 03      BCS $704C
7049 4C 31 EA   JMP $EA31
704C A9 00      LDA #$00
704E 8D BA 70   STA $70BA
7051 EE B9 70   INC $70B9
7054 AD B9 70   LDA $70B9
7057 C9 3C      CMP #$3C
7059 B0 03      BCS $705E
705B 4C 8D 70   JMP $708D
705E A9 00      LDA #$00
7060 8D B9 70   STA $70B9
7063 EE B8 70   INC $70B8
7066 AD B8 70   LDA $70B8
7069 C9 3C      CMP #$3C
706B B0 03      BCS $7070
706D 4C 8D 70   JMP $708D
7070 A9 00      LDA #$00
7072 8D B8 70   STA $70B8
7075 EE B7 70   INC $70B7
7078 AD B7 70   LDA $70B7
707B C9 18      CMP #$18
707D 90 0E      BCC $708D
707F A9 00      LDA #$00
7081 8D B9 70   STA $70B9
7084 8D B8 70   STA $70B8
7087 8D B7 70   STA $70B7
708A 4C 31 EA   JMP $EA31
708D A9 13      LDA #$13
```

```
708F 20 D2 FF     JSR $FFD2
7092 A9 00        LDA #$00
7094 AE B7 70     LDX $70B7
7097 20 CD BD     JSR $BDCD
709A A9 3A        LDA #$3A
709C 20 D2 FF     JSR $FFD2
709F A9 00        LDA #$00
70A1 AE B8 70     LDX $70B8
70A4 20 CD BD     JSR $BDCD
70A7 A9 3A        LDA #$3A
70A9 20 D2 FF     JSR $FFD2
70AC A9 00        LDA #$00
70AE AE B9 70     LDX $70B9
70B1 20 CD BD     JSR $BDCD
70B4 4C 31 EA     JMP $EA31
70B7 00           BRK
70B8 00           BRK
70B9 00           BRK
70BA 00           BRK
.
```

6. Pixel scroll left

The following routine scrolls the screen to the left by one pixel every time that it is called.

To scroll the screen one pixel to the left type SYS 4096.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     1000                        .OPT P,OO
30:     1000                        *=   $1000
40:     1000 AD 16 D0               LDA  53270
50:     1003 29 F8                  AND  #248
60:     1005 18                     CLC
70:     1006 6D 5B 10               ADC  BYTE
80:     1009 8D 16 D0               STA  53270
90:     100C CE 5B 10               DEC  BYTE
100:    100F AD 5B 10               LDA  BYTE
110:    1012 C9 FF                  CMP  #$FF
120:    1014 F0 01                  BEQ  RESET
130:    1016 60                     RTS
140:    1017 AD 16 D0 RESET         LDA  53270
140:    101A 29 F8                  AND  #248
140:    101C 18                     CLC
140:    101D 69 07                  ADC  #7
140:    101F 8D 16 D0               STA  53270
150:    1022 A9 07                  LDA  #7
150:    1024 8D 5B 10               STA  BYTE
160:    1027 20 2B 10               JSR  CHARSCROLL
170:    102A 60                     RTS
180:    102B A9 06     CHARSCROLLDA  #6
190:    102D 8D 44 03               STA  $0344
200:    1030 A2 00                  LDX  #0
210:    1032 A0 00                  LDY  #0
220:    1034 BD 01 04 LOOP          LDA  $0401,X
```

```
230:    1037 9D 00 04          STA   $0400,X
240:    103A BD F1 04          LDA   $04F1,X
250:    103D 9D F0 04          STA   $04F0,X
260:    1040 BD E1 05          LDA   $05E1,X
270:    1043 9D E0 05          STA   $05E0,X
280:    1046 BD D1 06          LDA   $06D1,X
290:    1049 9D D0 06          STA   $06D0,X
300:    104C E8                INX
310:    104D C8                INY
320:    104E C0 27             CPY   #$27
330:    1050 D0 E2             BNE   LOOP
340:    1052 E8                INX
350:    1053 A0 00             LDY   #0
360:    1055 CE 44 03          DEC   $0344
370:    1058 D0 DA             BNE   LOOP
380:    105A 60                RTS
390:    105B 07        BYTE    .BYTE7
]1000-105C

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
1000 AD 16 D0     LDA $D016
1003 29 F8        AND #$F8
1005 18           CLC
1006 6D 5B 10     ADC $105B
1009 8D 16 D0     STA $D016
100C CE 5B 10     DEC $105B
100F AD 5B 10     LDA $105B
1012 C9 FF        CMP #$FF
1014 F0 01        BEQ $1017
1016 60           RTS
1017 AD 16 D0     LDA $D016
101A 29 F8        AND #$F8
```

```
101C 18          CLC
101D 69 07       ADC #$07
101F 8D 16 D0    STA $D016
1022 A9 07       LDA #$07
1024 8D 5B 10    STA $105B
1027 20 2B 10    JSR $102B
102A 60          RTS
102B A9 06       LDA #$06
102D 8D 44 03    STA $0344
1030 A2 00       LDX #$00
1032 A0 00       LDY #$00
1034 BD 01 04    LDA $0401,X
1037 9D 00 04    STA $0400,X
103A BD F1 04    LDA $04F1,X
103D 9D F0 04    STA $04F0,X
1040 BD E1 05    LDA $05E1,X
1043 9D E0 05    STA $05E0,X
1046 BD D1 06    LDA $06D1,X
1049 9D D0 06    STA $06D0,X
104C E8          INX
104D C8          INY
104E C0 27       CPY #$27
1050 D0 E2       BNE $1034
1052 E8          INX
1053 A0 00       LDY #$00
1055 CE 44 03    DEC $0344
1058 D0 DA       BNE $1034
105A 60          RTS
105B 07          ???
.
```

7. Pixel scroll right

The following routine scrolls the screen to the right by one pixel.

To scroll the screen by one pixel to the right type SYS 4096.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     1000                        .OPT P,00
30:     1000                        *=   $1000
40:     1000 AD 16 D0               LDA  53270
40:     1003 29 F8                  AND  #248
50:     1005 18                     CLC
50:     1006 6D C9 10               ADC  BYTE
60:     1009 8D 16 D0               STA  53270
70:     100C EE C9 10               INC  BYTE
80:     100F AD C9 10               LDA  BYTE
90:     1012 C9 08                  CMP  #8
100:    1014 F0 01                  BEQ  RESET
110:    1016 60                     RTS
120:    1017 A9 00      RESET       LDA  #0
120:    1019 8D C9 10               STA  BYTE
130:    101C AD 16 D0               LDA  53270
140:    101F 29 F8                  AND  #248
150:    1021 8D 16 D0               STA  53270
160:    1024 20 28 10               JSR  CHARSCROLL
170:    1027 60                     RTS
180:    1028 A2 26      CHARSCROLLDX #38
190:    102A BD 00 04 LOOP          LDA  1024,X
190:    102D 9D 01 04               STA  1025,X
200:    1030 BD 28 04               LDA  1024+40,X
200:    1033 9D 29 04               STA  1025+40,X
210:    1036 BD 50 04               LDA  1024+80,X
210:    1039 9D 51 04               STA  1025+80,X
220:    103C BD 78 04               LDA  1024+120,X
```

```
220:    103F 9D 79 04          STA   1025+120,X
230:    1042 BD A0 04          LDA   1024+160,X
230:    1045 9D A1 04          STA   1025+160,X
240:    1048 BD C8 04          LDA   1024+200,X
240:    104B 9D C9 04          STA   1025+200,X
250:    104E BD F0 04          LDA   1024+240,X
250:    1051 9D F1 04          STA   1025+240,X
260:    1054 BD 18 05          LDA   1024+280,X
260:    1057 9D 19 05          STA   1025+280,X
270:    105A BD 40 05          LDA   1024+320,X
270:    105D 9D 41 05          STA   1025+320,X
280:    1060 BD 68 05          LDA   1024+360,X
280:    1063 9D 69 05          STA   1025+360,X
290:    1066 BD 90 05          LDA   1024+400,X
290:    1069 9D 91 05          STA   1025+400,X
300:    106C BD B8 05          LDA   1024+440,X
300:    106F 9D B9 05          STA   1025+440,X
310:    1072 BD E0 05          LDA   1024+480,X
310:    1075 9D E1 05          STA   1025+480,X
320:    1078 BD 08 06          LDA   1024+520,X
320:    107B 9D 09 06          STA   1025+520,X
330:    107E BD 30 06          LDA   1024+560,X
330:    1081 9D 31 06          STA   1025+560,X
340:    1084 BD 58 06          LDA   1024+600,X
340:    1087 9D 59 06          STA   1025+600,X
350:    108A BD 80 06          LDA   1024+640,X
350:    108D 9D 81 06          STA   1025+640,X
360:    1090 BD A8 06          LDA   1024+680,X
360:    1093 9D A9 06          STA   1025+680,X
370:    1096 BD D0 06          LDA   1024+720,X
370:    1099 9D D1 06          STA   1025+720,X
380:    109C BD F8 06          LDA   1024+760,X
380:    109F 9D F9 06          STA   1025+760,X
390:    10A2 BD 20 07          LDA   1024+800,X
390:    10A5 9D 21 07          STA   1025+800,X
400:    10A8 BD 48 07          LDA   1024+840,X
400:    10AB 9D 49 07          STA   1025+840,X
410:    10AE BD 70 07          LDA   1024+880,X
410:    10B1 9D 71 07          STA   1025+880,X
420:    10B4 BD 98 07          LDA   1024+920,X
420:    10B7 9D 99 07          STA   1025+920,X
430:    10BA BD C0 07          LDA   1024+960,X
```

```
430:    10BD 9D C1 07          STA  1025+960,X
440:    10C0 CA                DEX
440:    10C1 E0 FF             CPX  #$FF
440:    10C3 F0 03             BEQ  FIN
440:    10C5 4C 2A 10          JMP  LOOP
450:    10C8 60          FIN   RTS
460:    10C9 00          BYTE  .BYTE0
]1000-10CA

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
1000 AD 16 D0     LDA $D016
1003 29 F8        AND #$F8
1005 18           CLC
1006 6D C9 10     ADC $10C9
1009 8D 16 D0     STA $D016
100C EE C9 10     INC $10C9
100F AD C9 10     LDA $10C9
1012 C9 08        CMP #$08
1014 F0 01        BEQ $1017
1016 60           RTS
1017 A9 00        LDA #$00
1019 8D C9 10     STA $10C9
101C AD 16 D0     LDA $D016
101F 29 F8        AND #$F8
1021 8D 16 D0     STA $D016
1024 20 28 10     JSR $1028
1027 60           RTS
1028 A2 26        LDX #$26
102A BD 00 04     LDA $0400,X
102D 9D 01 04     STA $0401,X
1030 BD 28 04     LDA $0428,X
```

```
1033 9D 29 04    STA $0429,X
1036 BD 50 04    LDA $0450,X
1039 9D 51 04    STA $0451,X
103C BD 78 04    LDA $0478,X
103F 9D 79 04    STA $0479,X
1042 BD A0 04    LDA $04A0,X
1045 9D A1 04    STA $04A1,X
1048 BD C8 04    LDA $04C8,X
104B 9D C9 04    STA $04C9,X
104E BD F0 04    LDA $04F0,X
1051 9D F1 04    STA $04F1,X
1054 BD 18 05    LDA $0518,X
1057 9D 19 05    STA $0519,X
105A BD 40 05    LDA $0540,X
105D 9D 41 05    STA $0541,X
1060 BD 68 05    LDA $0568,X
1063 9D 69 05    STA $0569,X
1066 BD 90 05    LDA $0590,X
1069 9D 91 05    STA $0591,X
106C BD B8 05    LDA $05B8,X
106F 9D B9 05    STA $05B9,X
1072 BD E0 05    LDA $05E0,X
1075 9D E1 05    STA $05E1,X
1078 BD 08 06    LDA $0608,X
107B 9D 09 06    STA $0609,X
107E BD 30 06    LDA $0630,X
1081 9D 31 06    STA $0631,X
1084 BD 58 06    LDA $0658,X
1087 9D 59 06    STA $0659,X
108A BD 80 06    LDA $0680,X
108D 9D 81 06    STA $0681,X
1090 BD A8 06    LDA $06A8,X
1093 9D A9 06    STA $06A9,X
1096 BD D0 06    LDA $06D0,X
1099 9D D1 06    STA $06D1,X
109C BD F8 06    LDA $06F8,X
109F 9D F9 06    STA $06F9,X
10A2 BD 20 07    LDA $0720,X
10A5 9D 21 07    STA $0721,X
10A8 BD 48 07    LDA $0748,X
10AB 9D 49 07    STA $0749,X
```

```
10AE BD 70 07     LDA $0770,X
10B1 9D 71 07     STA $0771,X
10B4 BD 98 07     LDA $0798,X
10B7 9D 99 07     STA $0799,X
10BA BD C0 07     LDA $07C0,X
10BD 9D C1 07     STA $07C1,X
10C0 CA           DEX
10C1 E0 FF        CPX #$FF
10C3 F0 03        BEQ $10C8
10C5 4C 2A 10     JMP $102A
10C8 60           RTS
10C9 00           BRK
.
```

8. Pixel scroll up

The routine here scrolls the screen up one pixel every time that it is called.

To set up the screen for scrolling type SYS 16384.

To scroll the screen up one pixel type SYS 16398.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                        .OPT P,00
30:     4000                        *=   $4000
                                ;TO SETUP TYPE
                                ;SYS16384
                                ; TO USE TYPE SYS 16398
70:     4000 AD 11 D0 SETUP     LDA  53265
                                ;USE BEFORE STARTING
80:     4003 29 F7              AND  #247
90:     4005 8D 11 D0           STA  53265
100:    4008 A9 07              LDA  #7
100:    400A 8D 3B 40           STA  BYTE
110:    400D 60                 RTS
                                ; MAIN ROUTINE
130:    400E AD 11 D0           LDA  53265
140:    4011 29 F8              AND  #248
150:    4013 18                 CLC
160:    4014 6D 3B 40           ADC  BYTE
170:    4017 8D 11 D0           STA  53265
180:    401A CE 3B 40           DEC  BYTE
190:    401D AD 3B 40           LDA  BYTE
200:    4020 C9 FF              CMP  #$FF
210:    4022 F0 01              BEQ  RESET
220:    4024 60                 RTS
230:    4025 A9 07      RESET   LDA  #7
230:    4027 8D 3B 40           STA  BYTE
240:    402A AD 11 D0           LDA  53265
```

```
240:    402D 29 F8              AND  #248
240:    402F 18                 CLC
240:    4030 69 07              ADC  #7
240:    4032 8D 11 D0           STA  53265
250:    4035 A9 0D              LDA  #13
260:    4037 20 D2 FF           JSR  $FFD2
270:    403A 60                 RTS
280:    403B 07         BYTE    .BYTE7
]4000-403C

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
4000 AD 11 D0     LDA $D011
4003 29 F7        AND #$F7
4005 8D 11 D0     STA $D011
4008 A9 07        LDA #$07
400A 8D 3B 40     STA $403B
400D 60           RTS
400E AD 11 D0     LDA $D011
4011 29 F8        AND #$F8
4013 18           CLC
4014 6D 3B 40     ADC $403B
4017 8D 11 D0     STA $D011
401A CE 3B 40     DEC $403B
401D AD 3B 40     LDA $403B
4020 C9 FF        CMP #$FF
4022 F0 01        BEQ $4025
4024 60           RTS
4025 A9 07        LDA #$07
4027 8D 3B 40     STA $403B
402A AD 11 D0     LDA $D011
402D 29 F8        AND #$F8
```

```
402F 18          CLC
4030 69 07       ADC #$07
4032 8D 11 D0    STA $D011
4035 A9 0D       LDA #$0D
4037 20 D2 FF    JSR $FFD2
403A 60          RTS
403B 07          ???
.
```

9. Pixel scroll down

The following routine scrolls the screen down one pixel when it is called. However, due to the way the character scroll works (using the ROM print routine), the top line of the screen is not scrolled. If this routine were coupled with a raster interrupt to suppress the scroll at the top of the screen then this area would stay stationary while the rest would scroll independently.

To set up the screen for scrolling type SYS 16384.

To scroll the screen down one pixel type SYS 16398.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                        .OPT P,00
30:     4000                        *=   $4000
40:     4000 AD 11 D0 SETUP     LDA  53265
                           ; USE SETUP BEFORE
                             STARTING
60:     4003 29 F7              AND  #247
70:     4005 8D 11 D0           STA  53265
80:     4008 A9 00              LDA  #0
80:     400A 8D 4B 40           STA  BYTE
90:     400D 60                 RTS
                           ; MAIN ROUTINE
110:    400E AD 11 D0           LDA  53265
120:    4011 29 F8              AND  #248
130:    4013 18                 CLC
140:    4014 6D 4B 40           ADC  BYTE
150:    4017 8D 11 D0           STA  53265
160:    401A EE 4B 40           INC  BYTE
170:    401D AD 4B 40           LDA  BYTE
180:    4020 C9 08              CMP  #$08
190:    4022 F0 01              BEQ  RESET
200:    4024 60                 RTS
210:    4025 A9 00    RESET     LDA  #0
```

```
210:    4027 8D 4B 40          STA  BYTE
220:    402A AD 11 D0          LDA  53265
220:    402D 29 F8             AND  #248
220:    402F 8D 11 D0          STA  53265
230:    4032 A9 13             LDA  #"{HOME}"
240:    4034 20 D2 FF          JSR  $FFD2
250:    4037 A9 11             LDA  #"{CUR DN}"
260:    4039 20 D2 FF          JSR  $FFD2
270:    403C A9 9D             LDA  #"{CUR L}"
280:    403E 20 D2 FF          JSR  $FFD2
290:    4041 A9 94             LDA  #"{INST DEL}
300:    4043 20 D2 FF          JSR  $FFD2
310:    4046 A9 80             LDA  #128
320:    4048 85 DA             STA  218
330:    404A 60                RTS
340:    404B 00       BYTE     .BYTE0
]4000-404C

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
4000 AD 11 D0     LDA $D011
4003 29 F7        AND #$F7
4005 8D 11 D0     STA $D011
4008 A9 00        LDA #$00
400A 8D 4B 40     STA $404B
400D 60           RTS
400E AD 11 D0     LDA $D011
4011 29 F8        AND #$F8
4013 18           CLC
4014 6D 4B 40     ADC $404B
4017 8D 11 D0     STA $D011
401A EE 4B 40     INC $404B
401D AD 4B 40     LDA $404B
```

```
4020 C9 08      CMP #$08
4022 F0 01      BEQ $4025
4024 60         RTS
4025 A9 00      LDA #$00
4027 8D 4B 40   STA $404B
402A AD 11 D0   LDA $D011
402D 29 F8      AND #$F8
402F 8D 11 D0   STA $D011
4032 A9 13      LDA #$13
4034 20 D2 FF   JSR $FFD2
4037 A9 11      LDA #$11
4039 20 D2 FF   JSR $FFD2
403C A9 9D      LDA #$9D
403E 20 D2 FF   JSR $FFD2
4041 A9 94      LDA #$94
4043 20 D2 FF   JSR $FFD2
4046 A9 80      LDA #$80
4048 85 DA      STA $DA
404A 60         RTS
404B 00         BRK
.
```

10. Colour

This routine allows you to change the screen colour, the border colour, the text colour, extended colours 1, 2 and 3 (or multicolour) in one command.

The syntax is as follows:

SYS 28672,screen colour,border colour,text colour, multi1,multi2,multi3

NB. All parameters must be given.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     7000                    .OPT P,OO
30:     7000                    *=   $7000
                              ;
                              ;ROUTINE TO SET SCREEN
                              ;COLOURS AND BORDER AND
                              ; TEXT,MULTI1,MULTI2
80:     7000 20 FD AE           JSR  $AEFD
90:     7003 20 37 70           JSR  PARAM
100:    7006 8D 21 D0           STA  53281
110:    7009 20 FD AE           JSR  $AEFD
120:    700C 20 37 70           JSR  PARAM
130:    700F 8D 20 D0           STA  53280
                              ;
150:    7012 20 FD AE           JSR  $AEFD
160:    7015 20 37 70           JSR  PARAM
180:    7018 8D 86 02           STA  646
190:    701B 20 FD AE           JSR  $AEFD
200:    701E 20 37 70           JSR  PARAM
220:    7021 8D 22 D0           STA  53282
230:    7024 20 FD AE           JSR  $AEFD
```

```
240:    7027 20 37 70           JSR  PARAM
260:    702A 8D 23 D0           STA  53283
270:    702D 20 FD AE           JSR  $AEFD
280:    7030 20 37 70           JSR  PARAM
300:    7033 8D 24 D0           STA  53284
310:    7036 60                 RTS
320:    7037 20 9E B7 PARAM     JSR  $B79E
320:    703A 8A                 TXA
330:    703B 60                 RTS
340:    703C 4C 48 B2 IQERR     JMP  $B248
]7000-703F

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
7000 20 FD AE     JSR $AEFD
7003 20 37 70     JSR $7037
7006 8D 21 D0     STA $D021
7009 20 FD AE     JSR $AEFD
700C 20 37 70     JSR $7037
700F 8D 20 D0     STA $D020
7012 20 FD AE     JSR $AEFD
7015 20 37 70     JSR $7037
7018 8D 86 02     STA $0286
701B 20 FD AE     JSR $AEFD
701E 20 37 70     JSR $7037
7021 8D 22 D0     STA $D022
7024 20 FD AE     JSR $AEFD
7027 20 37 70     JSR $7037
702A 8D 23 D0     STA $D023
702D 20 FD AE     JSR $AEFD
7030 20 37 70     JSR $7037
7033 8D 24 D0     STA $D024
7036 60           RTS
7037 20 9E B7     JSR $B79E
703A 8A           TXA
703B 60           RTS
703C 4C 48 B2     JMP $B248
```

11. Copy

This routine allows you to copy the contents of part of or all of the character ROM to a specified part of RAM. This is to make user defined characters easier to set up.

The syntax is SYS 24576,address,no. of pages to copy.

The address is where you want to start your character set at. The number of pages to copy is the number of 256 byte blocks of the ROM to copy down. Only whole numbers are allowed. The character ROM is 16 blocks long. If you specify more than 16 then an illegal quantity error will occur.

e.g. To copy the whole character ROM down to location 8192 type the following:

```
SYS 24576,8192,16
```

or, to copy only the first K of the ROM down to location 12288 type:

```
SYS 24576,12288,4
```

To enable the character set use location 53272 or the change banks routine in this book.

To enable the character set at location 8192 type:

```
POKE 53272,24
```

```
PAL (C)1979 BRAD TEMPLETON
2
20:     6000                    .OPT P,00
30:     6000                    *=   $6000
                        ;
                        ;ROUTINE TO MOVE
                        ;CHARACTER
                        ;ROM TO SPECIFIED
                        ;LOCATION
                        ;SYNTAX
                        ;
                        ;SYS24576,START,NO OF
                        ;PAGES TO COPY
                        ;WHERE PAGES ARE 256
                        ;BYTES LONG
150:    6000 20 FD AE           JSR  $AEFD
160:    6003 20 8A AD           JSR  $AD8A
170:    6006 20 F7 B7           JSR  $B7F7
180:    6009 A5 14              LDA  $14
190:    600B 85 FB              STA  $FB
200:    600D A5 15              LDA  $15
210:    600F 85 FC              STA  $FC
                        ;
230:    6011 20 FD AE           JSR  $AEFD
240:    6014 20 9E B7           JSR  $B79E
250:    6017 8A                 TXA
260:    6018 C9 11              CMP  #17
270:    601A 90 03              BCC  MORE
280:    601C 4C 48 B2           JMP  $B248
290:    601F 85 FD      MORE    STA  $FD
300:    6021 A9 00              LDA  #0
310:    6023 8D 5B 60           STA  TEMP
320:    6026 A0 00              LDY  #0
330:    6028 A9 00              LDA  #0
340:    602A 85 FE              STA  $FE
350:    602C A9 D0              LDA  #208
360:    602E 85 FF              STA  $FF
                        ;
375:    6030 A9 00              LDA  #0
376:    6032 8D 0E DC           STA  56334
380:    6035 A9 33              LDA  #51
```

```
390:    6037 85 01              STA  1
400:    6039 B1 FE     LOOP     LDA  ($FE),Y
410:    603B 91 FB              STA  ($FB),Y
420:    603D C8                 INY
430:    603E D0 F9              BNE  LOOP
                        ;
450:    6040 EE 5B 60           INC  TEMP
460:    6043 AD 5B 60           LDA  TEMP
470:    6046 C5 FD              CMP  $FD
480:    6048 B0 07              BCS  FINISH
                        ;
500:    604A E6 FC              INC  $FC
510:    604C E6 FF              INC  $FF
520:    604E 4C 39 60           JMP  LOOP
                        ;
540:    6051 A9 37     FINISH   LDA  #55
550:    6053 85 01              STA  1
560:    6055 A9 01              LDA  #1
570:    6057 8D 0E DC           STA  56334
580:    605A 60                 RTS
590:    605B           TEMP     =    *
]6000-605B

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
6000 20 FD AE     JSR $AEFD
6003 20 8A AD     JSR $AD8A
6006 20 F7 B7     JSR $B7F7
6009 A5 14        LDA $14
600B 85 FB        STA $FB
600D A5 15        LDA $15
600F 85 FC        STA $FC
```

```
6011 20 FD AE     JSR $AEFD
6014 20 9E B7     JSR $B79E
6017 8A           TXA
6018 C9 11        CMP #$11
601A 90 03        BCC $601F
601C 4C 48 B2     JMP $B248
601F 85 FD        STA $FD
6021 A9 00        LDA #$00
6023 8D 5B 60     STA $605B
6026 A0 00        LDY #$00
6028 A9 00        LDA #$00
602A 85 FE        STA $FE
602C A9 D0        LDA #$D0
602E 85 FF        STA $FF
6030 A9 00        LDA #$00
6032 8D 0E DC     STA $DC0E
6035 A9 33        LDA #$33
6037 85 01        STA $01
6039 B1 FE        LDA ($FE),Y
603B 91 FB        STA ($FB),Y
603D C8           INY
603E D0 F9        BNE $6039
6040 EE 5B 60     INC $605B
6043 AD 5B 60     LDA $605B
6046 C5 FD        CMP $FD
6048 B0 07        BCS $6051
604A E6 FC        INC $FC
604C E6 FF        INC $FF
604E 4C 39 60     JMP $6039
6051 A9 37        LDA #$37
6053 85 01        STA $01
6055 A9 01        LDA #$01
6057 8D 0E DC     STA $DC0E
605A 60           RTS
.
```

12. Sprite/char

If you are using sprites in a program the time will come when you want to find what character the sprite is under or over. You can see which one, but the computer cannot. Commodore kindly made it possible for the video chip to detect if it has hit a character or not, but not to detect which one. The following program does this. It is written to detect the charcter under sprite 0. To find out which character it is, use SYS 16384 from Basic or JSR $4000 from machine code. The character code is returned in location 828 ($033C), so to find the character execute the routine and PEEK or LDA(X or Y) location 828 ($033C)

No doubt you will want to check which character is under a different sprite than sprite 0. Rather than listing 8 programs, one for each sprite, here is a list of what to change to make it work for any sprite:

1. Change the first line from LDA $D000 to LDA $ hex location of 'X' coordinate of the sprite that you want to test.

2. Change the line at address $400A to CMP #$ bit value of sprite to be tested (sprite 0 = 1 through to sprite 7 = 128).

3. Change the line at address $400E to LDX $ hex location of 'X' coordinate of the sprite to be tested.

4. Change the line at address $4011 to LDA $ hex location of 'Y' coordinate of sprite to be tested.

5. Change the line at address $4032 to CMP #$ bit value of sprite to be tested (as in 2).

The routine checks which character is under the top left 8 bytes of the sprite (going down). i.e.

1 2 3
1 2 3
1 2 3
1 2 3
1 2 3
1 2 3
1 2 3
1 2 3
and so on ...

It checks the character under the 1s in the above diagram, but this can be altered by changing two bytes in the program as follows:

The line at location $4004 is SBC #$18. The number after the SBC must never be less than $18 (24), but if you add one to this value for every bit across the sprite then you can alter where on the horizontal the routine will check. (This number must never exceed $30 (48) if the sprite is not expanded in the 'X' direction or $60 (96) if expanded.) Remember that as the sprite is expanded each dot on the sprite is 2 dots wide, therefore you will need to multiply the amount greater than $18 by two and add it to $18.

e.g. to get the routine to check for the rightmost 8 bits of an unexpanded sprite, make the line SBC #$30.

Or, to get the routine to check for the 7th to the 15th bit across in an expanded sprite, make the line SBC #(24+ 7*2) which is SBC #$26.

To alter where the routine checks on the vertical change the line at address $4015 (SBC #$3A). The rules for changing are the same as for the 'X' direction. If the sprite is unexpanded in the 'Y' direction then the value is $3A + the byte down. If the sprite is expanded then the value is $3A + 2* the byte down. The value must never be less than $3A and if the sprite is unexpanded no greater than $4F (79) or if the sprite is expanded no greater than $64 (100) for the routine.

e.g. to make the routine check for the bottom 8 bytes of the sprite when it is unexpanded the line is SBC #$47.

or, to make the routine check for the 10th to the 18th byte down in an expanded sprite the line is SBC #$3A + 2*10 which is SBC #$4E

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                        .OPT P,00
30:     4000                        *=   $4000
40:     4000 AD 00 D0               LDA  53248
50:     4003 38                     SEC
50:     4004 E9 18                  SBC  #24
50:     4006 AA                     TAX
60:     4007 AD 10 D0               LDA  53264
60:     400A C9 01                  CMP  #1
60:     400C D0 03                  BNE  MORE
70:     400E AE 00 D0               LDX  53248
80:     4011 AD 01 D0 MORE          LDA  53249
80:     4014 38                     SEC
80:     4015 E9 3A                  SBC  #58
80:     4017 A8                     TAY
90:     4018 8E 98 40               STX  X1STORE  ;X1
100:    401B 8C 9A 40               STY  Y1STORE ;Y1
110:    401E 98                     TYA
120:    401F 4A                     LSR  A
120:    4020 4A                     LSR  A
120:    4021 4A                     LSR  A ;Y2=Y1/8
130:    4022 18                     CLC
130:    4023 69 01                  ADC  #1
130:    4025 8D 9B 40               STA  Y2STORE
140:    4028 8A                     TXA
150:    4029 4A                     LSR  A
150:    402A 4A                     LSR  A
150:    402B 4A                     LSR  A ;X2=X2/8
160:    402C 8D 99 40               STA  X2STORE
170:    402F AD 10 D0               LDA  53264
170:    4032 C9 01                  CMP  #1
170:    4034 D0 09                  BNE  MORE1
180:    4036 AD 99 40               LDA  X2STORE
190:    4039 18                     CLC
```

```
190:   403A 69 1D              ADC  #29
200:   403C 8D 99 40           STA  X2STORE
210:   403F AD 9B 40 MORE1     LDA  Y2STORE
220:   4042 8D 96 40           STA  NUMBER1
230:   4045 A9 28              LDA  #40
240:   4047 8D 97 40           STA  NUMBER2
250:   404A 20 79 40           JSR  MULTIPLY
260:   404D AD 99 40           LDA  X2STORE
270:   4050 6D 94 40           ADC  RESULT
280:   4053 8D 94 40           STA  RESULT
290:   4056 AD 95 40           LDA  RESULT+1
300:   4059 69 00              ADC  #0
310:   405B 8D 95 40           STA  RESULT+1
320:   405E AD 95 40           LDA  RESULT+1
330:   4061 18                 CLC
340:   4062 69 04              ADC  #4
350:   4064 8D 95 40           STA  RESULT+1
                ; CHARACTER IN LOCATION
                ;IN LOCS RESULT AND RESULT+1
380:   4067 AD 94 40           LDA  RESULT
380:   406A 85 FB              STA  $FB
390:   406C AD 95 40           LDA  RESULT+1
390:   406F 85 FC              STA  $FC
400:   4071 A0 00              LDY  #0
410:   4073 B1 FB              LDA  ($FB),Y
420:   4075 8D 3C 03           STA  828
430:   4078 60                 RTS
440:   4079 A9 00     MULTIPLY LDA  #0
450:   407B 8D 94 40           STA  RESULT
460:   407E A2 08              LDX  #8
470:   4080 4E 96 40 LOOP      LSR  NUMBER1
480:   4083 90 04              BCC  NOADD
490:   4085 18                 CLC
500:   4086 6D 97 40           ADC  NUMBER2
510:   4089 6A        NOADD    ROR  A
520:   408A 6E 94 40           ROR  RESULT
530:   408D CA                 DEX
540:   408E D0 F0              BNE  LOOP
550:   4090 8D 95 40           STA  RESULT+1
560:   4093 60                 RTS
                        ;
```

```
580:    4094 00 00     RESULT    .WORD0
590:    4096 00        NUMBER1   .BYTE0
600:    4097 00        NUMBER2   .BYTE0
610:    4098 00        X1STORE   .BYTE0
620:    4099 00        X2STORE   .BYTE0
630:    409A 00        Y1STORE   .BYTE0
640:    409B 00        Y2STORE   .BYTE0
]4000-409C

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
4000 AD 00 D0     LDA $D000
4003 38           SEC
4004 E9 18        SBC #$18
4006 AA           TAX
4007 AD 10 D0     LDA $D010
400A C9 01        CMP #$01
400C D0 03        BNE $4011
400E AE 00 D0     LDX $D000
4011 AD 01 D0     LDA $D001
4014 38           SEC
4015 E9 3A        SBC #$3A
4017 A8           TAY
4018 8E 98 40     STX $4098
401B 8C 9A 40     STY $409A
401E 98           TYA
401F 4A           LSR
4020 4A           LSR
4021 4A           LSR
4022 18           CLC
4023 69 01        ADC #$01
4025 8D 9B 40     STA $409B
```

```
4028 8A          TXA
4029 4A          LSR
402A 4A          LSR
402B 4A          LSR
402C 8D 99 40    STA $4099
402F AD 10 D0    LDA $D010
4032 C9 01       CMP #$01
4034 D0 09       BNE $403F
4036 AD 99 40    LDA $4099
4039 18          CLC
403A 69 1D       ADC #$1D
403C 8D 99 40    STA $4099
403F AD 9B 40    LDA $409B
4042 8D 96 40    STA $4096
4045 A9 28       LDA #$28
4047 8D 97 40    STA $4097
404A 20 79 40    JSR $4079
404D AD 99 40    LDA $4099
4050 6D 94 40    ADC $4094
4053 8D 94 40    STA $4094
4056 AD 95 40    LDA $4095
4059 69 00       ADC #$00
405B 8D 95 40    STA $4095
405E AD 95 40    LDA $4095
4061 18          CLC
4062 69 04       ADC #$04
4064 8D 95 40    STA $4095
4067 AD 94 40    LDA $4094
406A 85 FB       STA $FB
406C AD 95 40    LDA $4095
406F 85 FC       STA $FC
4071 A0 00       LDY #$00
4073 B1 FB       LDA ($FB),Y
4075 8D 3C 03    STA $033C
4078 60          RTS
4079 A9 00       LDA #$00
407B 8D 94 40    STA $4094
407E A2 08       LDX #$08
4080 4E 96 40    LSR $4096
4083 90 04       BCC $4089
4085 18          CLC
```

```
4086 6D 97 40     ADC $4097
4089 6A           ROR
408A 6E 94 40     ROR $4094
408D CA           DEX
408E D0 F0        BNE $4080
4090 8D 95 40     STA $4095
4093 60           RTS
4094 00           BRK
4095 00           BRK
4096 00           BRK
4097 00           BRK
4098 00           BRK
4099 00           BRK
409A 00           BRK
409B 00           BRK
.
```

13. Doke

The following routine allows you to POKE a 16 bit number into two consecutive locations . This could be to change a RAM vector. It replaces the following line of Basic code:

a = number: hi = int(a/256): lo = (a-number)*256: poke address,lo:pokeaddress + 1,hi

To use the routine type SYS 960,address,number.

e.g. to change the output character routine to point to your own routine at 828 (as in the list alter routine later) type SYS 960,806,828.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     03C0                    .OPT P,OO
30:     03C0                    *=   960
                        ;
                        ; DOKE ROUTINE
                        ;
                        ;SYNTAX SYS 960,
                        ;ADDRESS,VALUE
                        ; EG SYS16384,788,16384
                        ;
110:    03C0 20 FD AE           JSR  $AEFD
120:    03C3 20 8A AD           JSR  $AD8A
130:    03C6 20 F7 B7           JSR  $B7F7
                        ;
150:    03C9 A5 14              LDA  $14
160:    03CB 85 FB              STA  $FB
170:    03CD A5 15              LDA  $15
180:    03CF 85 FC              STA  $FC
                        ;
```

```
200:    03D1 20 FD AE           JSR  $AEFD
210:    03D4 20 8A AD           JSR  $AD8A
220:    03D7 20 F7 B7           JSR  $B7F7
                        ;
240:    03DA A0 00              LDY  #0
250:    03DC A5 14              LDA  $14
260:    03DE 91 FB              STA  ($FB),Y
270:    03E0 A0 01              LDY  #1
280:    03E2 A5 15              LDA  $15
290:    03E4 91 FB              STA  ($FB),Y
                        ;
310:    03E6 60                 RTS
]03C0-03E7

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
03C0 20 FD AE    JSR $AEFD
03C3 20 8A AD    JSR $AD8A
03C6 20 F7 B7    JSR $B7F7
03C9 A5 14       LDA $14
03CB 85 FB       STA $FB
03CD A5 15       LDA $15
03CF 85 FC       STA $FC
03D1 20 FD AE    JSR $AEFD
03D4 20 8A AD    JSR $AD8A
03D7 20 F7 B7    JSR $B7F7
03DA A0 00       LDY #$00
03DC A5 14       LDA $14
03DE 91 FB       STA ($FB),Y
03E0 A0 01       LDY #$01
03E2 A5 15       LDA $15
03E4 91 FB       STA ($FB),Y
03E6 60          RTS
.
```

14. Deek

This routine is complementary to Doke. It allows you to read the contents of two consecutive locations in memory. It replaces the following line of Basic code:

PRINT PEEK(ADDRESS) + 256*PEEK(ADDRESS + 1)

The routine cannot create a variable (e.g. a = Deek (address) is not possible).

The syntax for the routine is as follows:

SYS 828,address

```
PAL (C)1979 BRAD TEMPLETON
2
20:     033C                    .OPT P,00
30:     033C                    *=   828
                          ;
                          ; SIMULATED DEEK
                          ; FUNCTION
                          ;ONLY USED TO PRINT
                          ;THE VALUE
                          ;IN TWO CONSECUTIVE
                          ;
                          ;LOCATIONS IN 16 BIT
                          ;FORMAT
                          ;SYNTAX
                          ;
                          ;SYS828,ADDRESS
                          ;
                          ;EG. SYS828,788
                          ;
                          ;WILL RETURN 59953
                          ;
```

```
210:    033C 20 FD AE          JSR  $AEFD
220:    033F 20 8A AD          JSR  $AD8A
230:    0342 20 F7 B7          JSR  $B7F7
                        ;
250:    0345 A5 14             LDA  $14
260:    0347 85 FB             STA  $FB
270:    0349 A5 15             LDA  $15
280:    034B 85 FC             STA  $FC
                        ;
300:    034D A0 00             LDY  #0
310:    034F B1 FB             LDA  ($FB),Y
320:    0351 C8                INY
330:    0352 AA                TAX
340:    0353 B1 FB             LDA  ($FB),Y
                        ;
360:    0355 4C CD BD          JMP  $BDCD
                        ;
]033C-0358

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
033C 20 FD AE    JSR $AEFD
033F 20 8A AD    JSR $AD8A
0342 20 F7 B7    JSR $B7F7
0345 A5 14       LDA $14
0347 85 FB       STA $FB
0349 A5 15       LDA $15
034B 85 FC       STA $FC
034D A0 00       LDY #$00
034F B1 FB       LDA ($FB),Y
0351 C8          INY
0352 AA          TAX
0353 B1 FB       LDA ($FB),Y
0355 4C CD BD    JMP $BDCD
.
```

15. 3 channel IRQ tune

The following routine will play a tune independently of the other things that the computer is doing.

The routine is enabled by SYS 24576 and can be stopped with run/stop and restore.

The data for the tune is held in the tunetable in the PAL listing and from location $6074 onwards in the disassembly.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     6000                        .OPT P,00
30:     6000                        *=   $6000

40:     6000 78                     SEI
40:     6001 A9 32                  LDA  #<MAI
N
40:     6003 8D 14 03               STA  788
40:     6006 A9 60                  LDA  #>MAI
N
40:     6008 8D 15 03               STA  789
40:     600B A9 0F                  LDA  #15
40:     600D 8D 18 D4               STA  54296

50:     6010 A9 13                  LDA  #19
50:     6012 8D 04 D4               STA  54276

50:     6015 A9 40                  LDA  #64
50:     6017 8D 05 D4               STA  54277

50:     601A 8D 06 D4               STA  54278

50:     601D 8D 0C D4               STA  54284
```

```
50:     6020 8D 0D D4           STA  54285

52:     6023 A9 21              LDA  #33
52:     6025 8D 0B D4           STA  54283

55:     6028 A9 00              LDA  #0
55:     602A 85 FB              STA  251
55:     602C 85 FC              STA  252
55:     602E 85 FD              STA  253
55:     6030 58                 CLI
55:     6031 60                 RTS
                                ;
70:     6032 A6 FB      MAIN    LDX  251
70:     6034 A4 FC              LDY  252
70:     6036
80:     6036 BD 74 60           LDA  TUNE,
X
90:     6039 8D 00 D4           STA  54272

95:     603C BD A6 60           LDA  TUNE1
-2,X
95:     603F 8D 07 D4           STA  54279

95:     6042 BD A7 60           LDA  TUNE1
-1,X
95:     6045 8D 08 D4           STA  54280

100:    6048 BD 75 60           LDA  TUNE+
1,X
110:    604B 8D 01 D4           STA  54273

120:    604E A5 FD              LDA  253
130:    6050 C9 0A              CMP  #10
140:    6052 B0 05              BCS  NEXDE
LAY
150:    6054 E6 FD              INC  253
150:    6056 4C 31 EA           JMP  $EA31

160:    6059 A9 00      NEXDELAY LDA #0
160:    605B 85 FD              STA  253
160:    605D E8                 INX
```

```
160:    605E E8                 INX
160:    605F C8                 INY
160:    6060 86 FB              STX  251
160:    6062 84 FC              STY  252
160:    6064 E0 30              CPX  #48
160:    6066 B0 03              BCS  RE
160:    6068 4C 31 EA           JMP  $EA31

165:    606B A2 00     RE       LDX  #0
165:    606D 85 FB              STA  251
165:    606F 85 FC              STA  252
165:    6071 4C 31 EA           JMP  $EA31

1000:   6074 C6 2D 00 TUNE      .BYT 198,4
5,0,0,198,45,52,43,126,38,0,0,126,38
1010:   6082 4B 22 7E           .BYT 75,34
,126,38,75,34,141,30,214,28,0,0
1015:   608E D6 1C 8D           .BYT 214,2
8,141,30,75,34,227,22
1020:   6096 B1 19 8D           .BYT 177,2
5,141,30,214,28,177,25,227,22
1030:   60A0 00 00 00           .BYT 0,0,0
,0,0,0,0,0
1050:   60A8 72 0B 00 TUNE1     .BYT 114,1
1,0,0,114,11,205,10,159,9,0,0,159,9
1060:   60B6 93 08 9F           .BYT 147,8
,159,9,147,8,163,7,53,7,0,0
1070:   60C2 35 07 A3           .BYT 53,7,
163,7,147,8,185,5
1080:   60CA 6C 06 A3           .BYT 108,6
,163,7,53,7,108,6,185,5
1090:   60D4 00 00 00           .BYT 0,0,0
,0,0,0,0,0
16000-60DC

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
6000 78          SEI
6001 A9 32       LDA #$32
6003 8D 14 03    STA $0314
6006 A9 60       LDA #$60
6008 8D 15 03    STA $0315
600B A9 0F       LDA #$0F
600D 8D 18 D4    STA $D418
6010 A9 13       LDA #$13
6012 8D 04 D4    STA $D404
6015 A9 40       LDA #$40
6017 8D 05 D4    STA $D405
601A 8D 06 D4    STA $D406
601D 8D 0C D4    STA $D40C
6020 8D 0D D4    STA $D40D
6023 A9 21       LDA #$21
6025 8D 0B D4    STA $D40B
6028 A9 00       LDA #$00
602A 85 FB       STA $FB
602C 85 FC       STA $FC
602E 85 FD       STA $FD
6030 58          CLI
6031 60          RTS
6032 A6 FB       LDX $FB
6034 A4 FC       LDY $FC
6036 BD 74 60    LDA $6074,X
6039 8D 00 D4    STA $D400
603C BD A6 60    LDA $60A6,X
603F 8D 07 D4    STA $D407
6042 BD A7 60    LDA $60A7,X
6045 8D 08 D4    STA $D408
6048 BD 75 60    LDA $6075,X
604B 8D 01 D4    STA $D401
604E A5 FD       LDA $FD
6050 C9 0A       CMP #$0A
6052 B0 05       BCS $6059
6054 E6 FD       INC $FD
6056 4C 31 EA    JMP $EA31
```

```
6059 A9 00       LDA #$00
605B 85 FD       STA $FD
605D E8          INX
605E E8          INX
605F C8          INY
6060 86 FB       STX $FB
6062 84 FC       STY $FC
6064 E0 30       CPX #$30
6066 B0 03       BCS $606B
6068 4C 31 EA    JMP $EA31
606B A2 00       LDX #$00
606D 85 FB       STA $FB
606F 85 FC       STA $FC
6071 4C 31 EA    JMP $EA31
6074 C6 2D       DEC $2D
6076 00          BRK
6077 00          BRK
6078 C6 2D       DEC $2D

.
.:6074 C6 2D 00 00 C6 2D 34 2B
.:607C 7E 26 00 00 7E 26 4B 22
.:6084 7E 26 4B 22 8D 1E D6 1C
.:608C 00 00 D6 1C 8D 1E 4B 22
.:6094 E3 16 B1 19 8D 1E D6 1C
.:609C B1 19 E3 16 00 00 00 00
.:60A4 00 00 00 00 72 0B 00 00
.:60AC 72 0B CD 0A 9F 09 00 00
.:60B4 9F 09 93 08 9F 09 93 08
.:60BC A3 07 35 07 00 00 35 07
.:60C4 A3 07 93 08 B9 05 6C 06
.:60CC A3 07 35 07 6C 06 B9 05
.:60D4 00 00 00 00 00 00 00 00
.
```

16. List alter

The following routine lets you list a program in a specified column width. I have used it to list the Supermon loader in a width suitable for a book page.

To use this routine type SYS 828,number of columns.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     033C                        .OPT P,OO
30:     033C                        *=   $033C
40:     033C            IBSOUT      =    $0326
50:     033C 20 FD AE               JSR  $AEFD
60:     033F 20 9E B7               JSR  $B79E
70:     0342 8E 77 03               STX  COLUMN
80:     0345 AD 26 03               LDA  IBSOUT
90:     0348 8D 78 03               STA  OLDOUT
100:    034B AD 27 03               LDA  IBSOUT+1
110:    034E 8D 79 03               STA  OLDOUT+1
120:    0351 A9 5C                  LDA  #<MAIN
130:    0353 8D 26 03               STA  IBSOUT
140:    0356 A9 03                  LDA  #>MAIN
150:    0358 8D 27 03               STA  IBSOUT+1
160:    035B 60                     RTS
                        ;
180:    035C C9 0D      MAIN        CMP  #13
190:    035E F0 08                  BEQ  DOCR
200:    0360 CE 7A 03               DEC  COUNT
210:    0363 D0 0B                  BNE  NADDCR
220:    0365 20 74 03               JSR  NEWPRT
230:    0368 AD 77 03 DOCR          LDA  COLUMN
240:    036B 8D 7A 03               STA  COUNT
250:    036E A9 0D                  LDA  #13
260:    0370 20 74 03 NADDCR        JSR  NEWPRT
```

```
270:    0373 60                 RTS
280:    0374 6C 78 03 NEWPRT    JMP   (OLDOUT)
290:    0377 50       COLUMN    .BYT  80
300:    0378          OLDOUT    =     *
310:    0378          COUNT     =     OLDOUT+2
]033C-0378

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
033C 20 FD AE     JSR $AEFD
033F 20 9E B7     JSR $B79E
0342 8E 77 03     STX $0377
0345 AD 26 03     LDA $0326
0348 8D 78 03     STA $0378
034B AD 27 03     LDA $0327
034E 8D 79 03     STA $0379
0351 A9 5C        LDA #$5C
0353 8D 26 03     STA $0326
0356 A9 03        LDA #$03
0358 8D 27 03     STA $0327
035B 60           RTS
035C C9 0D        CMP #$0D
035E F0 08        BEQ $0368
0360 CE 7A 03     DEC $037A
0363 D0 0B        BNE $0370
0365 20 74 03     JSR $0374
0368 AD 77 03     LDA $0377
036B 8D 7A 03     STA $037A
036E A9 0D        LDA #$0D
0370 20 74 03     JSR $0374
0373 60           RTS
0374 6C 78 03     JMP ($0378)
0377 50 00        BVC $0379
.
```

17. Old

This routine allows a program accidentally newed to be recovered. It also works after a SYS 64738 or SYS 58260 (cold or warm start). If the old routine is not in memory when you need it, do not worry: it can be loaded in after the new and executed and the program will still be recovered.

To use type SYS 300.

To load into memory after a new type LOAD"OLD",8,1 (or LOAD"OLD",1,1) and then SYS 300.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     012C                        .OPT P,OO
30:     012C                        *=   300
                              ;OLD ROUTINE
50:     012C A9 FF                  LDA  #$FF
60:     012E A0 01                  LDY  #1
70:     0130 91 2B                  STA  ($2B),BY
80:     0132 20 33 A5               JSR  $A533
90:     0135 A5 22                  LDA  $22
100:    0137 18                     CLC
110:    0138 69 02                  ADC  #2
110:    013A 85 2D                  STA  $2D
120:    013C A5 23                  LDA  $23
130:    013E 69 00                  ADC  #0
140:    0140 85 2E                  STA  $2E
150:    0142 4C 5E A6               JMP  $A65E
]012C-0145

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
.


B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
012C A9 FF      LDA #$FF
012E A0 01      LDY #$01
0130 91 2B      STA ($2B),Y
0132 20 33 A5   JSR $A533
0135 A5 22      LDA $22
0137 18         CLC
0138 69 02      ADC #$02
013A 85 2D      STA $2D
013C A5 23      LDA $23
013E 69 00      ADC #$00
0140 85 2E      STA $2E
0142 4C 5E A6   JMP $A65E
.
```

18. Graph

This routine is the graph (or high res) command. It turns on the high res screen which is located at 24576 and the colour memory at 16384. It does not clear the screen.

To use type SYS 49152.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     C000                        .OPT P,00
30:     C000                        *=   $C000
                              ;
                              ;GRAPH FUNCTION 26
                              ;
70:     C000 A9 16                  LDA  #$16
90:     C002 8D 00 DD               STA  56576
                              ;CHANGE BLOCK
                              ;
110:    C005 A9 08                  LDA  #8
120:    C007 8D 18 D0               STA  53272
                              ;
140:    C00A AD 11 D0               LDA  53265
140:    C00D 09 20                  ORA  #32
140:    C00F 8D 11 D0               STA  53265
150:    C012 60                     RTS
]C000-C013

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 ØØ ØØ Ø1 F6
.
CØØØ A9 16       LDA #$16
CØØ2 8D ØØ DD    STA $DDØØ
CØØ5 A9 Ø8       LDA #$Ø8
CØØ7 8D 18 DØ    STA $DØ18
CØØA AD 11 DØ    LDA $DØ11
CØØD Ø9 2Ø       ORA #$2Ø
CØØF 8D 11 DØ    STA $DØ11
CØ12 6Ø          RTS
.
```

19. NRM

This is the complementary routine to graph. It turns the high res screen off and returns to the normal text screen.

To use type SYS 49174.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     C016                        .OPT P,00
30:     C016                        *=   $C016
                          ;NORM COMMAND
50:     C016 A9 15                  LDA  #21
60:     C018 8D 18 D0               STA  53272
70:     C01B A9 1B                  LDA  #27
80:     C01D 8D 11 D0               STA  53265
90:     C020 A9 17                  LDA  #23
100:    C022 8D 00 DD               STA  56576
110:    C025 60                     RTS
1C016-C026

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
C016 A9 15        LDA #$15
C018 8D 18 D0     STA $D018
C01B A9 1B        LDA #$1B
C01D 8D 11 D0     STA $D011
C020 A9 17        LDA #$17
C022 8D 00 DD     STA $DD00
C025 60           RTS
.
```

20. CLG

This routine clears the high res screen. Two parameters are required. The first defines the drawing colour and the second the background colour. Both are values between 0 and 15 and are the same as the usual text colours.

To use type SYS 49190, drawing colour, background colour.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     C026                        .OPT P,OO
30:     C026                        *=   $C026
                              ; CLG COMMAND
50:     C026 20 FD AE               JSR  $AEFD
60:     C029 20 8A AD               JSR  $AD8A
70:     C02C 20 F7 B7               JSR  $B7F7
80:     C02F A5 15                  LDA  $15
80:     C031 F0 03                  BEQ  MORE
80:     C033 4C 48 B2               JMP  $B248
90:     C036 A5 14      MORE        LDA  $14
90:     C038 8D 85 C0               STA  FIN
100:    C03B 20 FD AE               JSR  $AEFD
110:    C03E 20 8A AD               JSR  $AD8A
120:    C041 20 F7 B7               JSR  $B7F7
130:    C044 A5 15                  LDA  $15
130:    C046 F0 03                  BEQ  MORE1
130:    C048 4C 48 B2               JMP  $B248
140:    C04B A5 14      MORE1       LDA  $14
140:    C04D 0A                     ASL  A
140:    C04E 0A                     ASL  A
140:    C04F 0A                     ASL  A
140:    C050 0A                     ASL  A
140:    C051 0D 85 C0               ORA  FIN
140:    C054 8D 85 C0               STA  FIN
```

```
150:    C057 A9 00              LDA  #0
150:    C059 85 FB              STA  $FB
160:    C05B A9 60              LDA  #96
160:    C05D 85 FC              STA  $FC
170:    C05F A0 00              LDY  #0
180:    C061 A9 00              LDA  #0
190:    C063 91 FB     LOOP     STA  ($FB),Y
200:    C065 C8                 INY
210:    C066 D0 FB              BNE  LOOP
220:    C068 E6 FC              INC  $FC
230:    C06A A6 FC              LDX  $FC
240:    C06C E0 80              CPX  #128
250:    C06E D0 F3              BNE  LOOP
260:    C070 AD 85 C0           LDA  FIN
270:    C073 A2 00              LDX  #0
280:    C075 9D 00 40 LOOP1     STA  $4000,X
290:    C078 9D 00 41           STA  $4100,X
300:    C07B 9D 00 42           STA  $4200,X
310:    C07E 9D 00 43           STA  $4300,X
320:    C081 E8                 INX
320:    C082 D0 F1              BNE  LOOP1
320:    C084 60                 RTS
330:    C085           FIN      =    *
]C026-C085

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
C026 20 FD AE    JSR $AEFD
C029 20 8A AD    JSR $AD8A
C02C 20 F7 B7    JSR $B7F7
C02F A5 15       LDA $15
C031 F0 03       BEQ $C036
C033 4C 48 B2    JMP $B248
C036 A5 14       LDA $14
```

```
C038 8D 85 C0     STA $C085
C03B 20 FD AE     JSR $AEFD
C03E 20 8A AD     JSR $AD8A
C041 20 F7 B7     JSR $B7F7
C044 A5 15        LDA $15
C046 F0 03        BEQ $C04B
C048 4C 48 B2     JMP $B248
C04B A5 14        LDA $14
C04D 0A           ASL
C04E 0A           ASL
C04F 0A           ASL
C050 0A           ASL
C051 0D 85 C0     ORA $C085
C054 8D 85 C0     STA $C085
C057 A9 00        LDA #$00
C059 85 FB        STA $FB
C05B A9 60        LDA #$60
C05D 85 FC        STA $FC
C05F A0 00        LDY #$00
C061 A9 00        LDA #$00
C063 91 FB        STA ($FB),Y
C065 C8           INY
C066 D0 FB        BNE $C063
C068 E6 FC        INC $FC
C06A A6 FC        LDX $FC
C06C E0 80        CPX #$80
C06E D0 F3        BNE $C063
C070 AD 85 C0     LDA $C085
C073 A2 00        LDX #$00
C075 9D 00 40     STA $4000,X
C078 9D 00 41     STA $4100,X
C07B 9D 00 42     STA $4200,X
C07E 9D 00 43     STA $4300,X
C081 E8           INX
C082 D0 F1        BNE $C075
C084 60           RTS
.
```

21. Plot

This routine plots a point on the high res screen . It requires two parameters: the X coordinate (0-319) and the Y coordinate (0-199) to be plotted.

The syntax is SYS 49286,X coord, Y coord.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     C08A                        .OPT P,OO
30:     C08A                        *=   $C08A
40:     C08A            XCOORD      =    $14


;AND $15
50:     C08A            TEMP        =    $FD
60:     C08A            SCREEN      =    $6000
70:     C08A            CHECKCOM    =    $AEFD
80:     C08A            COORD       =    $B7EB
90:     C08A            FALSE       =    255
100:    C08A            TRUE        =    0
130:    C08A A9 00      SET         LDA  #TRUE
140:    C08C 8D 3A C1   SET1        STA  RSFLAG

150:    C08F 20 FD AE               JSR  CHECKC
OM
160:    C092 20 EB B7               JSR  COORD
170:    C095 E0 C8                  CPX  #200
180:    C097 B0 5E                  BCS  TOOBIG

190:    C099 A5 14                  LDA  XCOORD

200:    C09B C9 40                  CMP  #<320
210:    C09D A5 15                  LDA  XCOORD
+1
```

```
220:    C09F E9 01              SBC  #>320
230:    C0A1 B0 54              BCS  TOOBIG

240:    C0A3 8A                 TXA
250:    C0A4 4A                 LSR
260:    C0A5 4A                 LSR
270:    C0A6 4A                 LSR
280:    C0A7 0A                 ASL
290:    C0A8 A8                 TAY
300:    C0A9 B9 F8 C0           LDA  TABLE,
Y       ;MULTIPLY PUT IN
310:    C0AC 85 FD              STA  TEMP
320:    C0AE B9 F9 C0           LDA  TABLE+
1,Y
330:    C0B1 85 FE              STA  TEMP+1

340:    C0B3 8A                 TXA
350:    C0B4 29 07              AND  #%0000
0111
360:    C0B6 18                 CLC
370:    C0B7 65 FD              ADC  TEMP
380:    C0B9 85 FD              STA  TEMP
390:    C0BB A5 FE              LDA  TEMP+1

400:    C0BD 69 00              ADC  #0
410:    C0BF 85 FE              STA  TEMP+1

420:    C0C1 A5 14              LDA  XCOORD

430:    C0C3 29 07              AND  #%0000
0111
440:    C0C5 A8                 TAY
450:    C0C6 A5 14              LDA  XCOORD

460:    C0C8 29 F8              AND  #%1111
1000
470:    C0CA 18                 CLC
480:    C0CB 65 FD              ADC  TEMP
490:    C0CD 85 FD              STA  TEMP
500:    C0CF A5 FE              LDA  TEMP+1
```

```
510:    C0D1 65 15              ADC   XCOORD
+1
520:    C0D3 85 FE              STA   TEMP+1

530:    C0D5 A5 FD              LDA   TEMP
540:    C0D7 18                 CLC
550:    C0D8 69 00              ADC   #<SCRE
EN
560:    C0DA 85 FD              STA   TEMP
570:    C0DC A5 FE              LDA   TEMP+1

580:    C0DE 69 60              ADC   #>SCRE
EN
590:    C0E0 85 FE              STA   TEMP+1

600:    C0E2 A2 00              LDX   #0
610:    C0E4 A1 FD              LDA   (TEMP,
X)
620:    C0E6 2C 3A C1           BIT   RSFLAG

630:    C0E9 10 06              BPL   SET2
640:    C0EB 39 32 C1           AND   ANDMAS
K,Y
650:    C0EE 4C F4 C0           JMP   SET3
660:    C0F1 19 2A C1 SET2      ORA   ORMASK
,Y
670:    C0F4 81 FD    SET3      STA   (TEMP,
X)
680:    C0F6 60                 RTS
690:    C0F7 60       TOOBIG    RTS
700:    C0F8          N         =     320
710:    C0F8 00 00 40 TABLE     .WORD0*N,1*
N,2*N,3*N,4*N
720:    C102 40 06 80           .WORD5*N,6*
N,7*N,8*N,9*N
730:    C10C 80 0C C0           .WORD10*N,1
1*N,12*N,13*N,14*N
740:    C116 C0 12 00           .WORD15*N,1
6*N,17*N,18*N,19*N
750:    C120 00 19 40           .WORD20*N,2
1*N,22*N,23*N,24*N
```

```
                                ;
770:    C12A 80         ORMASK  .BYT %10000
000
780:    C12B 40                 .BYT %01000
000
790:    C12C 20                 .BYT %00100
000
800:    C12D 10                 .BYT %00010
000
810:    C12E 08                 .BYT %00001
000
820:    C12F 04                 .BYT %00000
100
830:    C130 02                 .BYT %00000
010
840:    C131 01                 .BYT %00000
001
                                ;
860:    C132 7F         ANDMASK .BYT %01111
111
870:    C133 BF                 .BYT %10111
111
880:    C134 DF                 .BYT %11011
111
890:    C135 EF                 .BYT %11101
111
900:    C136 F7                 .BYT %11110
111
910:    C137 FB                 .BYT %11111
011
920:    C138 FD                 .BYT %11111
101
930:    C139 FE                 .BYT %11111
110
                                ;
950:    C13A 00         RSFLAG  .BYT 0
]C08A-C13B

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 ØØ ØØ Ø1 F6
.
CØ8A A9 ØØ      LDA ##$ØØ
CØ8C 8D 3A C1    STA $C13A
CØ8F 2Ø FD AE    JSR $AEFD
CØ92 2Ø EB B7    JSR $B7EB
CØ95 EØ C8       CPX ##$C8
CØ97 BØ 5E       BCS $CØF7
CØ99 A5 14       LDA $14
CØ9B C9 4Ø       CMP ##$4Ø
CØ9D A5 15       LDA $15
CØ9F E9 Ø1       SBC ##$Ø1
CØA1 BØ 54       BCS $CØF7
CØA3 8A          TXA
CØA4 4A          LSR
CØA5 4A          LSR
CØA6 4A          LSR
CØA7 ØA          ASL
CØA8 A8          TAY
CØA9 B9 F8 CØ    LDA $CØF8,Y
CØAC 85 FD       STA $FD
CØAE B9 F9 CØ    LDA $CØF9,Y
CØB1 85 FE       STA $FE
CØB3 8A          TXA
CØB4 29 Ø7       AND ##$Ø7
CØB6 18          CLC
CØB7 65 FD       ADC $FD
CØB9 85 FD       STA $FD
CØBB A5 FE       LDA $FE
CØBD 69 ØØ       ADC ##$ØØ
CØBF 85 FE       STA $FE
CØC1 A5 14       LDA $14
CØC3 29 Ø7       AND ##$Ø7
CØC5 A8          TAY
CØC6 A5 14       LDA $14
CØC8 29 F8       AND ##$F8
CØCA 18          CLC
CØCB 65 FD       ADC $FD
CØCD 85 FD       STA $FD
```

```
C0CF A5 FE        LDA $FE
C0D1 65 15        ADC #15
C0D3 85 FE        STA $FE
C0D5 A5 FD        LDA $FD
C0D7 18           CLC
C0D8 69 00        ADC #$00
C0DA 85 FD        STA $FD
C0DC A5 FE        LDA $FE
C0DE 69 60        ADC #$60
C0E0 85 FE        STA $FE
C0E2 A2 00        LDX #$00
C0E4 A1 FD        LDA ($FD,X)
C0E6 2C 3A C1     BIT $C13A
C0E9 10 06        BPL $C0F1
C0EB 39 32 C1     AND $C132,Y
C0EE 4C F4 C0     JMP $C0F4
C0F1 19 2A C1     ORA $C12A,Y
C0F4 81 FD        STA ($FD,X)
C0F6 60           RTS
C0F7 60           RTS
.
.
.
.
.:C0F8 00 00 40 01 80 02 C0 03
.:C100 00 05 40 06 80 07 C0 08
.:C108 00 0A 40 0B 80 0C C0 0D
.:C110 00 0F 40 10 80 11 C0 12
.:C118 00 14 40 15 80 16 C0 17
.:C120 00 19 40 1A 80 1B C0 1C
.:C128 00 1E 80 40 20 10 08 04
.:C130 02 01 7F BF DF EF F7 FB
.:C138 FD FE 00 C2 C9 F0 08 20
.
```

22. Unplot

This routine is complementary to Plot. It unplots a point on the high res screen. Just type in the routine below and unplot is ready.

To use type SYS 49286,X,Y

```
30 *=$C086
40 LDA #$FF
50 BNE SET1

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
C086 A9 FF        LDA #$FF
C088 D0 02        BNE $C08C
.
```

23. Char

This routine puts a character onto the high res screen. You specify three parameters: the X coordinate (0-39), the Y coordinate (0-24) and the character code (screen code).

The syntax is SYS 49467,X,Y,char code

```
PAL (C)1979 BRAD TEMPLETON
2
20:     C13B                        .OPT P,OO
30:     C13B                        *=   $C13B
                                ;
                                ;CHAR X,Y,CHARACTER,
                                ;EOR OR DELETE
70:     C13B 4C 48 B2 ERROR         JMP  $B248
80:     C13E 20 FD AE               JSR  $AEFD
90:     C141 20 1D C2               JSR  PARAMS
100:    C144 A5 14                  LDA  $14
100:    C146 C9 28                  CMP  #40
100:    C148 B0 F1                  BCS  ERROR
110:    C14A 8D 4B C2               STA  XSTORE
120:    C14D 20 FD AE               JSR  $AEFD
130:    C150 20 1D C2               JSR  PARAMS
140:    C153 A5 14                  LDA  $14
140:    C155 C9 19                  CMP  #25
140:    C157 B0 E2                  BCS  ERROR
150:    C159 8D 4C C2               STA  YSTORE
                                ;TOTAL = Y*320 + X*8
170:    C15C AD 4B C2               LDA  XSTORE
180:    C15F 8D 48 C2               STA  MULT1
190:    C162 A9 08                  LDA  #8
200:    C164 8D 49 C2               STA  MULT2
210:    C167 20 2B C2               JSR  MULTIPLY
220:    C16A AD 46 C2               LDA  RESULT
```

```
230:   C16D 85 FB              STA  $FB
240:   C16F AD 47 C2           LDA  RESULT+1
250:   C172 85 FC              STA  $FC
                               ;
                               ;NOW Y=320*Y
280:   C174 AD 4C C2           LDA  YSTORE
290:   C177 8D 48 C2           STA  MULT1
300:   C17A A9 28              LDA  #40
310:   C17C 8D 49 C2           STA  MULT2
320:   C17F 20 2B C2           JSR  MULTIPLY
330:   C182 AD 46 C2           LDA  RESULT
330:   C185 8D 50 C2           STA  STORERES
330:   C188 AD 47 C2           LDA  RESULT+1
330:   C18B 8D 51 C2           STA  STORERES+1
340:   C18E A2 07              LDX  #7
350:   C190 AD 46 C2 LOOP12    LDA  RESULT
350:   C193 6D 50 C2           ADC  STORERES
360:   C196 8D 46 C2           STA  RESULT
360:   C199 AD 47 C2           LDA  RESULT+1
370:   C19C 69 00              ADC  #0
370:   C19E 8D 47 C2           STA  RESULT+1
380:   C1A1 CA                 DEX
390:   C1A2 D0 EC              BNE  LOOP12
400:   C1A4 A2 07              LDX  #7
410:   C1A6 AD 47 C2 LOOP14    LDA  RESULT+1
420:   C1A9 18                 CLC
420:   C1AA 6D 51 C2           ADC  STORERES+1
430:   C1AD 8D 47 C2           STA  RESULT+1
440:   C1B0 CA                 DEX
450:   C1B1 D0 F3              BNE  LOOP14
460:   C1B3 AD 47 C2           LDA  RESULT+1
470:   C1B6 18                 CLC
470:   C1B7 69 60              ADC  #$60
480:   C1B9 8D 47 C2           STA  RESULT+1
490:   C1BC A5 FB              LDA  $FB
500:   C1BE 18                 CLC
500:   C1BF 6D 46 C2           ADC  RESULT
510:   C1C2 85 FB              STA  $FB
520:   C1C4 A5 FC              LDA  $FC
530:   C1C6 6D 47 C2           ADC  RESULT+1
540:   C1C9 85 FC              STA  $FC
```

```
550:   C1CB 20 FD AE          JSR  $AEFD
560:   C1CE 20 1D C2          JSR  PARAMS
570:   C1D1 A5 14             LDA  $14
580:   C1D3 8D 4E C2          STA  CHAR
590:   C1D6 AD 4E C2          LDA  CHAR
600:   C1D9 8D 48 C2          STA  MULT1
610:   C1DC A9 08             LDA  #8
620:   C1DE 8D 49 C2          STA  MULT2
630:   C1E1 20 2B C2          JSR  MULTIPLY
640:   C1E4 AD 46 C2          LDA  RESULT
                          ;CHARACTER LOCATION
650:   C1E7 85 FD             STA  $FD
660:   C1E9 AD 47 C2          LDA  RESULT+1
670:   C1EC 18                CLC
                          ;ADD $D0 TO $D000
670:   C1ED 69 D0             ADC  #$D0
680:   C1EF 85 FE             STA  $FE
690:   C1F1 A9 00             LDA  #0
690:   C1F3 8D 4A C2          STA  COUNT
690:   C1F6 78                SEI
690:   C1F7 A9 33             LDA  #51
690:   C1F9 85 01             STA  $01
700:   C1FB A0 00             LDY  #0
710:   C1FD B1 FD     LOOP1   LDA  ($FD),Y
720:   C1FF 91 FB             STA  ($FB),Y
730:   C201 E6 FB             INC  $FB
730:   C203 D0 02             BNE  N1
740:   C205 E6 FC             INC  $FC
750:   C207 E6 FD     N1      INC  $FD
760:   C209 D0 02             BNE  N2
770:   C20B E6 FE             INC  $FE
780:   C20D EE 4A C2  N2      INC  COUNT
790:   C210 AD 4A C2          LDA  COUNT
800:   C213 C9 08             CMP  #8
810:   C215 D0 E6             BNE  LOOP1
820:   C217 A9 37             LDA  #55
820:   C219 85 01             STA  1
820:   C21B 58                CLI
820:   C21C 60                RTS
830:   C21D 20 8A AD  PARAMS  JSR  $AD8A
840:   C220 20 F7 B7          JSR  $B7F7
```

```
850:   C223 A5 15            LDA  $15
850:   C225 F0 03            BEQ  FINROUT
860:   C227 4C 48 B2         JMP  $B248
860:   C22A 60         FINROUT RTS
870:   C22B A9 00      MULTIPLY LDA  #0
880:   C22D 8D 46 C2         STA  RESULT
890:   C230 A2 08            LDX  #8
900:   C232 4E 48 C2 LOOP21   LSR  MULT1
910:   C235 90 04            BCC  LOOP9
920:   C237 18               CLC
930:   C238 6D 49 C2         ADC  MULT2
940:   C23B 6A         LOOP9 ROR  A
950:   C23C 6E 46 C2         ROR  RESULT
960:   C23F CA               DEX
970:   C240 D0 F0            BNE  LOOP21
980:   C242 8D 47 C2         STA  RESULT+1
990:   C245 60               RTS
1000:  C246 00 00      RESULT .WORD0
1010:  C248 00         MULT1  .BYT 0
1020:  C249 00         MULT2  .BYT 0
1030:  C24A 00         COUNT  .BYT 0
1040:  C24B 00         XSTORE .BYT 0
1050:  C24C 00         YSTORE .BYT 0
1060:  C24D 00         EORFLAG .BYT 0
1070:  C24E 00         CHAR   .BYT 0
1080:  C24F 00         STORE  .BYT 0
1090:  C250 00 00      STORERES .WORD0
]C13B-C252

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
C13B 4C 48 B2    JMP $B248
C13E 20 FD AE    JSR $AEFD
C141 20 1D C2    JSR $C21D
```

```
C144 A5 14       LDA $14
C146 C9 28       CMP #$28
C148 B0 F1       BCS $C13B
C14A 8D 4B C2    STA $C24B
C14D 20 FD AE    JSR $AEFD
C150 20 1D C2    JSR $C21D
C153 A5 14       LDA $14
C155 C9 19       CMP #$19
C157 B0 E2       BCS $C13B
C159 8D 4C C2    STA $C24C
C15C AD 4B C2    LDA $C24B
C15F 8D 48 C2    STA $C248
C162 A9 08       LDA #$08
C164 8D 49 C2    STA $C249
C167 20 2B C2    JSR $C22B
C16A AD 46 C2    LDA $C246
C16D 85 FB       STA $FB
C16F AD 47 C2    LDA $C247
C172 85 FC       STA $FC
C174 AD 4C C2    LDA $C24C
C177 8D 48 C2    STA $C248
C17A A9 28       LDA #$28
C17C 8D 49 C2    STA $C249
C17F 20 2B C2    JSR $C22B
C182 AD 46 C2    LDA $C246
C185 8D 50 C2    STA $C250
C188 AD 47 C2    LDA $C247
C18B 8D 51 C2    STA $C251
C18E A2 07       LDX #$07
C190 AD 46 C2    LDA $C246
C193 6D 50 C2    ADC $C250
C196 8D 46 C2    STA $C246
C199 AD 47 C2    LDA $C247
C19C 69 00       ADC #$00
C19E 8D 47 C2    STA $C247
C1A1 CA          DEX
C1A2 D0 EC       BNE $C190
C1A4 A2 07       LDX #$07
C1A6 AD 47 C2    LDA $C247
C1A9 18          CLC
C1AA 6D 51 C2    ADC $C251
```

```
C1AD 8D 47 C2    STA $C247
C1B0 CA          DEX
C1B1 D0 F3       BNE $C1A6
C1B3 AD 47 C2    LDA $C247
C1B6 18          CLC
C1B7 69 60       ADC #$60
C1B9 8D 47 C2    STA $C247
C1BC A5 FB       LDA $FB
C1BE 18          CLC
C1BF 6D 46 C2    ADC $C246
C1C2 85 FB       STA $FB
C1C4 A5 FC       LDA $FC
C1C6 6D 47 C2    ADC $C247
C1C9 85 FC       STA $FC
C1CB 20 FD AE    JSR $AEFD
C1CE 20 1D C2    JSR $C21D
C1D1 A5 14       LDA $14
C1D3 8D 4E C2    STA $C24E
C1D6 AD 4E C2    LDA $C24E
C1D9 8D 48 C2    STA $C248
C1DC A9 08       LDA #$08
C1DE 8D 49 C2    STA $C249
C1E1 20 2B C2    JSR $C22B
C1E4 AD 46 C2    LDA $C246
C1E7 85 FD       STA $FD
C1E9 AD 47 C2    LDA $C247
C1EC 18          CLC
C1ED 69 D0       ADC #$D0
C1EF 85 FE       STA $FE
C1F1 A9 00       LDA #$00
C1F3 8D 4A C2    STA $C24A
C1F6 78          SEI
C1F7 A9 33       LDA #$33
C1F9 85 01       STA $01
C1FB A0 00       LDY #$00
C1FD B1 FD       LDA ($FD),Y
C1FF 91 FB       STA ($FB),Y
C201 E6 FB       INC $FB
C203 D0 02       BNE $C207
C205 E6 FC       INC $FC
C207 E6 FD       INC $FD
```

```
C209 D0 02       BNE $C20D
C20B E6 FE       INC $FE
C20D EE 4A C2    INC $C24A
C210 AD 4A C2    LDA $C24A
C213 C9 08       CMP #$08
C215 D0 E6       BNE $C1FD
C217 A9 37       LDA #$37
C219 85 01       STA $01
C21B 58          CLI
C21C 60          RTS
C21D 20 8A AD    JSR $AD8A
C220 20 F7 B7    JSR $B7F7
C223 A5 15       LDA $15
C225 F0 03       BEQ $C22A
C227 4C 48 B2    JMP $B248
C22A 60          RTS
C22B A9 00       LDA #$00
C22D 8D 46 C2    STA $C246
C230 A2 08       LDX #$08
C232 4E 48 C2    LSR $C248
C235 90 04       BCC $C23B
C237 18          CLC
C238 6D 49 C2    ADC $C249
C23B 6A          ROR
C23C 6E 46 C2    ROR $C246
C23F CA          DEX
C240 D0 F0       BNE $C232
C242 8D 47 C2    STA $C247
C245 60          RTS
.
.
.
.
.:C246 00 00 00 00 00 00 00 00
.:C24E 00 00 00 00 10 CF A5 BA
.
```

24. Change bank

This routine allows easy access to the four 16K banks accessible by the VIC II chip. It does not copy the character set down. To do this, use the copy routine given above.

The syntax is SYS 828, bank (0-3)

where bank 0 is 0-16383 , 1 is 16384 to 32767 and so on.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     033C                    .OPT P,00
30:     033C                    *=   828
                          ;
                          ;ROUTINE TO CHANGE
                          ; BANK FOR
                          ;VIC II CHIP
                          ;
                          ;SYNTAX
                          ;
                          ;SYS 828,BANK (0-3)
                          ;
130:    033C 20 FD AE           JSR  $AEFD
140:    033F 20 9E B7           JSR  $B79E
150:    0342 8A                 TXA
160:    0343 C9 05              CMP  #5
170:    0345 90 03              BCC  MORE
180:    0347 4C 48 B2           JMP  $B248
                          ;
200:    034A AA           MORE  TAX
210:    034B BD 63 03           LDA  L53272,X
220:    034E 8D 18 D0           STA  53272
230:    0351 BD 67 03           LDA  L648,X
240:    0354 8D 88 02           STA  648
```

```
250:    0357 BD 6B 03          LDA  L56576,X
260:    035A 8D 00 DD          STA  56576
270:    035D A9 93             LDA  #"*
280:    035F 20 D2 FF          JSR  $FFD2
290:    0362 60                RTS
                        ;
310:    0363 15 15 15 L53272   .BYT 21,21,21,21
320:    0367 04 04 04 L648     .BYT 4,4,4,4
330:    036B 47 46 45 L56576   .BYT 71,70,69,68
]033C-036F

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
033C 20 FD AE     JSR $AEFD
033F 20 9E B7     JSR $B79E
0342 8A           TXA
0343 C9 05        CMP #$05
0345 90 03        BCC $034A
0347 4C 48 B2     JMP $B248
034A AA           TAX
034B BD 63 03     LDA $0363,X
034E 8D 18 D0     STA $D018
0351 BD 67 03     LDA $0367,X
0354 8D 88 02     STA $0288
0357 BD 6B 03     LDA $036B,X
035A 8D 00 DD     STA $DD00
035D A9 93        LDA #$93
035F 20 D2 FF     JSR $FFD2
0362 60           RTS
.
.
.
.
.:0363 15 15 15 15 04 04 04 04
.:036B 47 46 45 44 0D 20 74 03
.
```

25. Invert

This routine inverts all or some of the high res screen (it can invert any part of memory).

The syntax is SYS 49746,start,invert

```
PAL (C)1979 BRAD TEMPLETON
2
20:     C252                    .OPT P,OO
30:     C252                    *=   $C252
                        ;FILL ROUTINE
                        ;
                        ;USES $FB AND $FC
                        ;STORE TOP ADDRESS
                        ;IN 828 AND 829
                        ;SCAN PAST COMMA
90:     C252 20 FD AE           JSR  $AEFD
                        ;READ 16 BIT NUMBER
100:    C255 20 8A AD           JSR  $AD8A
                        ;PUT INTO $14 AND $15
110:    C258 20 F7 B7           JSR  $B7F7
120:    C25B A5 14              LDA  $14
120:    C25D 85 FB              STA  $FB
130:    C25F A5 15              LDA  $15
130:    C261 85 FC              STA  $FC
                        ;
150:    C263 20 FD AE           JSR  $AEFD
                        ;SCAN PAST NEXT COMMA
160:    C266 20 8A AD           JSR  $AD8A
170:    C269 20 F7 B7           JSR  $B7F7
180:    C26C A5 14              LDA  $14
180:    C26E 8D 3C 03           STA  828
190:    C271 A5 15              LDA  $15
190:    C273 8D 3D 03           STA  829
```

```
                          ;
210:    C276 A0 00     LOOP      LDY  #0
220:    C278 A9 FF               LDA  #255
230:    C27A 51 FB               EOR  ($FB),Y
240:    C27C 91 FB               STA  ($FB),Y
250:    C27E 20 95 C2            JSR  ADD
260:    C281 A5 FB               LDA  $FB
260:    C283 CD 3C 03            CMP  828
260:    C286 F0 03               BEQ  CHECK
270:    C288 4C 76 C2            JMP  LOOP
280:    C28B A5 FC     CHECK     LDA  $FC
280:    C28D CD 3D 03            CMP  829
280:    C290 F0 0B               BEQ  FINISH
290:    C292 4C 76 C2            JMP  LOOP
300:    C295 E6 FB     ADD       INC  $FB
300:    C297 F0 01               BEQ  FCPLUS1
310:    C299 60                  RTS
320:    C29A E6 FC     FCPLUS1   INC  $FC
320:    C29C 60                  RTS
330:    C29D 60        FINISH    RTS
]C252-C29E

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
C252 20 FD AE    JSR $AEFD
C255 20 8A AD    JSR $AD8A
C258 20 F7 B7    JSR $B7F7
C25B A5 14       LDA $14
C25D 85 FB       STA $FB
C25F A5 15       LDA $15
C261 85 FC       STA $FC
C263 20 FD AE    JSR $AEFD
```

```
C266 20 8A AD     JSR $AD8A
C269 20 F7 B7     JSR $B7F7
C26C A5 14        LDA $14
C26E 8D 3C 03     STA $033C
C271 A5 15        LDA $15
C273 8D 3D 03     STA $033D
C276 A0 00        LDY #$00
C278 A9 FF        LDA #$FF
C27A 51 FB        EOR ($FB),Y
C27C 91 FB        STA ($FB),Y
C27E 20 95 C2     JSR $C295
C281 A5 FB        LDA $FB
C283 CD 3C 03     CMP $033C
C286 F0 03        BEQ $C28B
C288 4C 76 C2     JMP $C276
C28B A5 FC        LDA $FC
C28D CD 3D 03     CMP $033D
C290 F0 0B        BEQ $C29D
C292 4C 76 C2     JMP $C276
C295 E6 FB        INC $FB
C297 F0 01        BEQ $C29A
C299 60           RTS
C29A E6 FC        INC $FC
C29C 60           RTS
C29D 60           RTS
.
```

26. Organ

The following is a simple interrupt driven organ program. It allows you to play a tune on the keyboard whether a program is running or not. The program could run with a sound shaping program, for example.

The keys used are as follows:

q w e r t y u i o p @ * ↑
and the space bar to turn the notes off

To turn on the organ type SYS 49152.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     C000                        .OPT P,OO
30:     C000                        *=   $C000
                              ;
50:     C000 78                     SEI
50:     C001 A9 1F                  LDA  #<MAIN

50:     C003 8D 14 03               STA  788
60:     C006 A9 C0                  LDA  #>MAIN

60:     C008 8D 15 03               STA  789
70:     C00B A9 0F                  LDA  #15
70:     C00D 8D 18 D4               STA  54296
70:     C010 A9 21                  LDA  #33
70:     C012 8D 04 D4               STA  54276
70:     C015 A9 38                  LDA  #<56
70:     C017 8D 05 D4               STA  54277
70:     C01A 8D 06 D4               STA  54278
70:     C01D 58                     CLI
70:     C01E 60                     RTS
```

```
                        ;
90:     C01F A5 C5      MAIN    LDA  197
100:    C021 A2 00              LDX  #0
100:    C023 A0 00              LDY  #0
110:    C025 DD 43 C0   LOOP    CMP  KEYDAT
A,X
120:    C028 F0 0A              BEQ  PLAYNO
TE
130:    C02A E8                 INX
130:    C02B C8                 INY
130:    C02C C8                 INY
140:    C02D E0 0F              CPX  #15
150:    C02F D0 F4              BNE  LOOP
160:    C031 4C 31 EA           JMP  $EA31
                        ;
180:    C034            PLAYNOTE =   *
190:    C034 B9 51 C0           LDA  NOTETA
BLE,Y
190:    C037 8D 01 D4           STA  54273
190:    C03A B9 52 C0           LDA  NOTETA
BLE+1,Y
190:    C03D 8D 00 D4           STA  54272
200:    C040 4C 31 EA           JMP  $EA31
210:    C043 3E 09 0E KEYDATA   .BYT 62,9,1
4,17,22,25,30,33,38,41
220:    C04D 2E 31 36           .BYT 46,49,
54,60
                        ;
240:    C051 11 25 13 NOTETABLE.BYT 17,37,
19,63,21,154,22,227
250:    C059 19 B1 1C           .BYT 25,177
,28,214,32,94,34,75,38,126,43,52
260:    C065 2D C6 33           .BYT 45,198
,51,97,57,172,0,0
]C000-C06D
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
```

```
.
C000 78          SEI
C001 A9 1F       LDA #$1F
C003 8D 14 03    STA $0314
C006 A9 C0       LDA #$C0
C008 8D 15 03    STA $0315
C00B A9 0F       LDA #$0F
C00D 8D 18 D4    STA $D418
C010 A9 21       LDA #$21
C012 8D 04 D4    STA $D404
C015 A9 38       LDA #$38
C017 8D 05 D4    STA $D405
C01A 8D 06 D4    STA $D406
C01D 58          CLI
C01E 60          RTS
C01F A5 C5       LDA $C5
C021 A2 00       LDX #$00
C023 A0 00       LDY #$00
C025 DD 43 C0    CMP $C043,X
C028 F0 0A       BEQ $C034
C02A E8          INX
C02B C8          INY
C02C C8          INY
C02D E0 0F       CPX #$0F
C02F D0 F4       BNE $C025
C031 4C 31 EA    JMP $EA31
C034 B9 51 C0    LDA $C051,Y
C037 8D 01 D4    STA $D401
C03A B9 52 C0    LDA $C052,Y
C03D 8D 00 D4    STA $D400
C040 4C 31 EA    JMP $EA31
.
.
.:C043 3E 09 0E 11 16 19 1E 21
.:C04B 26 29 2E 31 36 3C 11 25
.:C053 13 3F 15 9A 16 E3 19 B1
.:C05B 1C D6 20 5E 22 4B 26 7E
.:C063 2B 34 2D C6 33 61 39 AC
.:C06B 00 00 80 D0 F3 AD 85 C0
.
```

27. Sound

This routine makes sound much easier to use. It allows you to set the voice, volume, frequency and waveform for the sound.

The syntax is SYS 16384,voice,volume,frequency,waveform.

The voice is between 1 and 3. The volume is between 0 and 15. The frequency is between 0 and 65535. The waveform is one of 17 (triangle), 33 (sawtooth) and 129 (noise). Pulse waveform is not implemented. It can be set but it will not function.

The ADSR and all other features of the SID chip are set automatically.

To produce a rising tone the following routine could be used.

```
FOR A = 0 TO 65535 STEP100 :
SYS16384,1,15,A,33:NEXT:SYS16384,1,0,0,33
```

The last statement turns off the sound.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                    .OPT P,OO
30:     4000                    *=    $4000
                          ;
                          ; SOUND ROUTINE
                          ;
                          ;SYNTAX ;
                          ;
                          ; SYS 16384,VOICE,
                          ; VOLUME,FREQ,WAVE
110:    4000 20 FD AE           JSR   $AEFD
120:    4003 20 8A AD           JSR   $AD8A
```

```
130:   4006 20 F7 B7          JSR  $B7F7
140:   4009 A5 15             LDA  $15
150:   400B D0 3F             BNE  IQERR
160:   400D A5 14             LDA  $14
170:   400F 8D DA 40          STA  VOICE
                              ;
190:   4012 20 FD AE          JSR  $AEFD
200:   4015 20 8A AD          JSR  $AD8A
210:   4018 20 F7 B7          JSR  $B7F7
220:   401B A5 15             LDA  $15
230:   401D D0 2D             BNE  IQERR
240:   401F A5 14             LDA  $14
250:   4021 8D DB 40          STA  VOLUME
                              ;
270:   4024 20 FD AE          JSR  $AEFD
280:   4027 20 8A AD          JSR  $AD8A
290:   402A 20 F7 B7          JSR  $B7F7
300:   402D A5 14             LDA  $14
310:   402F 8D DD 40          STA  FREQ
320:   4032 A5 15             LDA  $15
330:   4034 8D DE 40          STA  FREQ+1
                              ;
350:   4037 20 FD AE          JSR  $AEFD
360:   403A 20 8A AD          JSR  $AD8A
370:   403D 20 F7 B7          JSR  $B7F7
380:   4040 A5 15             LDA  $15
390:   4042 D0 08             BNE  IQERR
400:   4044 A5 14             LDA  $14
410:   4046 8D DC 40          STA  WAVE
420:   4049 4C 4F 40          JMP  DO
430:   404C 4C 48 B2 IQERR    JMP  $B248
                              ;
450:   404F A2 00       DO    LDX  #0
450:   4051 AD DC 40          LDA  WAVE
460:   4054 DD DF 40 LOP      CMP  WAVETABLE,X
470:   4057 F0 08             BEQ  MORE
480:   4059 E8                INX
480:   405A E0 04             CPX  #4
490:   405C D0 F6             BNE  LOP
500:   405E 4C 4C 40          JMP  IQERR
510:   4061 AD DA 40 MORE     LDA  VOICE
```

```
520:   4064 F0 E6              BEQ  IQERR
530:   4066 C9 04              CMP  #4
540:   4068 B0 E2              BCS  IQERR
                        ;
560:   406A AD DB 40           LDA  VOLUME
570:   406D C9 10              CMP  #16
580:   406F B0 DB              BCS  IQERR
                        ;
600:   4071 AD DB 40           LDA  VOLUME
610:   4074 8D 18 D4           STA  54296
                        ;
630:   4077 AD DA 40           LDA  VOICE
                        ;
650:   407A C9 01              CMP  #1
660:   407C F0 07              BEQ  VOICE1
670:   407E C9 02              CMP  #2
680:   4080 F0 20              BEQ  VOICE2
690:   4082 4C BF 40           JMP  VOICE3
                        ;
710:   4085 AD DC 40 VOICE1    LDA  WAVE
720:   4088 8D 04 D4           STA  54276
730:   408B A9 80              LDA  #128
740:   408D 8D 05 D4           STA  54277
750:   4090 8D 06 D4           STA  54278
760:   4093 AD DD 40           LDA  FREQ
770:   4096 8D 00 D4           STA  54272
780:   4099 AD DE 40           LDA  FREQ+1
790:   409C 8D 01 D4           STA  54273
800:   409F 4C D9 40           JMP  FINISH
                        ;
820:   40A2 AD DC 40 VOICE2    LDA  WAVE
830:   40A5 8D 0B D4           STA  54283
840:   40A8 A9 80              LDA  #128
850:   40AA 8D 0C D4           STA  54284
860:   40AD 8D 0D D4           STA  54285
870:   40B0 AD DD 40           LDA  FREQ
880:   40B3 8D 07 D4           STA  54279
890:   40B6 AD DE 40           LDA  FREQ+1
900:   40B9 8D 08 D4           STA  54280
910:   40BC 4C D9 40           JMP  FINISH
                        ;
```

```
930:    40BF AD DC 40 VOICE3   LDA  WAVE
940:    40C2 8D 12 D4          STA  54290
950:    40C5 A9 80             LDA  #128
960:    40C7 8D 13 D4          STA  54291
970:    40CA 8D 14 D4          STA  54292
980:    40CD AD DD 40          LDA  FREQ
990:    40D0 8D 0E D4          STA  54286
1000:   40D3 AD DE 40          LDA  FREQ+1
1010:   40D6 8D 0F D4          STA  54287
                               ;
1030:   40D9 60        FINISH  RTS
1040:   40DA 00        VOICE   .BYT 0
1050:   40DB 00        VOLUME  .BYT 0
1060:   40DC 00        WAVE    .BYT 0
1070:   40DD 00 00     FREQ    .WORD0
1080:   40DF 11 21 41 WAVETABLE.BYT 17,33,65,129
]4000-40E3

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
4000 20 FD AE     JSR $AEFD
4003 20 8A AD     JSR $AD8A
4006 20 F7 B7     JSR $B7F7
4009 A5 15        LDA $15
400B D0 3F        BNE $404C
400D A5 14        LDA $14
400F 8D DA 40     STA $40DA
4012 20 FD AE     JSR $AEFD
4015 20 8A AD     JSR $AD8A
4018 20 F7 B7     JSR $B7F7
401B A5 15        LDA $15
401D D0 2D        BNE $404C
401F A5 14        LDA $14
```

```
4021 8D DB 40     STA $40DB
4024 20 FD AE     JSR $AEFD
4027 20 8A AD     JSR $AD8A
402A 20 F7 B7     JSR $B7F7
402D A5 14        LDA $14
402F 8D DD 40     STA $40DD
4032 A5 15        LDA $15
4034 8D DE 40     STA $40DE
4037 20 FD AE     JSR $AEFD
403A 20 8A AD     JSR $AD8A
403D 20 F7 B7     JSR $B7F7
4040 A5 15        LDA $15
4042 D0 08        BNE $404C
4044 A5 14        LDA $14
4046 8D DC 40     STA $40DC
4049 4C 4F 40     JMP $404F
404C 4C 48 B2     JMP $B248
404F A2 00        LDX #$00
4051 AD DC 40     LDA $40DC
4054 DD DF 40     CMP $40DF,X
4057 F0 08        BEQ $4061
4059 E8           INX
405A E0 04        CPX #$04
405C D0 F6        BNE $4054
405E 4C 4C 40     JMP $404C
4061 AD DA 40     LDA $40DA
4064 F0 E6        BEQ $404C
4066 C9 04        CMP #$04
4068 B0 E2        BCS $404C
406A AD DB 40     LDA $40DB
406D C9 10        CMP #$10
406F B0 DB        BCS $404C
4071 AD DB 40     LDA $40DB
4074 8D 18 D4     STA $D418
4077 AD DA 40     LDA $40DA
407A C9 01        CMP #$01
407C F0 07        BEQ $4085
407E C9 02        CMP #$02
4080 F0 20        BEQ $40A2
4082 4C BF 40     JMP $40BF
4085 AD DC 40     LDA $40DC
```

```
40B8 8D 04 D4     STA $D404
40BB A9 80        LDA #$80
40BD 8D 05 D4     STA $D405
40C0 8D 06 D4     STA $D406
40C3 AD DD 40     LDA $40DD
40C6 8D 00 D4     STA $D400
40C9 AD DE 40     LDA $40DE
40CC 8D 01 D4     STA $D401
40CF 4C D9 40     JMP $40D9
40A2 AD DC 40     LDA $40DC
40A5 8D 0B D4     STA $D40B
40A8 A9 80        LDA #$80
40AA 8D 0C D4     STA $D40C
40AD 8D 0D D4     STA $D40D
40B0 AD DD 40     LDA $40DD
40B3 8D 07 D4     STA $D407
40B6 AD DE 40     LDA $40DE
40B9 8D 08 D4     STA $D408
40BC 4C D9 40     JMP $40D9
40BF AD DC 40     LDA $40DC
40C2 8D 12 D4     STA $D412
40C5 A9 80        LDA #$80
40C7 8D 13 D4     STA $D413
40CA 8D 14 D4     STA $D414
40CD AD DD 40     LDA $40DD
40D0 8D 0E D4     STA $D40E
40D3 AD DE 40     LDA $40DE
40D6 8D 0F D4     STA $D40F
40D9 60           RTS
.
.
.
.
.:40DA 00 00 00 00 00 11 21 41
.:40E2 81 00 BE 00 00 00 F8 00
.
```

28. Envelope

This routine is similair to Sound (above) but it allows you to set the attack, decay, sustain and release as well.

Attack, decay, sustain and release are all betwen 0 and 15.

The syntax is SYS 16384, voice, volume, waveform, frequency, attack, decay, sustain, release.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                    .OPT P,OO
30:     4000                    *=   $4000
                          ;
                          ;
                          ;ENVELOPE FUNCTION
                          ;
                          ;SYNTAX
                          ;
                          ;SYS16384,VOICE,VOLUME,
                          ;WAVE,FREQ,A,D,S,R
120:    4000 20 24 41             JSR  GETPARAM
130:    4003 A5 15                LDA  $15
140:    4005 D0 6D                BNE  IQERR
150:    4007 A5 14                LDA  $14
160:    4009 8D 2E 41             STA  VOICE
170:    400C 20 24 41             JSR  GETPARAM
180:    400F A5 15                LDA  $15
190:    4011 D0 61                BNE  IQERR
200:    4013 A5 14                LDA  $14
210:    4015 8D 2F 41             STA  VOLUME
220:    4018 20 24 41             JSR  GETPARAM
230:    401B A5 15                LDA  $15
240:    401D D0 55                BNE  IQERR
```

```
250:   401F A5 14          LDA  $14
260:   4021 8D 30 41       STA  WAVE
270:   4024 20 24 41       JSR  GETPARAM
280:   4027 A5 14          LDA  $14
290:   4029 8D 31 41       STA  FREQ
300:   402C A5 15          LDA  $15
310:   402E 8D 32 41       STA  FREQ+1
320:   4031 20 24 41       JSR  GETPARAM
330:   4034 A5 15          LDA  $15
340:   4036 D0 3C          BNE  IQERR
350:   4038 A5 14          LDA  $14
360:   403A C9 10          CMP  #16
370:   403C B0 36          BCS  IQERR
380:   403E 8D 33 41       STA  ATTACK
390:   4041 20 24 41       JSR  GETPARAM
400:   4044 A5 15          LDA  $15
410:   4046 D0 2C          BNE  IQERR
420:   4048 A5 14          LDA  $14
430:   404A C9 10          CMP  #16
440:   404C B0 26          BCS  IQERR
450:   404E 8D 34 41       STA  DECAY
                           |
470:   4051 20 24 41       JSR  GETPARAM
480:   4054 A5 15          LDA  $15
490:   4056 D0 1C          BNE  IQERR
500:   4058 A5 14          LDA  $14
510:   405A C9 10          CMP  #16
520:   405C B0 16          BCS  IQERR
530:   405E 8D 35 41       STA  SUSTAIN
                           |
550:   4061 20 24 41       JSR  GETPARAM
560:   4064 A5 15          LDA  $15
570:   4066 D0 0C          BNE  IQERR
580:   4068 A5 14          LDA  $14
590:   406A C9 10          CMP  #16
600:   406C B0 06          BCS  IQERR
610:   406E 8D 36 41       STA  RELEASE
                           |
630:   4071 4C 77 40       JMP  DO
                           |
650:   4074 4C 48 B2 IQERR JMP  $B248
```

```
                              ;
670:    4077 AD 2F 41 D0      LDA  VOLUME
680:    407A C9 10            CMP  #16
690:    407C B0 F6            BCS  IQERR
700:    407E 8D 18 D4         STA  54296
                              ;
                              ;CALCULATE ADSR
                              ;
740:    4081 AD 34 41         LDA  DECAY
750:    4084 4A               LSR  A
760:    4085 4A               LSR  A
770:    4086 4A               LSR  A
780:    4087 4A               LSR  A
790:    4088 18               CLC
800:    4089 6D 33 41         ADC  ATTACK
810:    408C 8D 37 41         STA  AD
                              ;
830:    408F AD 36 41         LDA  RELEASE
840:    4092 4A               LSR  A
850:    4093 4A               LSR  A
860:    4094 4A               LSR  A
870:    4095 4A               LSR  A
880:    4096 18               CLC
890:    4097 6D 35 41         ADC  SUSTAIN
900:    409A 8D 38 41         STA  SR
                              ;
920:    409D A2 00            LDX  #0
930:    409F AD 30 41         LDA  WAVE
940:    40A2 DD 39 41 LOOP    CMP  WAVETABLE,X
950:    40A5 F0 08            BEQ  MORE
960:    40A7 E8               INX
960:    40A8 E0 04            CPX  #4
970:    40AA D0 F6            BNE  LOOP
980:    40AC 4C 48 B2 IQERR1  JMP  $B248 ;IQERR
                              ;
1000:   40AF AD 2E 41 MORE    LDA  VOICE
1010:   40B2 F0 F8            BEQ  IQERR1
1020:   40B4 C9 04            CMP  #4
1030:   40B6 B0 F4            BCS  IQERR1
                              ;
1050:   40B8 C9 01            CMP  #1
```

```
1060:   40BA F0 07              BEQ   VOICE1
1070:   40BC C9 02              CMP   #2
1080:   40BE F0 24              BEQ   VOICE2
1090:   40C0 4C 05 41           JMP   VOICE3
                                ;
                                ;
1120:   40C3 AD 30 41 VOICE1    LDA   WAVE
1130:   40C6 8D 04 D4           STA   54276
1140:   40C9 AD 37 41           LDA   AD
1150:   40CC 8D 05 D4           STA   54277
1160:   40CF AD 38 41           LDA   SR
1170:   40D2 8D 06 D4           STA   54278
1180:   40D5 AD 31 41           LDA   FREQ
1190:   40D8 8D 00 D4           STA   54272
1200:   40DB AD 32 41           LDA   FREQ+1
1210:   40DE 8D 01 D4           STA   54273
1220:   40E1 4C 23 41           JMP   FINISH
                                ;
1240:   40E4 AD 30 41 VOICE2    LDA   WAVE
1250:   40E7 8D 0B D4           STA   54283
1260:   40EA AD 37 41           LDA   AD
1270:   40ED 8D 0C D4           STA   54284
1280:   40F0 AD 38 41           LDA   SR
1290:   40F3 8D 0D D4           STA   54285
1300:   40F6 AD 31 41           LDA   FREQ
1310:   40F9 8D 07 D4           STA   54279
1320:   40FC AD 32 41           LDA   FREQ+1
1330:   40FF 8D 08 D4           STA   54280
1340:   4102 4C 23 41           JMP   FINISH
                                ;
1360:   4105 AD 30 41 VOICE3    LDA   WAVE
1370:   4108 8D 12 D4           STA   54290
1380:   410B AD 37 41           LDA   AD
1390:   410E 8D 13 D4           STA   54291
1400:   4111 AD 38 41           LDA   SR
1410:   4114 8D 14 D4           STA   54292
1420:   4117 AD 31 41           LDA   FREQ
1430:   411A 8D 0E D4           STA   54286
1440:   411D AD 32 41           LDA   FREQ+1
1450:   4120 8D 0F D4           STA   54287
                                ;
```

```
                          ;
1480:   4123 60        FINISH   RTS
1490:   4124 20 FD AE  GETPARAM JSR  $AEFD
1500:   4127 20 8A AD           JSR  $AD8A
1510:   412A 20 F7 B7           JSR  $B7F7
1520:   412D 60                 RTS
1530:   412E 00        VOICE    .BYT 0
1540:   412F 00        VOLUME   .BYT 0
1550:   4130 00        WAVE     .BYT 0
1560:   4131 00 00     FREQ     .WORD0
1570:   4133 00        ATTACK   .BYT 0
1580:   4134 00        DECAY    .BYT 0
1590:   4135 00        SUSTAIN  .BYT 0
1600:   4136 00        RELEASE  .BYT 0
1610:   4137 00        AD       .BYT 0
1620:   4138 00        SR       .BYT 0
1630:   4139 11 21 41 WAVETABLE.BYT 17,33,65,129
]4000-413D

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
4000 20 24 41     JSR $4124
4003 A5 15        LDA $15
4005 D0 6D        BNE $4074
4007 A5 14        LDA $14
4009 8D 2E 41     STA $412E
400C 20 24 41     JSR $4124
400F A5 15        LDA $15
4011 D0 61        BNE $4074
4013 A5 14        LDA $14
4015 8D 2F 41     STA $412F
4018 20 24 41     JSR $4124
```

```
401B A5 15      LDA $15
401D D0 55      BNE $4074
401F A5 14      LDA $14
4021 8D 30 41   STA $4130
4024 20 24 41   JSR $4124
4027 A5 14      LDA $14
4029 8D 31 41   STA $4131
402C A5 15      LDA $15
402E 8D 32 41   STA $4132
4031 20 24 41   JSR $4124
4034 A5 15      LDA $15
4036 D0 3C      BNE $4074
4038 A5 14      LDA $14
403A C9 10      CMP #$10
403C B0 36      BCS $4074
403E 8D 33 41   STA $4133
4041 20 24 41   JSR $4124
4044 A5 15      LDA $15
4046 D0 2C      BNE $4074
4048 A5 14      LDA $14
404A C9 10      CMP #$10
404C B0 26      BCS $4074
404E 8D 34 41   STA $4134
4051 20 24 41   JSR $4124
4054 A5 15      LDA $15
4056 D0 1C      BNE $4074
4058 A5 14      LDA $14
405A C9 10      CMP #$10
405C B0 16      BCS $4074
405E 8D 35 41   STA $4135
4061 20 24 41   JSR $4124
4064 A5 15      LDA $15
4066 D0 0C      BNE $4074
4068 A5 14      LDA $14
406A C9 10      CMP #$10
406C B0 06      BCS $4074
406E 8D 36 41   STA $4136
4071 4C 77 40   JMP $4077
4074 4C 48 B2   JMP $B248
4077 AD 2F 41   LDA $412F
407A C9 10      CMP #$10
```

```
407C B0 F6       BCS $4074
407E 8D 18 D4    STA $D418
4081 AD 34 41    LDA $4134
4084 4A          LSR
4085 4A          LSR
4086 4A          LSR
4087 4A          LSR
4088 18          CLC
4089 6D 33 41    ADC $4133
408C 8D 37 41    STA $4137
408F AD 36 41    LDA $4136
4092 4A          LSR
4093 4A          LSR
4094 4A          LSR
4095 4A          LSR
4096 18          CLC
4097 6D 35 41    ADC $4135
409A 8D 38 41    STA $4138
409D A2 00       LDX #$00
409F AD 30 41    LDA $4130
40A2 DD 39 41    CMP $4139,X
40A5 F0 08       BEQ $40AF
40A7 E8          INX
40A8 E0 04       CPX #$04
40AA D0 F6       BNE $40A2
40AC 4C 48 B2    JMP $B248
40AF AD 2E 41    LDA $412E
40B2 F0 F8       BEQ $40AC
40B4 C9 04       CMP #$04
40B6 B0 F4       BCS $40AC
40B8 C9 01       CMP #$01
40BA F0 07       BEQ $40C3
40BC C9 02       CMP #$02
40BE F0 24       BEQ $40E4
40C0 4C 05 41    JMP $4105
40C3 AD 30 41    LDA $4130
40C6 8D 04 D4    STA $D404
40C9 AD 37 41    LDA $4137
40CC 8D 05 D4    STA $D405
40CF AD 38 41    LDA $4138
40D2 8D 06 D4    STA $D406
```

```
40D5 AD 31 41     LDA $4131
40D8 8D 00 D4     STA $D400
40DB AD 32 41     LDA $4132
40DE 8D 01 D4     STA $D401
40E1 4C 23 41     JMP $4123
40E4 AD 30 41     LDA $4130
40E7 8D 0B D4     STA $D40B
40EA AD 37 41     LDA $4137
40ED 8D 0C D4     STA $D40C
40F0 AD 38 41     LDA $4138
40F3 8D 0D D4     STA $D40D
40F6 AD 31 41     LDA $4131
40F9 8D 07 D4     STA $D407
40FC AD 32 41     LDA $4132
40FF 8D 08 D4     STA $D408
4102 4C 23 41     JMP $4123
4105 AD 30 41     LDA $4130
4108 8D 12 D4     STA $D412
410B AD 37 41     LDA $4137
410E 8D 13 D4     STA $D413
4111 AD 38 41     LDA $4138
4114 8D 14 D4     STA $D414
4117 AD 31 41     LDA $4131
411A 8D 0E D4     STA $D40E
411D AD 32 41     LDA $4132
4120 8D 0F D4     STA $D40F
4123 60           RTS
4124 20 FD AE     JSR $AEFD
4127 20 8A AD     JSR $AD8A
412A 20 F7 B7     JSR $B7F7
412D 60           RTS
.

.
.:412E 00 00 00 00 00 00 00 00
.:4136 00 00 00 11 21 41 81 04
.
```

29. DIR

This routine allows you to read the disk directory (of either or both drives on a dual drive (not two 1541s)). It does not disturb the program in memory.

The syntax is SYS 16384,drive

where drive is 0 or 1, or 2 if both drives are to be read.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     3FFD                        .OPT P,00
30:     3FFD                        *=   16381
40:     3FFD            FNLENGTH =   $B7
50:     3FFD            SECADR   =   $B9
60:     3FFD            DEVNUM   =   $BA
70:     3FFD            FNADD    =   $BB
80:     3FFD            FNLEN    =   $FD
90:     3FFD            TEMP     =   $FB
100:    3FFD            ST       =   $90
110:    3FFD            SENDFNAM =   $F3D5
120:    3FFD            CLOSEFIL =   $F642
130:    3FFD            SENDSEC  =   $FF96
140:    3FFD            IECTALK  =   $FFB4
150:    3FFD            IECINP   =   $FFA5
160:    3FFD            LINENO   =   $BDCD
170:    3FFD            PRINT    =   $FFD2
180:    3FFD            CR       =   13
                         ;
200:    3FFD 4C 48 B2   IQERR    JMP  $B248
                         ;DIR   SYNTAX SYS 16384
220:    4000 20 FD AE            JSR  $AEFD
230:    4003 20 9E B7            JSR  $B79E
240:    4006 8A                  TXA
```

```
250:   4007 C9 03          CMP  #3
260:   4009 B0 F2          BCS  IQERR
270:   400B C9 00          CMP  #0
270:   400D F0 0F          BEQ  ZERO
280:   400F C9 01          CMP  #1
290:   4011 D0 16          BNE  BOTH
300:   4013 A9 31          LDA  #"1"
310:   4015 85 FC          STA  $FC
320:   4017 A9 02          LDA  #2
330:   4019 85 FD          STA  FNLEN
340:   401B 4C 2D 40       JMP  DIR
                           ;
360:   401E                ZERO =  *
370:   401E A9 30          LDA  #"0"
380:   4020 85 FC          STA  $FC
390:   4022 A9 02          LDA  #2
400:   4024 85 FD          STA  FNLEN
410:   4026 4C 2D 40       JMP  DIR
420:   4029 A9 01          BOTH LDA  #1
430:   402B 85 FD          STA  FNLEN
                           ;
450:   402D A9 00          DIR  LDA  #0
460:   402F 85 90          STA  ST
470:   4031 A9 24          LDA  #"$
480:   4033 85 FB          STA  TEMP
490:   4035 A9 FB          LDA  #<TEMP
500:   4037 85 BB          STA  FNADD
510:   4039 A9 00          LDA  #>TEMP
520:   403B 85 BC          STA  FNADD+1
530:   403D A5 FD          LDA  FNLEN
540:   403F 85 B7          STA  FNLENGTH
550:   4041 A9 08          LDA  #8
560:   4043 85 BA          STA  DEVNUM
570:   4045 A9 60          LDA  #$60
580:   4047 85 B9          STA  SECADR
590:   4049 20 D5 F3       JSR  SENDFNAM
600:   404C A5 BA          LDA  DEVNUM
610:   404E 20 B4 FF       JSR  IECTALK
620:   4051 A5 B9          LDA  SECADR
630:   4053 20 96 FF       JSR  SENDSEC
640:   4056 A4 90          LDY  ST
```

```
650:    4058 D0 3D              BNE  DLIST4
660:    405A A0 06              LDY  #6
670:    405C 84 FB     DLIST1   STY  TEMP
680:    405E 20 A5 FF           JSR  IECINP
690:    4061 A6 FC              LDX  TEMP+1
700:    4063 85 FC              STA  TEMP+1
710:    4065 A4 90              LDY  ST
720:    4067 D0 2E              BNE  DLIST4
730:    4069 A4 FB              LDY  TEMP
740:    406B 88                 DEY
750:    406C D0 EE              BNE  DLIST1
760:    406E A4 FC              LDY  TEMP+1
770:    4070 20 CD BD           JSR  LINENO
780:    4073 A9 20              LDA  #$20
790:    4075 20 D2 FF           JSR  PRINT
800:    4078 20 A5 FF  DLIST3   JSR  IECINP
810:    407B A6 90              LDX  ST
820:    407D D0 18              BNE  DLIST4
830:    407F AA                 TAX
840:    4080 F0 06              BEQ  DLIST2
850:    4082 20 D2 FF           JSR  PRINT
860:    4085 4C 78 40           JMP  DLIST3
870:    4088 A9 0D     DLIST2   LDA  #CR
880:    408A 20 D2 FF           JSR  PRINT
890:    408D A5 C5              LDA  $C5
900:    408F C9 3F              CMP  #63
900:    4091 F0 04              BEQ  DLIST4
910:    4093 A0 04              LDY  #4
920:    4095 D0 C5              BNE  DLIST1
930:    4097 20 42 F6  DLIST4   JSR  CLOSEFIL
940:    409A 60                 RTS
]3FFD-409B

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
4000 20 FD AE     JSR $AEFD
4003 20 9E B7     JSR $B79E
4006 8A           TXA
4007 C9 03        CMP #$03
4009 B0 F2        BCS $3FFD
400B C9 00        CMP #$00
400D F0 0F        BEQ $401E
400F C9 01        CMP #$01
4011 D0 16        BNE $4029
4013 A9 31        LDA #$31
4015 85 FC        STA $FC
4017 A9 02        LDA #$02
4019 85 FD        STA $FD
401B 4C 2D 40     JMP $402D
401E A9 30        LDA #$30
4020 85 FC        STA $FC
4022 A9 02        LDA #$02
4024 85 FD        STA $FD
4026 4C 2D 40     JMP $402D
4029 A9 01        LDA #$01
402B 85 FD        STA $FD
402D A9 00        LDA #$00
402F 85 90        STA $90
4031 A9 24        LDA #$24
4033 85 FB        STA $FB
4035 A9 FB        LDA #$FB
4037 85 BB        STA $BB
4039 A9 00        LDA #$00
403B 85 BC        STA $BC
403D A5 FD        LDA $FD
403F 85 B7        STA $B7
4041 A9 08        LDA #$08
4043 85 BA        STA $BA
4045 A9 60        LDA #$60
4047 85 B9        STA $B9
4049 20 D5 F3     JSR $F3D5
404C A5 BA        LDA $BA
```

```
404E 20 B4 FF     JSR $FFB4
4051 A5 B9        LDA $B9
4053 20 96 FF     JSR $FF96
4056 A4 90        LDY $90
4058 D0 3D        BNE $4097
405A A0 06        LDY #$06
405C 84 FB        STY $FB
405E 20 A5 FF     JSR $FFA5
4061 A6 FC        LDX $FC
4063 85 FC        STA $FC
4065 A4 90        LDY $90
4067 D0 2E        BNE $4097
4069 A4 FB        LDY $FB
406B 88           DEY
406C D0 EE        BNE $405C
406E A4 FC        LDY $FC
4070 20 CD BD     JSR $BDCD
4073 A9 20        LDA #$20
4075 20 D2 FF     JSR $FFD2
4078 20 A5 FF     JSR $FFA5
407B A6 90        LDX $90
407D D0 18        BNE $4097
407F AA           TAX
4080 F0 06        BEQ $4088
4082 20 D2 FF     JSR $FFD2
4085 4C 78 40     JMP $4078
4088 A9 0D        LDA #$0D
408A 20 D2 FF     JSR $FFD2
408D A5 C5        LDA $C5
408F C9 3F        CMP #$3F
4091 F0 04        BEQ $4097
4093 A0 04        LDY #$04
4095 D0 C5        BNE $405C
4097 20 42 F6     JSR $F642
409A 60           RTS
.
```

30. MSAVE

The following routine allows you save any specified area of memory. You specify the filename, the device, the secondary address, the start address and the finishing address + 1.

The syntax is as follows:

SYS 16384,"name",device,1,start,finish + 1

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                        .OPT P,OO
30:     4000                        *=   $4000
                                ;
50:     4000 20 FD AE               JSR  $AEFD
60:     4003 20 D4 E1               JSR  $E1D4
70:     4006 20 FD AE               JSR  $AEFD
80:     4009 20 8A AD               JSR  $AD8A
90:     400C 20 F7 B7               JSR  $B7F7
100:    400F A5 14                  LDA  $14
110:    4011 48                     PHA
120:    4012 A5 15                  LDA  $15
130:    4014 48                     PHA
140:    4015 20 FD AE               JSR  $AEFD
150:    4018 20 8A AD               JSR  $AD8A
160:    401B 20 F7 B7               JSR  $B7F7
170:    401E A6 14                  LDX  $14
180:    4020 A4 15                  LDY  $15
190:    4022 68                     PLA
200:    4023 85 FC                  STA  $FC
210:    4025 68                     PLA
220:    4026 85 FB                  STA  $FB
```

```
230:    4028 A9 FB              LDA  #$FB
240:    402A 4C 5F E1           JMP  $E15F
]4000-402D

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
.
4000 20 FD AE    JSR $AEFD
4003 20 D4 E1    JSR $E1D4
4006 20 FD AE    JSR $AEFD
4009 20 8A AD    JSR $AD8A
400C 20 F7 B7    JSR $B7F7
400F A5 14       LDA $14
4011 48          PHA
4012 A5 15       LDA $15
4014 48          PHA
4015 20 FD AE    JSR $AEFD
4018 20 8A AD    JSR $AD8A
401B 20 F7 B7    JSR $B7F7
401E A6 14       LDX $14
4020 A4 15       LDY $15
4022 68          PLA
4023 85 FC       STA $FC
4025 68          PLA
4026 85 FB       STA $FB
4028 A9 FB       LDA #$FB
402A 4C 5F E1    JMP $E15F
.
```

31. MLOAD/MVERIFY

The following routine allows you to load or verify to or from a specified area of memory. The load enables you to load into any area of memory, whether it was saved from that area or not. The verify allows you to verify a specific area of memory.

The syntax for MLOAD is as follows:

SYS 16394,"name",device,1,start address

The syntax for MVERIFY is as follows:

SYS 16384,"name",device,1,start

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                          .OPT P,00
30:     4000                          *=   $4000
40:     4000 20 FD AE MVERIFY         JSR  $AEFD
50:     4003 A9 01                    LDA  #1
60:     4005 85 0A                    STA  $A
70:     4007 4C 11 40                 JMP  LO
80:     400A 20 FD AE MLOAD           JSR  $AEFD
90:     400D A9 00                    LDA  #0
100:    400F 85 0A                    STA  $A
110:    4011 20 D4 E1 LO              JSR  $E1D4
120:    4014 20 FD AE                 JSR  $AEFD
130:    4017 20 8A AD                 JSR  $AD8A
140:    401A 20 F7 B7                 JSR  $B7F7
150:    401D A5 0A                    LDA  $A
160:    401F A6 14                    LDX  $14
170:    4021 A4 15                    LDY  $15
180:    4023 4C 75 E1                 JMP  $E175
]4000-4026

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
4000 20 FD AE     JSR $AEFD
4003 A9 01        LDA #$01
4005 85 0A        STA $0A
4007 4C 11 40     JMP $4011
400A 20 FD AE     JSR $AEFD
400D A9 00        LDA #$00
400F 85 0A        STA $0A
4011 20 D4 E1     JSR $E1D4
4014 20 FD AE     JSR $AEFD
4017 20 8A AD     JSR $AD8A
401A 20 F7 B7     JSR $B7F7
401D A5 0A        LDA $0A
401F A6 14        LDX $14
4021 A4 15        LDY $15
4023 4C 75 E1     JMP $E175
.
```

32. Disk

This routine allows you to send a command to the command channel of the disk drive, e.g. initialise or format.

It replaces the following in Basic:

OPEN15,8,15,"COMMAND"

The syntax is as follows:

SYS 16384,"command"

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                        .OPT P,OO
30:     4000                        *=   $4000
                          ; SYNTAX SYS16384,
                          ; "COMMAND"
60:     4000              CLOSE     =    $FFC3
70:     4000              OPEN      =    $FFC0
80:     4000              GETNAME   =    $E257
90:     4000              NEXTQ     =    $E206
100:    4000              SETFNA    =    $FFBD
110:    4000              SETFPA    =    $FFBA
120:    4000              GIVERR    =    $E0F9
                           ;
140:    4000 20 FD AE               JSR  $AEFD
150:    4003 A9 0F                  LDA  #15
160:    4005 20 C3 FF               JSR  CLOSE
170:    4008 20 16 40               JSR  GETFPAR
180:    400B 20 C0 FF               JSR  OPEN
190:    400E B0 1A                  BCS  ERROR
200:    4010 A9 0F                  LDA  #15
210:    4012 20 C3 FF               JSR  CLOSE
```

```
220:    4015 60                    RTS

                          ;
240:    4016 A9 00     GETFPAR  LDA  #0
250:    4018 20 BD FF           JSR  SETFNA
260:    401B A9 0F              LDA  #15
270:    401D A8                 TAY
280:    401E A2 08              LDX  #8
290:    4020 20 BA FF           JSR  SETFPA
300:    4023 20 06 E2           JSR  NEXTQ
310:    4026 20 57 E2           JSR  GETNAME
320:    4029 60                 RTS
330:    402A 4C F9 E0 ERROR     JMP  GIVERR
]4000-402D

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
4000 20 FD AE     JSR $AEFD
4003 A9 0F        LDA #$0F
4005 20 C3 FF     JSR $FFC3
4008 20 16 40     JSR $4016
400B 20 C0 FF     JSR $FFC0
400E B0 1A        BCS $402A
4010 A9 0F        LDA #$0F
4012 20 C3 FF     JSR $FFC3
4015 60           RTS
4016 A9 00        LDA #$00
4018 20 BD FF     JSR $FFBD
401B A9 0F        LDA #$0F
401D A8           TAY
401E A2 08        LDX #$08
4020 20 BA FF     JSR $FFBA
4023 20 06 E2     JSR $E206
4026 20 57 E2     JSR $E257
4029 60           RTS
402A 4C F9 E0     JMP $E0F9
.
```

33. DERROR

This routine allows you to read the disk error channel in direct mode or during a program.

It replaces the following BASIC program:

```
10 OPEN15,8,15
20 INPUT # 15,A$,B$,C$,D$,E$
30 PRINT A$;B$;C$;D$;E$
40 CLOSE15
```

The syntax is SYS 16384

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                        .OPT P,00
30:     4000                        *=   $4000
40:     4000            ST          =    $90
50:     4000            DEVNUM      =    $BA
60:     4000            SECADR      =    $B9
70:     4000            IECTALK     =    $FFB4
80:     4000            SENDSEC     =    $FF96
90:     4000            IECINP      =    $FFA5
100:    4000            PRINT       =    $FFD2
110:    4000            UNTALK      =    $FFAB
                         ;
                        ;DERROR COMMAND
                         ;
150:    4000 A9 00                  LDA  #0
160:    4002 85 90                  STA  ST
170:    4004 A9 08                  LDA  #8
180:    4006 85 BA                  STA  DEVNUM
190:    4008 20 B4 FF               JSR  IECTALK
200:    400B A9 6F                  LDA  #$6F
```

```
210:    400D 85 B9              STA  SECADR
220:    400F 20 96 FF           JSR  SENDSEC
230:    4012 A4 90     LOOP     LDY  ST
240:    4014 D0 0A              BNE  DERR4
250:    4016 20 A5 FF           JSR  IECINP
260:    4019 20 D2 FF           JSR  PRINT
270:    401C C9 0D              CMP  #13
280:    401E D0 F2              BNE  LOOP
290:    4020 20 AB FF  DERR4    JSR  UNTALK
300:    4023 60                 RTS
]4000-4024

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 01 F6
.
4000 A9 00        LDA #$00
4002 85 90        STA $90
4004 A9 08        LDA #$08
4006 85 BA        STA $BA
4008 20 B4 FF     JSR $FFB4
400B A9 6F        LDA #$6F
400D 85 B9        STA $B9
400F 20 96 FF     JSR $FF96
4012 A4 90        LDY $90
4014 D0 0A        BNE $4020
4016 20 A5 FF     JSR $FFA5
4019 20 D2 FF     JSR $FFD2
401C C9 0D        CMP #$0D
401E D0 F2        BNE $4012
4020 20 AB FF     JSR $FFAB
4023 60           RTS
.
```

34. Scroll message

This routine allows a message to be scrolled across the screen independently of anything else. This could be useful during the introduction to a game, for example.

The text to be scrolled across can be any length from 1 character onwards. The text must end with a $FF (255) byte to tell the routine to start from the beginning again.

Three parameters are required by the routine: the start location of the text in memory, the rate of scrolling and the colour of the text. If for example you wanted one new letter to appear on the screen once every sixth of a second then the rate would be 10 (as 10/60 is one sixth).

The syntax is as follows:

SYS 16384,start of text,rate,colour

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                        .OPT P,OO
30:     4000                        *=   $4000

                                ;
50:     4000 20 FD AE               JSR  $AEFD

60:     4003 20 8A AD               JSR  $AD8A

70:     4006 20 F7 B7               JSR  $B7F7

                                ;
90:     4009 A5 14                  LDA  $14
100:    400B 85 FB                  STA  $FB
```

```
100:    400D 8D 96 40           STA  TEMPF
B
110:    4010 A5 15              LDA  $15
120:    4012 85 FC              STA  $FC
120:    4014 8D 97 40           STA  TEMPF
C
                          ;
140:    4017 20 FD AE           JSR  $AEFD

150:    401A 20 9E B7           JSR  $B79E

160:    401D 8A                 TXA
170:    401E 8D 95 40           STA  TEMP
180:    4021 8D 94 40           STA  COUNT
ER
190:    4024 20 FD AE           JSR  $AEFD

200:    4027 20 9E B7           JSR  $B79E

210:    402A 8E 98 40           STX  COLOU
R
                          ;
230:    402D 78                 SEI
240:    402E A9 3A              LDA  #<MAI
N
250:    4030 8D 14 03           STA  788
260:    4033 A9 40              LDA  #>MAI
N
270:    4035 8D 15 03           STA  789
280:    4038 58                 CLI
290:    4039 60                 RTS
                          ;
                          ;
320:    403A CE 94 40 MAIN      DEC  COUNT
ER
330:    403D D0 38              BNE  FINIS
H
                          ;
350:    403F AD 95 40           LDA  TEMP
360:    4042 8D 94 40           STA  COUNT
ER
```

```
370:    4045 A2 00              LDX  #0
380:    4047 BD 99 07 LOOP      LDA  1945,
X
390:    404A 9D 98 07           STA  1944,
X
400:    404D BD 99 DB           LDA  1945+
54272,X
410:    4050 9D 98 DB           STA  1944+
54272,X
420:    4053 E8                 INX
430:    4054 E0 27              CPX  #39
440:    4056 D0 EF              BNE  LOOP
                          ;
460:    4058 A0 00              LDY  #0
470:    405A B1 FB              LDA  ($FB)
,Y
480:    405C C9 3F              CMP  #63
481:    405E B0 03              BCS  SUBTR

482:    4060 4C 66 40           JMP  PUTON

483:    4063 38         SUBTR   SEC
484:    4064 E9 40              SBC  #64
500:    4066 8D BF 07 PUTON     STA  1983
510:    4069 20 7A 40           JSR  INCRE
MENT
520:    406C A5 FC              LDA  $FC
530:    406E 18                 CLC
540:    406F 69 D4              ADC  #212
550:    4071 AD 98 40           LDA  COLOU
R
560:    4074 8D BF DB           STA  1983+
54272
                          ;
580:    4077 4C 31 EA FINISH    JMP  $EA31

590:    407A E6 FB     INCREMENTINC  $FB
600:    407C D0 02              BNE  CHECK

610:    407E E6 FC              INC  $FC
                          ;
```

```
630:    4080 A0 00     CHECK    LDY  #0
640:    4082 B1 FB              LDA  ($FB)
,Y
650:    4084 C9 FF              CMP  #$FF
660:    4086 F0 01              BEQ  RESET

670:    4088 60                 RTS
680:    4089 AD 96 40 RESET     LDA  TEMPF
B
690:    408C 85 FB              STA  $FB
700:    408E AD 97 40           LDA  TEMPF
C
710:    4091 85 FC              STA  $FC
720:    4093 60                 RTS
730:    4094 00        COUNTER  .BYT 0
740:    4095 00        TEMP     .BYT 0
750:    4096 00        TEMPFB   .BYT 0
760:    4097 00        TEMPFC   .BYT 0
770:    4098 00        COLOUR   .BYT 0
780:    4099 48 45 4C           .ASC "HELL
O I AM A CBM 64 MICRO-"
790:    40B3 43 4F 4D           .ASC "COMP
UTER AND I AM 64 "
800:    40C8 FF                 .BYT $FF
]4000-40C9
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 40 F6
.
4000 20 FD AE    JSR $AEFD
4003 20 8A AD    JSR $AD8A
4006 20 F7 B7    JSR $B7F7
4009 A5 14       LDA $14
400B 85 FB       STA $FB
400D 8D 96 40    STA $4096
4010 A5 15       LDA $15
4012 85 FC       STA $FC
```

```
4014 8D 97 40     STA $4097
4017 20 FD AE     JSR $AEFD
401A 20 9E B7     JSR $B79E
401D 8A           TXA
401E 8D 95 40     STA $4095
4021 8D 94 40     STA $4094
4024 20 FD AE     JSR $AEFD
4027 20 9E B7     JSR $B79E
402A 8E 98 40     STX $4098
402D 78           SEI
402E A9 3A        LDA #$3A
4030 8D 14 03     STA $0314
4033 A9 40        LDA #$40
4035 8D 15 03     STA $0315
4038 58           CLI
4039 60           RTS
403A CE 94 40     DEC $4094
403D D0 38        BNE $4077
403F AD 95 40     LDA $4095
4042 8D 94 40     STA $4094
4045 A2 00        LDX #$00
4047 BD 99 07     LDA $0799,X
404A 9D 98 07     STA $0798,X
404D BD 99 DB     LDA $DB99,X
4050 9D 98 DB     STA $DB98,X
4053 E8           INX
4054 E0 27        CPX #$27
4056 D0 EF        BNE $4047
4058 A0 00        LDY #$00
405A B1 FB        LDA ($FB),Y
405C C9 3F        CMP #$3F
405E B0 03        BCS $4063
4060 4C 66 40     JMP $4066
4063 38           SEC
4064 E9 40        SBC #$40
4066 8D BF 07     STA $07BF
4069 20 7A 40     JSR $407A
406C A5 FC        LDA $FC
406E 18           CLC
406F 69 D4        ADC #$D4
4071 AD 98 40     LDA $4098
```

```
4074 8D BF DB     STA $DBBF
4077 4C 31 EA     JMP $EA31
407A E6 FB        INC $FB
407C D0 02        BNE $4080
407E E6 FC        INC $FC
4080 A0 00        LDY #$00
4082 B1 FB        LDA ($FB),Y
4084 C9 FF        CMP #$FF
4086 F0 01        BEQ $4089
4088 60           RTS
4089 AD 96 40     LDA $4096
408C 85 FB        STA $FB
408E AD 97 40     LDA $4097
4091 85 FC        STA $FC
4093 60           RTS
.


.
.:4094 00 00 00 00 00 48 45 4C
.:409C 4C 4F 20 49 20 41 4D 20
.:40A4 41 20 43 42 4D 20 36 34
.:40AC 20 4D 49 43 52 4F 2D 43
.:40B4 4F 4D 50 55 54 45 52 20
.:40BC 41 4E 44 20 49 20 41 4D
.:40C4 20 36 34 20 FF AD 37 41
.
```

35. Flash screen

This routine allows you to flash the screen colour from one colour to another at a specified rate.

The syntax is as follows:

SYS 16384,colour1,colour2,rate

where colour1 is the first colour, colour2 is the second and rate is the number of 60ths of a second between flashes, e.g. 10 is 1/6 second. Setting the rate to 0 switches off the flash.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                    .OPT P,OO
30:     4000                    *=   $4000
                          ; SYNTAX
                          ; SYSFLASH,COLOUR1,
                          ; COLOUR2,NO OF
                          ; CHANGES A SECOND
50:     4000 20 FD AE           JSR  $AEFD
70:     4003 20 8A AD           JSR  $AD8A
80:     4006 20 F7 B7           JSR  $B7F7
90:     4009 A5 15              LDA  $15
90:     400B F0 03              BEQ  MORE
90:     400D 4C 48 B2           JMP  $B248
100:    4010 A5 14      MORE    LDA  $14
101:    4012 8D 8E 40           STA  TEMP
102:    4015 20 FD AE           JSR  $AEFD
110:    4018 20 8A AD           JSR  $AD8A
120:    401B 20 F7 B7           JSR  $B7F7
130:    401E A5 15              LDA  $15
```

```
140:    4020 F0 03          BEQ  MORE1
150:    4022 4C 48 B2       JMP  $B248
160:    4025 A5 14    MORE1 LDA  $14
170:    4027 8D 8F 40       STA  TEMP+1
180:    402A 20 FD AE       JSR  $AEFD
190:    402D 20 8A AD       JSR  $AD8A
200:    4030 20 F7 B7       JSR  $B7F7
210:    4033 A5 15          LDA  $15
220:    4035 F0 03          BEQ  MORE2
230:    4037 4C 48 B2       JMP  $B248
240:    403A A5 14    MORE2 LDA  $14
240:    403C F0 43          BEQ  RESET
250:    403E 8D 90 40       STA  TEMP+2
250:    4041 78             SEI
260:    4042 A9 54          LDA  #<MAIN
270:    4044 8D 14 03       STA  788
280:    4047 A9 40          LDA  #>MAIN
290:    4049 8D 15 03       STA  789
300:    404C 58             CLI
310:    404D AD 90 40       LDA  TEMP+2
310:    4050 8D 91 40       STA  TEMP+3
320:    4053 60             RTS
330:    4054          MAIN  =    *
340:    4054 CE 91 40       DEC  TEMP+3
350:    4057 D0 25          BNE  FINISH
360:    4059 AD 21 D0       LDA  53281
360:    405C 29 0F          AND  #15
370:    405E CD 8F 40       CMP  TEMP+1
380:    4061 F0 0F          BEQ  D00
390:    4063 AD 8F 40       LDA  TEMP+1
400:    4066 8D 21 D0       STA  53281
400:    4069 AD 90 40       LDA  TEMP+2
400:    406C 8D 91 40       STA  TEMP+3
410:    406F 4C 7E 40       JMP  FINISH
420:    4072 AD 8E 40 D00   LDA  TEMP
430:    4075 8D 21 D0       STA  53281
440:    4078 AD 90 40       LDA  TEMP+2
440:    407B 8D 91 40       STA  TEMP+3
450:    407E 4C 31 EA FINISH JMP $EA31
460:    4081 78       RESET SEI
470:    4082 A9 31          LDA  #49
```

```
480:    4084 8D 14 03           STA   788
490:    4087 A9 EA              LDA   #234
500:    4089 8D 15 03           STA   789
510:    408C 58                 CLI
520:    408D 60                 RTS
530:    408E           TEMP     =     *
]4000-408E

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 40 F6
.
4000 20 FD AE     JSR $AEFD
4003 20 8A AD     JSR $AD8A
4006 20 F7 B7     JSR $B7F7
4009 A5 15        LDA $15
400B F0 03        BEQ $4010
400D 4C 48 B2     JMP $B248
4010 A5 14        LDA $14
4012 8D 8E 40     STA $408E
4015 20 FD AE     JSR $AEFD
4018 20 8A AD     JSR $AD8A
401B 20 F7 B7     JSR $B7F7
401E A5 15        LDA $15
4020 F0 03        BEQ $4025
4022 4C 48 B2     JMP $B248
4025 A5 14        LDA $14
4027 8D 8F 40     STA $408F
402A 20 FD AE     JSR $AEFD
402D 20 8A AD     JSR $AD8A
4030 20 F7 B7     JSR $B7F7
4033 A5 15        LDA $15
4035 F0 03        BEQ $403A
4037 4C 48 B2     JMP $B248
```

```
403A A5 14      LDA $14
403C F0 43      BEQ $4081
403E 8D 90 40   STA $4090
4041 78         SEI
4042 A9 54      LDA #$54
4044 8D 14 03   STA $0314
4047 A9 40      LDA #$40
4049 8D 15 03   STA $0315
404C 58         CLI
404D AD 90 40   LDA $4090
4050 8D 91 40   STA $4091
4053 60         RTS
4054 CE 91 40   DEC $4091
4057 D0 25      BNE $407E
4059 AD 21 D0   LDA $D021
405C 29 0F      AND #$0F
405E CD 8F 40   CMP $408F
4061 F0 0F      BEQ $4072
4063 AD 8F 40   LDA $408F
4066 8D 21 D0   STA $D021
4069 AD 90 40   LDA $4090
406C 8D 91 40   STA $4091
406F 4C 7E 40   JMP $407E
4072 AD 8E 40   LDA $408E
4075 8D 21 D0   STA $D021
4078 AD 90 40   LDA $4090
407B 8D 91 40   STA $4091
407E 4C 31 EA   JMP $EA31
4081 78         SEI
4082 A9 31      LDA #$31
4084 8D 14 03   STA $0314
4087 A9 EA      LDA #$EA
4089 8D 15 03   STA $0315
408C 58         CLI
408D 60         RTS
.
```

36. Flash border

This routine does the same as the flash screen routine except that the border is flashed.

The syntax is as follows:

SYS16384,colour1,colour2,rate

Setting the rate to 0 turns off the flash.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                    .OPT P,OO
30:     4000                    *=   $4000
                          ; SYNTAX
                          ; SYSFLASH,COLOUR1,
                          ; COLOUR2,NO OF
                          ; CHANGES A SECOND
50:     4000 20 FD AE           JSR  $AEFD
70:     4003 20 8A AD           JSR  $AD8A
80:     4006 20 F7 B7           JSR  $B7F7
90:     4009 A5 15              LDA  $15
90:     400B F0 03              BEQ  MORE
90:     400D 4C 48 B2           JMP  $B248
100:    4010 A5 14      MORE    LDA  $14
101:    4012 8D 8E 40           STA  TEMP
102:    4015 20 FD AE           JSR  $AEFD
110:    4018 20 8A AD           JSR  $AD8A
120:    401B 20 F7 B7           JSR  $B7F7
130:    401E A5 15              LDA  $15
140:    4020 F0 03              BEQ  MORE1
150:    4022 4C 48 B2           JMP  $B248
```

```
160:   4025 A5 14     MORE1    LDA  $14
170:   4027 8D 8F 40            STA  TEMP+1
180:   402A 20 FD AE            JSR  $AEFD
190:   402D 20 8A AD            JSR  $AD8A
200:   4030 20 F7 B7            JSR  $B7F7
210:   4033 A5 15               LDA  $15
220:   4035 F0 03               BEQ  MORE2
230:   4037 4C 48 B2            JMP  $B248
240:   403A A5 14     MORE2     LDA  $14
240:   403C F0 43               BEQ  RESET
250:   403E 8D 90 40            STA  TEMP+2
250:   4041 78                  SEI
260:   4042 A9 54               LDA  #<MAIN
270:   4044 8D 14 03            STA  788
280:   4047 A9 40               LDA  #>MAIN
290:   4049 8D 15 03            STA  789
300:   404C 58                  CLI
310:   404D AD 90 40            LDA  TEMP+2
310:   4050 8D 91 40            STA  TEMP+3
320:   4053 60                  RTS
330:   4054           MAIN      =    *
340:   4054 CE 91 40            DEC  TEMP+3
350:   4057 D0 25               BNE  FINISH
360:   4059 AD 20 D0            LDA  53280
360:   405C 29 0F               AND  #15
370:   405E CD 8F 40            CMP  TEMP+1
380:   4061 F0 0F               BEQ  DO0
390:   4063 AD 8F 40            LDA  TEMP+1
400:   4066 8D 20 D0            STA  53280
400:   4069 AD 90 40            LDA  TEMP+2
400:   406C 8D 91 40            STA  TEMP+3
410:   406F 4C 7E 40            JMP  FINISH
420:   4072 AD 8E 40 DO0        LDA  TEMP
430:   4075 8D 20 D0            STA  53280
440:   4078 AD 90 40            LDA  TEMP+2
440:   407B 8D 91 40            STA  TEMP+3
450:   407E 4C 31 EA FINISH     JMP  $EA31
460:   4081 78       RESET      SEI
470:   4082 A9 31               LDA  #49
480:   4084 8D 14 03            STA  788
490:   4087 A9 EA               LDA  #234
```

```
500:    4089 8D 15 03           STA  789
510:    408C 58                 CLI
520:    408D 60                 RTS
530:    408E           TEMP     =    *
]4000-408E

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 40 F6
.
4000 20 FD AE     JSR $AEFD
4003 20 8A AD     JSR $AD8A
4006 20 F7 B7     JSR $B7F7
4009 A5 15        LDA $15
400B F0 03        BEQ $4010
400D 4C 48 B2     JMP $B248
4010 A5 14        LDA $14
4012 8D 8E 40     STA $408E
4015 20 FD AE     JSR $AEFD
4018 20 8A AD     JSR $AD8A
401B 20 F7 B7     JSR $B7F7
401E A5 15        LDA $15
4020 F0 03        BEQ $4025
4022 4C 48 B2     JMP $B248
4025 A5 14        LDA $14
4027 8D 8F 40     STA $408F
402A 20 FD AE     JSR $AEFD
402D 20 8A AD     JSR $AD8A
4030 20 F7 B7     JSR $B7F7
4033 A5 15        LDA $15
4035 F0 03        BEQ $403A
4037 4C 48 B2     JMP $B248
403A A5 14        LDA $14
403C F0 43        BEQ $4081
403E 8D 90 40     STA $4090
```

```
4041 78          SEI
4042 A9 54       LDA #$54
4044 8D 14 03    STA $0314
4047 A9 40       LDA #$40
4049 8D 15 03    STA $0315
404C 58          CLI
404D AD 90 40    LDA $4090
4050 8D 91 40    STA $4091
4053 60          RTS
4054 CE 91 40    DEC $4091
4057 D0 25       BNE $407E
4059 AD 20 D0    LDA $D020
405C 29 0F       AND #$0F
405E CD 8F 40    CMP $408F
4061 F0 0F       BEQ $4072
4063 AD 8F 40    LDA $408F
4066 8D 20 D0    STA $D020
4069 AD 90 40    LDA $4090
406C 8D 91 40    STA $4091
406F 4C 7E 40    JMP $407E
4072 AD 8E 40    LDA $408E
4075 8D 20 D0    STA $D020
4078 AD 90 40    LDA $4090
407B 8D 91 40    STA $4091
407E 4C 31 EA    JMP $EA31
4081 78          SEI
4082 A9 31       LDA #$31
4084 8D 14 03    STA $0314
4087 A9 EA       LDA #$EA
4089 8D 15 03    STA $0315
408C 58          CLI
408D 60          RTS
.
```

37. Flash characters

This routine flashes (or reverses) all the characters on the screen at a specified rate.

The syntax is as follows:

SYS 16384,rate

Setting the rate to 0 turns off the flash.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                        .OPT P,00
30:     4000                        *=   $4000

                            ;
                            ;SYNTAX FLASH 1 OR
                            ;0
                            ;
70:     4000 20 FD AE               JSR  $AEFD

80:     4003 20 8A AD               JSR  $AD8A

90:     4006 20 F7 B7               JSR  $B7F7

100:    4009 A5 14                  LDA  $14
110:    400B F0 13                  BEQ  RESET

120:    400D 8D 67 40               STA  TEMP
120:    4010 8D 68 40               STA  TEMP+
1
130:    4013 78                     SEI
140:    4014 A9 2D                  LDA  #<MAI
N
```

```
150:    4016 8D 14 03           STA  788
160:    4019 A9 40              LDA  #>MAI
N
170:    401B 8D 15 03           STA  789
180:    401E 58                 CLI
190:    401F 60                 RTS
200:    4020 78         RESET   SEI
220:    4021 A9 31              LDA  #49
230:    4023 8D 14 03           STA  788
240:    4026 A9 EA              LDA  #234
250:    4028 8D 15 03           STA  789
260:    402B 58                 CLI
270:    402C 60                 RTS
290:    402D CE 68 40 MAIN      DEC  TEMP+
1
300:    4030 F0 03              BEQ  MORE
310:    4032 4C 31 EA           JMP  $EA31

320:    4035 AD 67 40 MORE      LDA  TEMP
330:    4038 8D 68 40           STA  TEMP+
1
                        ;
                        ;INVERT CHARACTERS

                        ;
370:    403B A2 00              LDX  #0
380:    403D BD 00 04 LOOP      LDA  1024,
X
390:    4040 18                 CLC
400:    4041 69 80              ADC  #128
410:    4043 9D 00 04           STA  1024,
X
                        ;
430:    4046 BD FF 04           LDA  1024+
255,X
440:    4049 18                 CLC
450:    404A 69 80              ADC  #128
460:    404C 9D FF 04           STA  1024+
255,X
                        ;
480:    404F BD FE 05           LDA  1024+
```

```
255+255,X
490:    4052 18                 CLC
500:    4053 69 80              ADC  #128
510:    4055 9D FE 05           STA  1024+
255+255,X
                        ;
530:    4058 BD FD 06           LDA  1024+
255+255+255,X
540:    405B 18                 CLC
550:    405C 69 80              ADC  #128
560:    405E 9D FD 06           STA  1024+
255+255+255,X
570:    4061 E8                 INX
580:    4062 D0 D9              BNE  LOOP
590:    4064 4C 31 EA           JMP  $EA31

600:    4067          TEMP      =    *
]4000-4067

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 40 F6
.
4000 20 FD AE    JSR $AEFD
4003 20 8A AD    JSR $AD8A
4006 20 F7 B7    JSR $B7F7
4009 A5 14       LDA $14
400B F0 13       BEQ $4020
400D 8D 67 40    STA $4067
4010 8D 68 40    STA $4068
4013 78          SEI
4014 A9 2D       LDA #$2D
4016 8D 14 03    STA $0314
4019 A9 40       LDA #$40
401B 8D 15 03    STA $0315
401E 58          CLI
```

```
401F 60          RTS
4020 78          SEI
4021 A9 31       LDA #$31
4023 8D 14 03    STA $0314
4026 A9 EA       LDA #$EA
4028 8D 15 03    STA $0315
402B 58          CLI
402C 60          RTS
402D CE 68 40    DEC $4068
4030 F0 03       BEQ $4035
4032 4C 31 EA    JMP $EA31
4035 AD 67 40    LDA $4067
4038 8D 68 40    STA $4068
403B A2 00       LDX #$00
403D BD 00 04    LDA $0400,X
4040 18          CLC
4041 69 80       ADC #$80
4043 9D 00 04    STA $0400,X
4046 BD FF 04    LDA $04FF,X
4049 18          CLC
404A 69 80       ADC #$80
404C 9D FF 04    STA $04FF,X
404F BD FE 05    LDA $05FE,X
4052 18          CLC
4053 69 80       ADC #$80
4055 9D FE 05    STA $05FE,X
4058 BD FD 06    LDA $06FD,X
405B 18          CLC
405C 69 80       ADC #$80
405E 9D FD 06    STA $06FD,X
4061 E8          INX
4062 D0 D9       BNE $403D
4064 4C 31 EA    JMP $EA31
4067 20 D0 AD    JSR $ADD0
.
```

38. Flash colour

This routine flashes the colour of the characters between two specified colours at a specified rate.

The syntax is as follows:

SYS 16384,colour1,colour2,rate

A rate of zero turns off the flash.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                    .OPT P,OO
30:     4000                    *=    $4000

                        ;
                        ;SYNTAX
                        ; SYSFLASH,COLOUR1
                        ; ,COLOUR2,NO OF
                        ; CHANGES A SECOND

80:     4000 20 FD AE           JSR   $AEFD

90:     4003 20 8A AD           JSR   $AD8A

100:    4006 20 F7 B7           JSR   $B7F7

110:    4009 A5 15              LDA   $15
110:    400B F0 03              BEQ   MORE
110:    400D 4C 48 B2           JMP   $B248

120:    4010 A5 14      MORE    LDA   $14
130:    4012 8D A5 40           STA   TEMP
140:    4015 20 FD AE           JSR   $AEFD
```

```
150:    4018 20 8A AD           JSR  $AD8A

160:    401B 20 F7 B7           JSR  $B7F7

170:    401E A5 15              LDA  $15
180:    4020 F0 03              BEQ  MORE1

190:    4022 4C 48 B2           JMP  $B248

200:    4025 A5 14      MORE1   LDA  $14
210:    4027 8D A6 40           STA  TEMP+
1
220:    402A 20 FD AE           JSR  $AEFD

230:    402D 20 8A AD           JSR  $AD8A

240:    4030 20 F7 B7           JSR  $B7F7

250:    4033 A5 15              LDA  $15
260:    4035 F0 03              BEQ  MORE2

270:    4037 4C 48 B2           JMP  $B248

280:    403A A5 14      MORE2   LDA  $14
280:    403C F0 59              BEQ  RESET

290:    403E 8D A7 40           STA  TEMP+
2
290:    4041 78                 SEI
300:    4042 A9 54              LDA  #<MAI
N
310:    4044 8D 14 03           STA  788
320:    4047 A9 40              LDA  #>MAI
N
330:    4049 8D 15 03           STA  789
340:    404C 58                 CLI
350:    404D AD A7 40           LDA  TEMP+
2
350:    4050 8D A8 40           STA  TEMP+
3
360:    4053 60                 RTS
```

```
370:    4054             MAIN     =    *
380:    4054 CE A8 40             DEC  TEMP+
3
390:    4057 D0 29                BNE  FINIS
H
400:    4059 AD A4 40             LDA  STORE

410:    405C CD A6 40             CMP  TEMP+
1
420:    405F F0 12                BEQ  D00
                        ;
440:    4061 AD A6 40             LDA  TEMP+
1
450:    4064 8D A4 40             STA  STORE

460:    4067 20 85 40             JSR  FILL
470:    406A AD A7 40             LDA  TEMP+
2
480:    406D 8D A8 40             STA  TEMP+
3
490:    4070 4C 82 40             JMP  FINIS
H
                           ;
510:    4073 AD A5 40 D00         LDA  TEMP
520:    4076 8D A4 40             STA  STORE

530:    4079 20 85 40             JSR  FILL
540:    407C AD A7 40             LDA  TEMP+
2
550:    407F 8D A8 40             STA  TEMP+
3
                           ;
570:    4082 4C 31 EA FINISH      JMP  $EA31

                           ;
590:    4085 A2 00    FILL        LDX  #0
600:    4087 9D 00 D8 LOOP        STA  55296
,X
610:    408A 9D FF D8             STA  55296
+255,X
620:    408D 9D FE D9             STA  55296
```

```
+255+255,X
630:    4090 9D FD DA           STA  55296
+255+255+255,X
640:    4093 E8                 INX
650:    4094 D0 F1              BNE  LOOP
660:    4096 60                 RTS
                        ;
                        ;
690:    4097 78         RESET   SEI
700:    4098 A9 31              LDA  #49
710:    409A 8D 14 03           STA  788
720:    409D A9 EA              LDA  #234
730:    409F 8D 15 03           STA  789
740:    40A2 58                 CLI
750:    40A3 60                 RTS
760:    40A4 00         STORE   .BYT 0
770:    40A5            TEMP    =    *
14000-40A5

READY.
```

```
B*
   PC   SR AC XR YR SP
.;97FE 72 00 00 40 F6
.
4000 20 FD AE    JSR $AEFD
4003 20 8A AD    JSR $AD8A
4006 20 F7 B7    JSR $B7F7
4009 A5 15       LDA $15
400B F0 03       BEQ $4010
400D 4C 48 B2    JMP $B248
4010 A5 14       LDA $14
4012 8D A5 40    STA $40A5
4015 20 FD AE    JSR $AEFD
4018 20 8A AD    JSR $AD8A
401B 20 F7 B7    JSR $B7F7
401E A5 15       LDA $15
4020 F0 03       BEQ $4025
```

```
4022 4C 48 B2     JMP $B248
4025 A5 14        LDA $14
4027 8D A6 40     STA $40A6
402A 20 FD AE     JSR $AEFD
402D 20 8A AD     JSR $AD8A
4030 20 F7 B7     JSR $B7F7
4033 A5 15        LDA $15
4035 F0 03        BEQ $403A
4037 4C 48 B2     JMP $B248
403A A5 14        LDA $14
403C F0 59        BEQ $4097
403E 8D A7 40     STA $40A7
4041 78           SEI
4042 A9 54        LDA #$54
4044 8D 14 03     STA $0314
4047 A9 40        LDA #$40
4049 8D 15 03     STA $0315
404C 58           CLI
404D AD A7 40     LDA $40A7
4050 8D A8 40     STA $40A8
4053 60           RTS
4054 CE A8 40     DEC $40A8
4057 D0 29        BNE $4082
4059 AD A4 40     LDA $40A4
405C CD A6 40     CMP $40A6
405F F0 12        BEQ $4073
4061 AD A6 40     LDA $40A6
4064 8D A4 40     STA $40A4
4067 20 85 40     JSR $4085
406A AD A7 40     LDA $40A7
406D 8D A8 40     STA $40A8
4070 4C 82 40     JMP $4082
4073 AD A5 40     LDA $40A5
4076 8D A4 40     STA $40A4
4079 20 85 40     JSR $4085
407C AD A7 40     LDA $40A7
407F 8D A8 40     STA $40A8
4082 4C 31 EA     JMP $EA31
4085 A2 00        LDX #$00
4087 9D 00 D8     STA $D800,X
408A 9D FF D8     STA $D8FF,X
```

```
408D 9D FE D9     STA $D9FE,X
4090 9D FD DA     STA $DAFD,X
4093 E8           INX
4094 D0 F1        BNE $4087
4096 60           RTS
4097 78           SEI
4098 A9 31        LDA #$31
409A 8D 14 03     STA $0314
409D A9 EA        LDA #$EA
409F 8D 15 03     STA $0315
40A2 58           CLI
40A3 60           RTS
40A4 00           BRK
.
```

39. Print at

This routine allows you to print at any position on the screen without using lots of cursor controls.

The syntax is as follows:

SYS960,X,Y,"text"

X is the column to start at and is between 0 and 39. Y is the row to start at and is between 0 and 24. The text can be text in quotes, strings, numbers, variables or any other legal print statement.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     03C0                        .OPT P,OO
30:     03C0                        *=   960
                                ;
                                ;PRINT AT ROUTINE
60:     03C0 20 FD AE               JSR  $AEFD
70:     03C3 20 9E B7               JSR  $B79E
80:     03C6 8A                     TXA
90:     03C7 48                     PHA
100:    03C8 20 FD AE               JSR  $AEFD
110:    03CB 20 9E B7               JSR  $B79E
120:    03CE 8A                     TXA
130:    03CF A8                     TAY
140:    03D0 68                     PLA
150:    03D1 AA                     TAX
160:    03D2 18                     CLC
170:    03D3 20 F0 FF               JSR  $FFF0
180:    03D6 20 FD AE               JSR  $AEFD
190:    03D9 4C A0 AA               JMP  $AAA0
```

```
200:   03DC 00                    BRK
103C0-03DD

READY.
```

```
B*
   PC  SR AC XR YR SP
.;97FE 72 00 00 40 F6
.
03C0 20 FD AE    JSR $AEFD
03C3 20 9E B7    JSR $B79E
03C6 8A          TXA
03C7 48          PHA
03C8 20 FD AE    JSR $AEFD
03CB 20 9E B7    JSR $B79E
03CE 8A          TXA
03CF A8          TAY
03D0 68          PLA
03D1 AA          TAX
03D2 18          CLC
03D3 20 F0 FF    JSR $FFF0
03D6 20 FD AE    JSR $AEFD
03D9 4C A0 AA    JMP $AAA0
03DC 00          BRK
.
```

40. Split screen

This routine sets up a raster scan that allows the text and high res screen to coexist at the same time. You can specify where the cut is to take place and whether text or high res is at the top.

The syntax is as follows:

SYS 16384, line for change,option

where line is the line down the screen (the same as the Y coordinates for plot) and option is 1 for the text to be at the top and 0 for the text to be at the bottom. If line has the value 0 then the raster is switched off. The line number must be in the range 50 to 249.

```
PAL (C)1979 BRAD TEMPLETON
2
20:     4000                    .OPT P,OO
30:     4000                    *=   $4000
                              ;
                              ;RASTER TO ALLOW SPLIT
                              ;SCREENS
                              ;SYNTAX
                              ;
                              ;SYS16384,CHANGE,1=
                              ;TEXT/0=HIRES
110:    4000 20 FD AE           JSR  $AEFD
120:    4003 20 8A AD           JSR  $AD8A
130:    4006 20 F7 B7           JSR  $B7F7
                              ;
150:    4009 A5 15              LDA  $15
160:    400B D0 2B              BNE  IQERR
170:    400D A5 14              LDA  $14
180:    400F D0 03              BNE  MOR
180:    4011 4C A5 40           JMP  RESET
```

```
190:   4014 C9 31     MOR       CMP   #49
200:   4016 90 20               BCC   IQERR
210:   4018 C9 FA               CMP   #250
220:   401A B0 1C               BCS   IQERR
230:   401C 8D FE 40            STA   TEMP
                        ;
250:   401F 20 FD AE            JSR   $AEFD
260:   4022 20 8A AD            JSR   $AD8A
270:   4025 20 F7 B7            JSR   $B7F7
280:   4028 A5 15               LDA   $15
290:   402A D0 0C               BNE   IQERR
300:   402C A5 14               LDA   $14
310:   402E C9 02               CMP   #2
320:   4030 B0 06               BCS   IQERR
330:   4032 8D FF 40            STA   TEMP+1
340:   4035 4C 3B 40            JMP   MORE
350:   4038 4C 48 B2  IQERR     JMP   $B248
360:   403B AD FE 40  MORE      LDA   TEMP
370:   403E 8D F8 40            STA   RASTER
380:   4041 AD FF 40            LDA   TEMP+1
390:   4044 C9 01               CMP   #1
400:   4046 F0 17               BEQ   TEXTTOP
410:   4048 A9 08               LDA   #8
410:   404A A2 15               LDX   #21
420:   404C 8D FA 40            STA   TEXT
420:   404F 8E FB 40            STX   TEXT+1
430:   4052 A9 3B               LDA   #59
430:   4054 A2 1B               LDX   #27
440:   4056 8D FC 40            STA   HIRES
440:   4059 8E FD 40            STX   HIRES+1
450:   405C 4C 73 40            JMP   SETUP
460:   405F A9 15     TEXTTOP   LDA   #21
460:   4061 A2 08               LDX   #8
470:   4063 8D FA 40            STA   TEXT
470:   4066 8E FB 40            STX   TEXT+1
480:   4069 A9 1B               LDA   #27
480:   406B A2 3B               LDX   #59
490:   406D 8D FC 40            STA   HIRES
490:   4070 8E FD 40            STX   HIRES+1
                        ;
510:   4073           SETUP     =     *
```

```
520:   4073 78                    SEI
530:   4074 A9 7F                 LDA  #$7F
540:   4076 8D 0D DC              STA  $DC0D
550:   4079 A9 01                 LDA  #$01
560:   407B 8D 1A D0              STA  $D01A
570:   407E A9 02                 LDA  #$02
580:   4080 85 FB                 STA  $FB
590:   4082 AD F8 40              LDA  RASTER
600:   4085 8D 12 D0              STA  $D012
610:   4088 A9 18                 LDA  #$18
620:   408A 8D 11 D0              STA  $D011
630:   408D AD 14 03              LDA  $0314
640:   4090 8D F6 40              STA  FIN-2
650:   4093 AD 15 03              LDA  $0315
660:   4096 8D F7 40              STA  FIN-1
670:   4099 A9 C6                 LDA  #<MAIN
680:   409B 8D 14 03              STA  788
690:   409E A9 40                 LDA  #>MAIN
700:   40A0 8D 15 03              STA  789
710:   40A3 58                    CLI
720:   40A4 60                    RTS
730:   40A5 78           RESET    SEI
730:   40A6 A9 31                 LDA  #49
740:   40A8 8D 14 03              STA  788
750:   40AB A9 EA                 LDA  #234
750:   40AD 8D 15 03              STA  789
760:   40B0 A9 15                 LDA  #21
760:   40B2 8D 18 D0              STA  53272
770:   40B5 A9 1B                 LDA  #27
770:   40B7 8D 11 D0              STA  53265
780:   40BA A9 00                 LDA  #0
780:   40BC 8D 1A D0              STA  $D01A
790:   40BF A9 80                 LDA  #128
790:   40C1 8D 0D DC              STA  56333
800:   40C4 58                    CLI
800:   40C5 60                    RTS
810:   40C6 AD 19 D0     MAIN     LDA  $D019
820:   40C9 8D 19 D0              STA  $D019
830:   40CC 29 01                 AND  #$01
840:   40CE F0 1F                 BEQ  LOOP
850:   40D0 C6 FB                 DEC  $FB
```

```
860:    40D2 10 04              BPL  LOOP9
870:    40D4 A9 01              LDA  #$01
880:    40D6 85 FB              STA  $FB
890:    40D8 A6 FB     LOOP9    LDX  $FB
900:    40DA BD F8 40           LDA  RASTER,X
910:    40DD 8D 12 D0           STA  $D012
920:    40E0 BD FA 40           LDA  TEXT,X
930:    40E3 8D 18 D0           STA  53272
940:    40E6 BD FC 40           LDA  HIRES,X
950:    40E9 8D 11 D0           STA  $D011
960:    40EC 8A                 TXA
970:    40ED F0 06              BEQ  LOOP1
980:    40EF 68        LOOP     PLA
990:    40F0 A8                 TAY
1000:   40F1 68                 PLA
1010:   40F2 AA                 TAX
1020:   40F3 68                 PLA
1030:   40F4 40                 RTI
1040:   40F5 4C 31 EA  LOOP1    JMP  $EA31
1040:   40F8           FIN      =    *
1050:   40F8 96 00     RASTER   .BYT 150,0
1060:   40FA 08 15     TEXT     .BYT 8,21
1070:   40FC 3B 1B     HIRES    .BYT 59,27
1080:   40FE 00 00     TEMP     .WORD0
]4000-4100

READY.
```

```
.
4000 20 FD AE     JSR $AEFD
4003 20 8A AD     JSR $AD8A
4006 20 F7 B7     JSR $B7F7
4009 A5 15        LDA $15
400B D0 2B        BNE $4038
400D A5 14        LDA $14
400F D0 03        BNE $4014
4011 4C A5 40     JMP $40A5
4014 C9 31        CMP #$31
```

```
4016 90 20      BCC $4038
4018 C9 FA      CMP #$FA
401A B0 1C      BCS $4038
401C 8D FE 40   STA $40FE
401F 20 FD AE   JSR $AEFD
4022 20 8A AD   JSR $AD8A
4025 20 F7 B7   JSR $B7F7
4028 A5 15      LDA $15
402A D0 0C      BNE $4038
402C A5 14      LDA $14
402E C9 02      CMP #$02
4030 B0 06      BCS $4038
4032 8D FF 40   STA $40FF
4035 4C 3B 40   JMP $403B
4038 4C 48 B2   JMP $B248
403B AD FE 40   LDA $40FE
403E 8D F8 40   STA $40F8
4041 AD FF 40   LDA $40FF
4044 C9 01      CMP #$01
4046 F0 17      BEQ $405F
4048 A9 08      LDA #$08
404A A2 15      LDX #$15
404C 8D FA 40   STA $40FA
404F 8E FB 40   STX $40FB
4052 A9 3B      LDA #$3B
4054 A2 1B      LDX #$1B
4056 8D FC 40   STA $40FC
4059 8E FD 40   STX $40FD
405C 4C 73 40   JMP $4073
405F A9 15      LDA #$15
4061 A2 08      LDX #$08
4063 8D FA 40   STA $40FA
4066 8E FB 40   STX $40FB
4069 A9 1B      LDA #$1B
406B A2 3B      LDX #$3B
406D 8D FC 40   STA $40FC
4070 8E FD 40   STX $40FD
4073 78         SEI
4074 A9 7F      LDA #$7F
4076 8D 0D DC   STA $DC0D
4079 A9 01      LDA #$01
```

```
407B 8D 1A D0    STA $D01A
407E A9 02       LDA #$02
4080 85 FB       STA $FB
4082 AD F8 40    LDA $40F8
4085 8D 12 D0    STA $D012
4088 A9 18       LDA #$18
408A 8D 11 D0    STA $D011
408D AD 14 03    LDA $0314
4090 8D F6 40    STA $40F6
4093 AD 15 03    LDA $0315
4096 8D F7 40    STA $40F7
4099 A9 C6       LDA #$C6
409B 8D 14 03    STA $0314
409E A9 40       LDA #$40
40A0 8D 15 03    STA $0315
40A3 58          CLI
40A4 60          RTS
40A5 78          SEI
40A6 A9 31       LDA #$31
40A8 8D 14 03    STA $0314
40AB A9 EA       LDA #$EA
40AD 8D 15 03    STA $0315
40B0 A9 15       LDA #$15
40B2 8D 18 D0    STA $D018
40B5 A9 1B       LDA #$1B
40B7 8D 11 D0    STA $D011
40BA A9 00       LDA #$00
40BC 8D 1A D0    STA $D01A
40BF A9 80       LDA #$80
40C1 8D 0D DC    STA $DC0D
40C4 58          CLI
40C5 60          RTS
40C6 AD 19 D0    LDA $D019
40C9 8D 19 D0    STA $D019
40CC 29 01       AND #$01
40CE F0 1F       BEQ $40EF
40D0 C6 FB       DEC $FB
40D2 10 04       BPL $40D8
40D4 A9 01       LDA #$01
40D6 85 FB       STA $FB
40D8 A6 FB       LDX $FB
```

```
40DA BD F8 40     LDA $40F8,X
40DD 8D 12 D0     STA $D012
40E0 BD FA 40     LDA $40FA,X
40E3 8D 18 D0     STA $D018
40E6 BD FC 40     LDA $40FC,X
40E9 8D 11 D0     STA $D011
40EC 8A           TXA
40ED F0 06        BEQ $40F5
40EF 68           PLA
40F0 A8           TAY
40F1 68           PLA
40F2 AA           TAX
40F3 68           PLA
40F4 40           RTI
40F5 4C 31 EA     JMP $EA31
.
.
.:40F8 96 00 08 15 3B 1B 00 00
.
```